University of Southampton Research Repository ePrints Soton

Copyright © and Moral Rights for this thesis are retained by the author and/or other copyright owners. A copy can be downloaded for personal non-commercial research or study, without prior permission or charge. This thesis cannot be reproduced or quoted extensively from without first obtaining permission in writing from the copyright holder/s. The content must not be changed in any way or sold commercially in any format or medium without the formal permission of the copyright holders.

When referring to this work, full bibliographic details including the author, title, awarding institution and date of the thesis must be given e.g.

AUTHOR (year of submission) "Full thesis title", University of Southampton, name of the University School or Department, PhD Thesis, pagination

UNIVERSITY OF SOUTHAMPTON

FACULTY OF ENGINEERING AND THE ENVIRONMENT

ENGINEERING SCIENCES

MECHATRONICS GROUP

**Maximum Power Point Tracking of a Small-Scale
Compressed Air Energy Storage System**

by

Vorrapath Kokaew

Thesis for the degree of Doctor of Philosophy

December 2016

UNIVERSITY OF SOUTHAMPTON

ABSTRACT

FACULTY OF ENGINEERING AND THE ENVIRONMENT

MECHATRONICS GROUP

Thesis for the degree of Doctor of Philosophy

MAXIMUM POWER POINT TRACKING OF A SMALL-SCALE COMPRESSED AIR ENERGY STORAGE SYSTEM

Vorrapath Kokaew

The thesis is concerned with a small-scale compressed air energy storage (SS-CAES) system. Although these systems have relatively low energy density, they offer advantages of low environmental impact and ease of maintenance.

The thesis focuses on solving a number of commonly known problems related to the perturb and observe (P&O) maximum power point tracking (MPPT) system for SS-CAES, including confusion under input power fluctuation conditions and operating point dither.

A test rig was designed and built to be used for validation of the theoretical work. The rig comprised an air motor driving a permanent magnet DC generator whose power output is controlled by a buck converter. A speed control system was designed and implemented using a dSPACE controller. This enabled fast convergence of MPPT.

Four MPPT systems were investigated. In the first system, the air motor characteristics were used to determine the operating speed corresponding to MPP for a given pressure. This was compared to a maximum *efficiency* point tracking (MEPT) system. Operating at the maximum *power* point resulted in 1% loss of efficiency compared to operating at the maximum efficiency point. But MPPT does not require an accurate model of the system that is needed for MEPT, which also requires more sensors.

The second system that was investigated uses a hybrid MPPT approach that did not require *a priori* knowledge system model. It used the rate of change of power output with respect to the duty cycle of the buck converter as well as the change in duty cycle to avoid confusion under input power fluctuations. It also used a fine speed step in the vicinity of the MPP and a coarse speed step when the operating point was far from the MPP. Both simulation and experimental results demonstrate the efficiency of this proposed system.

The third P&O MPPT system used a fuzzy logic approach which avoided confusion and eliminated operating point dither. This system was also implemented experimentally.

A speed control system improved the controllable speed-range by using a buck-boost converter instead. The last MPPT system employed a hybrid P&O and incremental inductance (INC) approach to avoid confusion and eliminate operating point dither. The simulation results validate the design.

Although the focus of the work is on SS-CAES, the results are generic in nature and could be applied to MPPT of other systems such as PV and wind turbine.

Table of Contents

Table of Contents	i
List of Tables	v
List of Figures.....	vii
DECLARATION OF AUTHORSHIP	xiii
Dedication	xv
Acknowledgements.....	xv
Abbreviations & Symbols.....	xvii
Chapter 1: Introduction.....	1
1.1 Statement of problems	1
1.2 Aims and objectives of the thesis.....	5
1.3 Thesis novel contributions	6
1.4 Thesis outline	6
Chapter 2: SS-CAES system and its speed regulation.....	9
2.1 SS-CAES system	9
2.2 Speed regulation.....	11
2.3 SS-CAES System model.....	14
2.3.1 Permanent magnet DC generator-buck converter models	14
2.3.2 A small signal model	15
2.4 Speed regulator controller.....	17
2.4.1 The inner-current loop	18
2.4.2 The outer-speed loop	21
2.5 Simulation results.....	25
2.6 Experimental setup.....	26
2.7 Experiment results	29
2.8 Summary	32
Chapter 3: MEP and MPP of SS-CAES.....	35
3.1 Maximum efficiency or power point of SS-CAES	35
3.2 The air motor model.....	36
3.3 Maximum efficiency point and maximum power point of SS-CAES system ..	36
3.3.1 Maximum efficiency point	36

3.3.2	Maximum power point	38
3.3.3	A comparison between the MPP and the MEP	39
3.4	The maximum point controller	40
3.5	Simulation results	41
3.6	Experimental setup	43
3.7	Experiment results	44
3.8	Summary.....	46
Chapter 4:	MPPT algorithm.....	47
4.1	Review of maximum power point tracking (MPPT)	47
4.2	Control system.....	49
4.3	Principle of maximum power point tracking (MPPT).....	50
4.4	MPPT algorithm confusion due to power disturbances	53
4.5	Correct search direction in MPPT algorithm.....	56
4.6	Steady state power loss estimation	61
4.7	Simulation results	63
4.8	Experimental results	64
4.9	Summary.....	68
Chapter 5:	MPPT-Fuzzy Logic Control	69
5.1	Review of variable step size MPPT techniques	69
5.2	Control system.....	70
5.3	MPPT-FLC of wrong judgment	71
5.4	The MPPT–FLC based on correct direction.....	76
5.5	Fuzzy rule	80
5.5.1	Fuzzy rule under constant power.....	80
5.5.2	Fuzzy rule in power disturbance	81
5.6	A vector–fuzzy logic method	84
5.7	Simulation results	87
5.7.1	MPPT-FLC based on correct direction results	87
5.7.2	Vector-fuzzy logic results	88
5.8	Experimental results	91
5.9	Summary.....	96

Chapter 6:	Improved SS-CAES using a buck-boost converter, a hybrid P&O and an incremental inductance INC-MPPT	99
6.1	Speed regulator for SS-CAES system.....	99
6.2	Power converter under duty cycle criteria conditions.....	99
6.3	Power converter under power fluctuation conditions	100
6.4	Control system	102
6.4.1	Small signal model of the overall system	103
6.4.2	PI controller	105
6.4.3	MPPT controller	108
6.5	Simulation results.....	110
6.6	Summary	115
Chapter 7:	Conclusion and future work	117
7.1	Conclusions.....	117
7.2	Future work.....	119
7.2.1	Improving shortcomings in an MPPT controller	119
7.2.2	Heat and power management.....	120
Appendices	121	
Appendix A	Air motor model.....	123
A.1	Air motor characteristics.....	123
A.2	Analysis of the air motor model under constant pressure.....	124
A.3	Analysis of the air motor model under variable pressure	125
A.4	Thermodynamic analysis of the air motor conversion efficiency.....	129
Appendix B	Small signal model of the PM DC generator and buck converter	133
Appendix C	Terminology of fuzzy logic approach.....	141
Appendix D	Simulation of SS-CAES system	143
D.1	Air motor model.....	143
D.2	SS-CAES system model	146
D.3	Controllers.....	147
D.3.1	Speed regulator controller.....	147
D.3.2	Cascade PI controllers in the Matlab script design.....	147
D.3.3	MEPT and MPPT controller	149
D.3.4	MPPT algorithm	150

D.3.5	MPPT fuzzy logic control	152
Appendix E	System parameter values	155
Appendix F	dSPACE model	157
F.1	Controllers and data acquisition of sensors	157
F.2	Data acquisitions	160
Bibliography.....		161

List of Tables

Table I The percentage of the steady state error of the air motor speed for the speed regulator .	30
Table II the direction results	58
Table III Fuzzy rule	80
Table IV Fuzzy rule for correcting the search direction	83
Table E.1 Air motor model parameters.....	155
Table E.2 Permanent magnet DC generator.....	155
Table E.3 Buck converter	156
Table E.4 Buck-boost converter.....	156

List of Figures

Figure 1.1 Advanced Adiabatic CAES plant [2].....	1
Figure 1.2 Thermal and compressed air storage technology for UPS [9]	2
Figure 1.3 Comparison energy density and power density [1,3]	3
Figure 1.4 Hydro-pneumatic and supercapacitors storage system [3,12]	4
Figure 1.5 Maximum efficiency and power point lines on the efficiency and power characteristics of the air motor.....	4
Figure 1.6 The experimental rig of the SS-CAES system	5
Figure 2.1 Configuration of the speed regulator of the SS-CAES system.....	13
Figure 2.2 Equivalent circuit of the discharge process with buck converter	14
Figure 2.3 Block diagram of the transfer function of PM-DC generator with buck converter under continuous mode	16
Figure 2.4 The block diagram of the speed regulator controller.....	17
Figure 2.5 The fast Fourier transform (FFT) of inductor current signal within low-pass filter...	19
Figure 2.6 The dynamic oscillation of inductor current signal in the different cut-off frequency of LP filters	19
Figure 2.7 The Bode plot design of open-loop transfer function of $G_{ip}(z)$ and $G_{ip}(z) G_{ci}(z) H_f(z)$	20
Figure 2.8 Root locus plot of the outer-speed loop controller	22
Figure 2.9 The actual speed signal and FFT of actual speed	23
Figure 2.10 Block diagram of outer-speed loop with unity feedback control.....	23
Figure 2.11 The Bode plot design of open-loop transfer function of speed $G_{ap}(z)$ and $G_{ap}(z) G_{co}(z)$	24
Figure 2.12 Simulation results of the speed, the torque and the power output in various speed command and constant pressure conditions.....	25
Figure 2.13 Simulation results of the speed, the torque and the power output under varying pressure conditions.....	26
Figure 2.14 An isolation of the SS-CAES and speed controller	27

Figure 2.15 Experimental rig for the SS-CAES system	28
Figure 2.16 Experimental results of the speed regulator through a low-pass filter, with a cut-off frequency ω_{cf} of 1 rad/s at a constant pressure of 6 bar	29
Figure 2.17 Experimental results of the speed regulator through a low-pass filter, with a cut-off frequency ω_{cf} of 10 rad/s at a constant pressure of 6 bar	30
Figure 2.18 Experimental results of the speed regulator through a low-pass filter, with a cut-off frequency ω_{cf} of 1 rad/s for pressure changes	31
Figure 2.19 Experimental results of the speed regulator through a low-pass filter, with a cut-off frequency ω_{cf} of 10 rad/s for pressure changes	31
Figure 3.1 Configuration of the proposed discharging process with MEPT/MPPT	35
Figure 3.2 Maximum efficiency line on the efficiency-speed-pressure characteristics of the air motor	37
Figure 3.3 Maximum power line on the power-speed-pressure characteristics of the air motor	39
Figure 3.4 Maximum efficiency point (MEP) and power point (MPP) lines on the air motor characteristic curves	40
Figure 3.5 The MEPT/MPPT controller	40
Figure 3.6 Simulation results of the proposed MEPT strategy under varying pressure conditions	41
Figure 3.7 Simulation results of the proposed MPPT strategy under varying pressure conditions	42
Figure 3.8 Simulation results of the system response under MPPT and MEPT strategies	43
Figure 3.9 An isolation of the SS-CAES and MEPT/MPPT with speed regulator controller	43
Figure 3.10 Response of the system under MPPT and MEPT strategies at constant inlet pressure of 6 bar	44
Figure 3.11 Experimental and theoretical maximum power and maximum efficiency operating lines	45
Figure 4.1 Configuration of the proposed discharging process with MPPT	49
Figure 4.2 Block diagram of MPPT-P&O algorithm system with speed reference control	50
Figure 4.3 Basic MPPT on air motor power and buck duty cycle versus speed curve	51
Figure 4.4 The slope of the output power of the air motor with respect to speed and duty cycle	52

Figure 4.5 The proposed MPPT of the air motor power and buck duty cycle versus speed.....	53
Figure 4.6 Experiment results obtained when using $\Delta P_{am}/\Delta \omega_r$ MPPT-algorithm showing direction confusion during pressure transients.....	55
Figure 4.7 Speed responses to power disturbances during a sampling interval.....	57
Figure 4.8 The MPP tracking with fluctuating air motor power.....	58
Figure 4.9 MPPT Flow chart	60
Figure 4.10 The power reduction versus speed ratio	62
Figure 4. 11 Simulation results of the SS-CAES system under varying pressure conditions.....	63
Figure 4.12 Experimental results obtained using the proposed MPPT-algorithm	66
Figure 4.13 Comparison of the average speed curve between simulation and experimental results against pressure changes	67
Figure 4.14 The percentage of power reduction between simulation and experimental results against pressure changes	67
Figure 5.1 Configuration of the proposed discharging process with MPPT fuzzy logic	70
Figure 5.2 Block diagram of MPPT-FLC with speed reference control.....	71
Figure 5.3 The calculated speed reference of MPPT-FLC using the inputs of ΔP_{am} and $\Delta \omega_r$	71
Figure 5.4 The calculated reference speed of MPPT-FLC using the inputs of $\Delta P_{am}/\Delta \omega_r$ and $\Delta \omega_r$	72
Figure 5.5 Simulation results obtained when using the ΔP_{am} and $\Delta \omega_r$ into MPPT fuzzy logic control showing the direction confusion during pressure transient.....	73
Figure 5.6 Simulation results obtained when using the $\Delta P_{am}/\Delta \omega_r$ and $\Delta \omega_r$ into MPPT fuzzy logic control showing the direction confusion during pressure transient	74
Figure 5.7 Simulation results obtained when using the $\Delta P_{am}/\Delta \omega_r$ and $\Delta \omega_r$ into MPPT fuzzy logic control showing the wrong judgment during a small $\Delta \omega_r$	75
Figure 5.8 MPPT-FLC Flowchart.....	77
Figure 5.9 The corrected membership functions for (a) the input of change in air motor power (b) the input of change in duty cycle (c) the output variable step-size speed.....	79
Figure 5.10 Fuzzy logic control membership functions mapped onto the air motor power and duty cycle – speed curve	81

Figure 5.11 The MPP tracking with decreased air motor power	82
Figure 5.12 The MPP tracking with increased air motor power.....	82
Figure 5.13 The vector of speed output $\Delta\omega_r^*$ consequence under input power fluctuations conditions	84
Figure 5.14 The membership function of a vector-fuzzy for a) the input of ΔP^* b) the input of ΔD^* and c) the output of $\Delta\omega_r^*$	85
Figure 5.15 The data input management with a vector-fuzzy logic	86
Figure 5.16 Simulation results obtained using the MPPT-FLC.....	87
Figure 5.17 Simulation results obtained using the proposed vector-fuzzy logic	90
Figure 5.18 Experiment results obtained using the proposed FLC-MPPT	93
Figure 5.19 Experiment results obtained when using the proposed FLC-MPPT showing the improvements in transient and steady state for step pressure changes	94
Figure 5.20 MPPT-FLC experimental test under a ramp of pressure changes.....	94
Figure 5.21 Comparison of the average speed curve between simulation and experimental results against pressure changes.....	95
Figure 5.22 The percentage of power reduction between simulation and experimental results against pressure changes.....	95
Figure 6.1 Air motor power and duty cycle of buck, buck-boost and boost converters versus speed	100
Figure 6.2 Air motor power and duty cycle of buck and buck-boost converters versus speed under power fluctuation.....	101
Figure 6.3 Air motor power and duty cycle of boost and buck-boost converters versus speed under power fluctuation.....	102
Figure 6.4 The speed regulator with buck-boost converter for a SS-CAES system.....	103
Figure 6.5 Speed regulator with PI controller and the small-signal of SS-CAES system	105
Figure 6.6 Closed-loop system of SS-CAES	105
Figure 6.7 Root locus for a reference speed control utilizing a positive and negative gain K_p of the proportional controller	106

Figure 6.8 Bode plot design of the open-loop transfer function of the speed with the negative gain $G_{op}(z)$ and obtaining controller $G_{op}(z)^* G_{c\omega}(z)$	107
Figure 6.9 The hybrid P&O and INC –MPPT flowchart	109
Figure 6.10 SS-CAES system model in Matlab/Simulink	111
Figure 6.11 Simulation results obtained using the MPPT algorithm under input pressure changes from 6 bar to 2 bar and turn it to 6 bar	113
Figure 6.12 Efficiency of the air motor for using a) the hybrid P&O algorithm and b) the hybrid P&O and INC under high level pressure changes.....	114
Figure A.1 Block diagram of the pneumatic-to-mechanical energy conversion process.....	123
Figure A.2 Characteristics of the air motor LZB 14 AR034 (100W)	124
Figure A.3 Estimated functions $T_o(p_i)$ and $\omega_{ro}(p_i)$ from the boundary parameters	126
Figure A.4 Estimated function f_a from boundary parameters	126
Figure A.5 Model torque characteristics of air motor.....	127
Figure A.6 Model power characteristics of air motor	128
Figure A.7 Model air consumption characteristics of air motor	128
Figure B.1 DC generator with buck converter model under switch-mode on-off conditions....	133
Figure B.2 Inductor current waveform in heavy mode	134
Figure B.3 The small signal model of a constant-frequency buck converter with DC generator source in continuous mode.....	139
Figure D.1 Subsystem of air motor model.....	143
Figure D.2 Subsystem of air flow to speed block.....	144
Figure D.3 Subsystem of speed to torque/power output block	144
Figure D.4 Subsystem of boundary block adjustment	145
Figure D.5 Subsystem of air consumption.....	145
Figure D.6 Dialogue of air motor block.....	146
Figure D.7 SS-CAES system model	146
Figure D.8 Cascade PI controllers with speed command level of speed regulator	147

Figure D.9 MEPT/MPPT controllers with speed regulator	149
Figure D.10 Subsystem of the estimation of K_1	149
Figure D.11 Subsystem of the estimation of K_2	150
Figure D.12 MPPT-algorithm with speed regulator	150
Figure D.13 Data acquisition of MPPT-algorithm and limitation of the duty cycle	150
Figure D.14 MPPT-fuzzy logic controller with speed regulator	152
Figure D.15 Data acquisition of MPPT-FLC and limitation of the duty cycle.....	152
Figure D.16 Subsystem of the conventional MPPT-FLC when using the inputs of ΔP_{am} and $\Delta \omega_r$	152
Figure D.17 Subsystem of the conventional MPPT-FLC when using the inputs of $\Delta P_{am}/\Delta \omega_r$ and $\Delta \omega_r$	153
Figure D.18 Subsystem of the proposed MPPT-FLC.....	153
Figure D.19 Subsystem of the dP/dD	153
Figure D.20 Subsystem of the proposed vector-fuzzy logic.....	154
Figure F.1 The overall controllers and data acquisition of sensor.....	157
Figure F.2 Subsystem of PI controller	157
Figure F.3 Subsystem of MEPT/MPPT strategies block.....	158
Figure F.4 Subsystem of MPPT-algorithm block.....	158
Figure F.5 Subsystem of MPPT-FLC block	158
Figure F.6 MPPT-FLC	159
Figure F.7 The derivative air motor power over duty cycle change estimation	159
Figure F.8 The analog to digital converter of all sensors	160
Figure F.9 The subsystem of flow sensor estimation	160

DECLARATION OF AUTHORSHIP

I, VORRAPATH KOKAEW declare that this thesis entitled

MAXIMUM POWER POINT TRACKING OF A SMALL-SCALE COMPRESSED AIR ENERGY STORAGE SYSTEM

and the work presented in it are my own and have been generated by me as the result of my own original research. I confirm that:

1. This work was done wholly or mainly while in candidature for a research degree at this University;
2. Where any part of this thesis has previously been submitted for a degree or any other qualification at this University or any other institution, this has been clearly stated;
3. Where I have consulted the published work of others, this is always clearly attributed;
4. Where I have quoted from the work of others, the source is always given. With the exception of such quotations, this thesis is entirely my own work;
5. I have acknowledged all main sources of help;
6. Where the thesis is based on work done by myself jointly with others, I have made clear exactly what was done by others and what I have contributed myself;
7. Parts of this work have been published as: [please list references below]:

Maximum Power Point Tracking of a Small Scale Compressed Air Energy Storage System,
Transactions on Industrial Electronics, 2015

*Maximum Efficiency or Power Tracking of Stand-Alone Small Scale Compressed Air Energy
Storage System*, Energy Procedia, 2013.

A Hybrid Method for Maximum Power Tracking of a Small Scale CAES System, Processing of
CSNDSP14, 2014.

Simulation of a Solar Powered Air Compressor, Int. Conf. IEEEIC, 2011

Signed:

Date:

Dedication

To my family

Acknowledgements

Firstly I would like to thank the University of the Thai Chamber of Commerce (UTCC) who supported me with a full time PhD studentship. Professor Wanchai Rattanawong was a key figure who strongly supported my PhD journey. I would also like to thank Professor Vichai Sangkachantranonda for his lectures and for being an inspiration for my study of Engineering.

I would also like to express my gratitude to my first supervisor Dr Mohamed Moshrefi-Torbati who has provided me with much appreciated guidance and support. Similarly, my second supervisor Professor Suleiman M. Sharkh who has been very influential and another valuable source of knowledge and advice.

I owe a debt of gratitude to Mr. Tim Hartley and Mr. Brian Clark who set up my laboratory, facilitated the use of equipment and gave me useful advice for my experiment.

My family has been so supportive and understanding throughout this PhD. They are a constant source of both mental and physical support. My wife deserves massive thanks for devoting her time to look after the children. I would like to thank my children for their patience and tolerance with regard to all the lost school holidays they encountered. I would like to dedicate this PhD thesis to my lovely family.

Abbreviations & Symbols

ADC	Analog to Digital Converter
A-CAES	Adiabatic-Compressed Air Energy Storage
AIC	Absorbed injected current
CAES	Compressed Air Energy Storage
dc-dc	Direct current to direct current
DAC	Digital to Analog Converter
DPWM	Digital Pulse Width Modulator
EST	Energy Storage Technologies
FLC	Fuzzy Logic Control
I-CAES	Isothermal-Compressed Air Energy Storage
INC	Incremental conductance
MEP	Maximum Efficiency Point
MOSFET	Metal-oxide-semiconductor field-effect transistor
MPP	Maximum Power Point
MEPT	Maximum Efficiency Point Tracking
MF	Membership function
MPPT	Maximum Power Point Tracking
PHS	Pumped Hydroelectric Storage
PI	Proportional-Integral
PM	Permanent Magnet
P&O	Perturb and Observe
PV	Photovoltaics
PWM	Pulse Width Modulation
r.m.s.	Root mean square

SMES	Superconducting Magnetic Energy Storage
SSA	State-space averaging
SS-CAES	Small Scale Compressed Air Energy Storage
TES	Thermal energy store
UPS	Uninterruptable power supply
ZOH	Zero order hold
B_t	Total of viscous friction coefficients
C_o	Capacitance of the buck converter
c_p	Heat capacity at constant pressure
c_v	Heat capacity at constant volume
$D_{\min}$	Minimum of duty cycle in variable step-size area
$D_{\max}$	Maximum of duty cycle in variable step-size area
D	Duty cycle
D_o	Centre of duty cycle in variable step-size area
e	Derivative of the conversion efficiency of the air motor with respect to the speed change (error)
$E_{ag}(s)$	Transfer function of generator's electromotive force (EMF)
e_{ag}	Generator's electromotive force
f_s	Metal-oxide-semiconductor field-effect transistor (MOSFET) switching frequency
f_{sc}	Sampling frequency
$G_I(s)$	Transfer function of the generator's electromotive force (EMF) to inductor current
$G_2(s)$	Transfer function of the output voltage to inductor current
$G_3(s)$	Transfer function of the duty cycle to inductor current
$G_{ci}(s)$	Transfer function of inner loop controller
$G_{cw}(s)$	Transfer function of outer loop controller
$H_f(s)$	Transfer function of low-pass filter

I^*	Inductor current command
$I_{ag}(s)$	Transfer function of generator's armature current
i_{ag}	Generator's armature current
i_d	Diode current
$I_d(s)$	Transfer function of diode current
$I_L(s)$	Transfer function of inductor current
i_L	Inductor current
I_m	Minimum inductor current
i_o	Average output current
J_t	Total moments of inertia
K	Pure gain
K_e	Torque constant
K_I	Integral gain
K_m	Back EMF constant
K_P	Proportional gain
L	Inductance of the buck converter
L_{ag}	Inductance of the generator
L_t	Total inductance of inductance of the buck converter and inductance of the generator
M_v	Steady-state dc voltage transfer function of converter
N	Number of rules
Nr_{min}	Minimum speed
p_a	Atmospheric pressure
P_{am}	Power of the air motor
P_{fc}	Friction and copper losses
P_h	Power harvested

P_{mpp}	Available power for the maximum power point tracking at steady state
p_i	Inlet pressure
T	Time period of switching
T_{am}	Torque of air motor
T_{eg}	Electric torque
T_d	Time delay
T_o	Stall torque of the air motor
T_{sc}	Sampling period (or sampling interval) of the regulator controller
T_{sm}	Sampling period of the maximum power point tracking (MPPT) controller
r_{ag}	Generator armature resistance
R_L	Resistive load
V_a	Volume of air
V_{max}	Maximum volume of air
$V_o(s)$	Transfer function of voltage output
v_o	Voltage output of buck converter
α	The firing strength of AND operator
γ	Ratio of specific heats
λ	Speed ratio
η_c	Efficiency of the power converter
η_{am}	Efficiency of the air motor
σ	Rang of the air motor speed where the fine step size is used by perturb and observe
τ	Time constant
ω_{cf}	Cut-off frequency
ω_{com}	Speed command
ω_d	Speed demand

ω_{max}	Maximum speed in variable step-size area
ω_{min}	Minimum speed in variable step-size area
ω_{mpp}	Air motor speed at the maximum power point
ω_o	Centre speed in variable step-size area
ω_{op}	Optimal speed
ω_r	Air motor speed
ω_{re}	Difference speed between the optimal speed and the air motor speed at maximum power
ω_{ro}	Free speed
ω_{ref}	Air motor speed reference
ΔD	Change in duty cycle
ΔD^*	Per unit of change in duty cycle
ΔP^*	Per unit of change in air motor power for avoiding the division of small quantities
ΔP_{am}	Change in air motor power
$\Delta P_{am,max}$	Maximum change in air motor power
Δi_L	Inductor ripple current
Δv_o	Output ripple voltage
$\Delta \omega_c$	Step size in coarse-tuning area
$\Delta \omega_f$	Step size in fine-tuning area
$\Delta \omega_r$	Change in speed
$\Delta \omega_r^*$	Per unit of change in speed
$\Delta \omega_{max}$	Maximum change in speed

Chapter 1: Introduction

1.1 Statement of problems

Large scale compressed air energy storage (CAES) [1] has been used for many years for grid, load-levelling and frequency balancing. In these systems underground caves are usually used to store the compressed air. The air is preheated during the decompression process, before the turbine stage which drives a MW-size generator. In Figure 1.1, for example, the heat energy is extracted from the compression process and stored in the thermal energy storage (TES) during the off-peak (electrical in) and the compressed air enters a cavern. When energy is required by the grid at the on-peak (electrical out), the compressed air and the heat energy are recombined and expanded through a gas turbine, e.g., the Advanced Adiabatic CAES plant described in reference [2]. Such a CAES system provides higher storage efficiencies and lower CO₂ emissions.

Figure 1.1 Advanced Adiabatic CAES plant [2]

A small scale compressed air energy storage (SS-CAES) system [3,4,5,6,7,8,9,10,11,12] is similar to a large scale system in its principles of operation. The main difference is that air is stored in pressure vessels, and the power levels are much smaller, usually of the order of kW. Air motors, rather than turbines, are typically used in these systems. Pre-heating is sometimes used but heat exchangers are used to achieve isothermal decompression. For example, the SS-CAES system with TES supplied by the grid has been industrialised for uninterruptible power supply (UPS) as shown in Figure 1.2. The batteries system for the UPS applications is replaced here by high-pressure gas cylinders for air storage. The use of high temperature TES heated by the grid and the releasable air

from cylinders are combined to drive the turbine. The higher power quality is enhanced by a small flywheel to manage slight power fluctuations.

Figure 1.2 Thermal and compressed air storage technology for UPS [9]

The main advantage of a CAES is that it uses air as the storage medium with none of the toxic waste or fire risks that are associated with batteries. However, the energy density of this system is considerably lower than that of batteries such as Lead–acid, Li-ion, NiCd, and ZnBr, as shown in Figure 1.3. In addition to CAES, there are many energy storage technologies (EST). For example, pumped hydroelectric storage (PHS) has been built worldwide and is a mature and commercially available technology. It is considered that PHS requires two separate water reservoirs. The amount of energy stored depends on the height differences between the two reservoirs and the total volume of water stored. Superconducting magnetic energy storage (SMES) is another EST which stores electrical energy in the magnetic field generated by the direct current in the superconducting coil. However, the SMES system has been cooled with liquid helium or nitrogen to a temperature below a superconducting critical temperature for lower losses. The flywheel is another EST which has been categorised as a mechanical technology, the same as PHS and CAES systems. The stored kinetic energy is transferred to accelerate/deaccelerate the flywheel through an integrated motor/generator. The main weakness of a flywheel is that the device suffers from friction losses during the time when the flywheel is on standby [1].

The main application of SS-CAES is seen to be in the integration of renewable energy sources, but other applications are also possible. The focus of the research has been on improving the thermodynamic efficiency of the electro-pneumatic energy conversion process through control of the electrical power output to achieve maximum efficiency point tracking (MEPT) [9,10,11,12].

Figure 1.3 Comparison energy density and power density [1,3]

The most important work in this area is that reported by Lemofouet-Gatsi [3] who investigated MEPT of a hydro-pneumatic-grid connected energy storage system, as shown in Figure 1.4. This system aims to pressurise and discharge fresh air, which exerts force on the liquid-piston in the working chambers of an oil-hydraulic system via controlling valves. A smoothly variable high quality output power is enhanced by employing supercapacitive auxiliary storage using a dc-dc converter. MEPT (using a perturb and observe (P&O) technique) and a heat exchanger are used to increase system efficiency. However, the MEPT technique requires the use of many sensors including pressure, flowrate and speed transducers for controlling the motor speed at the maximum efficiency point. Crucially, it also relies on the model of the air motor/hydraulic motor and the accuracy of the MEPT is strongly dependent on the accuracy of the model. The dependence of an MEPT on accurate modelling and a large number of sensors adds to the cost of the system and reduces its reliability. For this reason, alternative low cost and more reliable approaches are required.

Fortunately, the maximum power point (MPP) is very close to the maximum efficiency point (MEP), as seen in the previous publication [13] and also in Figure 1.5. Figure 1.5 illustrates the efficiency and power characteristics of the air motor. The figure indicates the slightly different air motor speed of the MPP and the MEP under pressure levels. Maximum power point tracking (MPPT), which requires a few sensors and does not require the *a priori* knowledge of the air motor characteristics, is an attractive alternative to MEPT [13,14].

Figure 1.4 Hydro-pneumatic and supercapacitors storage system [3,12]

The aim of the research work presented in this thesis therefore focuses on MPPT of SS-CAES. However, as there are many similarities between MPPT of a CAES system and a PV system, much of the work presented within this thesis can be applied to improve MPPT of a PV system, in particular eliminating the associated confusion problem and hence reducing operating point fluctuations.

Figure 1.5 Maximum efficiency and power point lines on the efficiency and power characteristics of the air motor

1.2 Aims and objectives of the thesis

This thesis focuses on solving a number of common problems associated with a Perturb and Observe (P&O) maximum power point tracking system, with a specific application to SS-CAES. The investigated problems are:

- 1) Confusion of the MPPT under input power fluctuation conditions. In a SS-CAES system, this occurs due to pressure fluctuations. In a PV system, this occurs due to changes in irradiance [15].
- 2) Under a conventional P&O, the operating point dithers around the MPP but never stays at a fixed point.
- 3) Slow transient response.

The objectives of the thesis are therefore to:

1. Build a test rig as shown in Figure 1.6. It comprises an air motor to drive a permanent magnet (PM) DC generator, which is loaded by a buck converter supplying a resistive load. The buck converter is controlled by a dSPACE system that can be graphically programmed using Matlab/Simulink. A controller estimates data from the pressure, flow rate, current and speed sensors in order to achieve MEPT/MPPT strategies when the ball valve is opened in the discharging process.

Figure 1.6 The experimental rig of the SS-CAES system

2. Design a speed control system for the air motor. Speed is controlled by controlling the duty cycle of the buck converter and hence the power output of the air motor. This approach is used as it has been demonstrated in the literature on MPPT of PV system that direct control of the voltage reference [15] (equivalent to the speed reference in CAES) by an MPPT system gives a significantly faster response than an MPPT system controlling the duty cycle of the converter.
3. Develop an MPPT system using the characteristics of the air motor as a lookup table to determine the appropriate reference speed that corresponds to the MPP for given pressure. The performance of this system is compared with that of an MEPT system to quantify the loss of efficiency caused by using MPPT instead of MEPT.
4. Develop an MPPT system that overcomes the problem of confusion or loss of direction of tracking that results from input power fluctuations.
5. Develop an MPPT system with reduced operating point dither.

1.3 Thesis novel contributions

The study of MPPT of a small-scale compressed air energy storage system contributes to producing new knowledge in the following three ways:

1. Development of a novel hybrid MPPT of a SS-CAES that avoids confusion under pressure fluctuation conditions. The work has been published in the following IEEE journal paper.
Kokaew, V., Sharkh, S.M. and Moshrefi-Torbati, M. (2015) Maximum Power Point Tracking of a Small Scale Compressed Air Energy Storage System, IEEE Transactions on Industrial Electronics, 63 (2), 985-994 [16]
2. Development of a novel fuzzy logic MPPT with variable speed step that avoids confusion (wrong judgement) under search operating conditions and reduces operating point dither. A journal paper will soon be submitted on this work.
3. Quantification of the loss of efficiency of a CAES system resulting from operating at MPPT rather than MEPT. The work has been published as a journal paper.
Kokaew, V., Moshrefi-Torbati, M. and Sharkh, S.M. (2013) Maximum Efficiency or Power Tracking of Stand-Alone Small Scale Compressed Air Energy Storage System, Energy Procedia, 42, 387-396 [13]
4. Development of a test rig is used to validate the theoretical work in this thesis.

1.4 Thesis outline

This thesis consists of six chapters. Chapter 1 introduces the aims and objectives of the research. Chapter 2 presents a detailed description of the test rig and develops a model including a small signal model of the buck converter. The design of a speed regulator is also presented in this

chapter. Chapter 3 describes the work on MPP using the motor characteristics lookup table approach and the MEPT approach that was published in [13]. Chapter 4 describes the hybrid MPPT system which avoids confusion under pressure fluctuations. This work was published in an IEEE journal paper [16]. Chapter 5 is concerned with the fuzzy logic MPPT system, with variable speed step to reduce operating point dither. Chapter 6 presents a limitation of the buck converter with regard to the controllable speed range which can be overcome by using a buck-boost converter instead. An improved hybrid MPPT system is also presented, which avoids confusion and eliminates operating point dither. Chapter 7 presents the conclusion of the work and suggests areas for further research.

Chapter 2: SS-CAES system and its speed regulation

This chapter aims to describe the significance of a speed regulator for the SS-CAES system. It begins with a description of the SS-CAES system. The chapter then moves on to a speed regulator which is used to increase MPPT performance in the SS-CAES system and propose the SS-CAES system with the speed regulator. In order to determine the parameters for enhancing the MPPT efficiency, a speed regulator is next designed to validate the simulation by experimentation. The design includes mathematical models of the air motor, and a permanent magnet (PM) DC generator cascaded with a buck converter. These are later transformed into a small signal model of the SS-CAES system and used for designing cascaded proportional-integral (PI) controllers in the speed regulator.

2.1 SS-CAES system

A SS-CAES is a compact storage system developed from a large scale compressed air energy storage (CAES) system. In order to understand how the SS-CAES system is developed from the large scale CAES, this section firstly reviews the operating process of the CAES and its main limitations. The section then emphasises the development of the SS-CAES for storage applications.

For many year, CAES systems have been used for power system re-enforcement, including peak shaving and frequency balancing. A conventional CAES system consists of a motor-compressor, an air reservoir (normally underground) and a combustion turbine generator. The air is stored in the reservoir during the charging process, using the motor-compressor. In the discharging process, the pressurised air from the reservoir is expanded through the turbine to run the generator. The expansion stage requires heating of the air with fuel; typically natural gas is burned [17,18]. The CAES system is also considered as an attractive storage technology for renewable energy sources that enables their integration within the power system. For off-peak, the renewable generation is used to pressurise air into the caverns which will be released during periods of peak power demand [19,20,21,22]. Examples of large scale CAES plants are in Germany (290 MW), USA (110 MW), Israel (300 MW), Morocco (400 MW) and S. Korea (300 MW), which are used for peak power shaving. These large plants obviously require massive underground storage areas [23,24].

The CAES system; however, suffers from several drawbacks. One of these is its low efficiency for single-stage compression and expansion which is a limiting factor of a very high pressure system. However, efficient design of the CAES system can lead to an improvement in its performance. Higher efficiencies are possible with larger CAES systems, using multi-stage turbines with preheating between expansion stages, using highly efficient heat exchangers [25,26].

Another drawback concerns gas burning in the generation phase to increase the power output of the plant and prevent water vapour in the air from freezing [27]. In order to improve the CAES system to be a fuel-free energy storage technology, heat has to be managed effectively by extracting it from the air during compression and continuously returning/reusing that heat during expansion [28,29]. Adiabatic-CAES (A-CAES) and Isothermal-CAES (I-CAES) have therefore been investigated without the use of gas combustion.

Thermal energy storage (TES) is used in an A-CAES plant to eliminate the need for a combustor [30,31]. The heat energy is extracted and stored separately before the compressed air enters the cavern. When energy is required by the grid, the compressed air and heat energy are recombined, and expanded through an air turbine. The A-CAES benefits from higher storage efficiencies and, especially, zero CO₂ emissions. It is currently being developed within a European funded project called Advanced-Adiabatic CAES [2].

I-CAES compresses and expands air at near-isothermal conditions. The compressed air is generally stored in pressure vessels aboveground. A spray of water or an air–liquid mixture absorbs the heat of compression so that energy is stored in the form of cool air at high pressure and warm fluid at low pressure [32,33]. During isothermal expansion, the mixture delivers heat back to the air which generates electricity. The expanding air in the I-CAES system drives a hydra-pneumatic, which in turn drives an electric generator. However, an I-CAES system has size limitations in terms of the heat transfer area between the mixture and the compressed air. Heat exchange is therefore carried out in many stages to achieve near-isothermal characteristics for the compression and expansion processes [10].

Small scale compressed air energy storage (SS-CAES) systems have been developed from the large CAES, mainly for use in rural and/or remote areas. SS-CAES systems can be also used as parts of an uninterruptable power supply (UPS). In the SS-CAES system, tanks or vessels are used to store the compressed air [34,35]. The air drives an air motor or a turbine, which in turn drives an electric generator that supplies power to consumers. SS-CAES is also potentially an alternative choice for use with renewable sources [4,5,6,12,21,36,37,38]. It is obviously environmentally friendly due to pure air being the only energy source for the charging and discharging processes. Comparing the SS-CAES with the more well-known energy storage devices such as lithium batteries [39,40,41], SS-CAES has a lower energy density but batteries produce toxic waste and possibly experience failure due to heating-up of their internal resistance [41]; therefore, a battery management system is required [42,43,44].

To increase the energy conversion efficiency, the SS-CAES system can be integrated with TES systems [9]. The results showed that the system can store energy at high pressure in billet-formed cylinders (above 310 bar) and relies on oil-lubricated reciprocating compressors which are nearly isothermal. The efficiency of such a system can reach 72%. In [11], constant air pressure is

maintained in the storage vessels during compression or expansion by injecting water/liquid. In this system a quasi-isothermal condition is achieved, which results in an overall efficiency of 74% at 50 bar.

There are many possibilities to increase the overall efficiency of a CAES system, for example, the combustion, thermal and generator efficiencies [45]. The operation of the prime mover (air motor/turbine) can improve the overall efficiency of the expansion process. However, SS-CAES system has scarcely been examined or analysed academically, particularly with regard to its efficacy in storing [46] and discharging energy. So far, the only dedicated research on this topic has been carried out by Lemofouet-Gatsi [3,12] who investigated the SS-CAES system as the main storage technology, together with an auxiliary supercapacitor for solar renewable energy. Improving the performance of the discharging process, using a maximum efficiency point tracking (MEPT) algorithm, has recently been the focus of research [3,12]. In this thesis, the maximum power point tracking (MPPT) is chosen to improve the efficiency/ power conversion of the SS-CAES system with the enhancement of a speed regulator. The next section discusses how the speed regulator improves the MPPT performance of the SS-CAES system.

2.2 Speed regulation

Speed regulation controls the speed of engines and generators and is relevant to the fast dynamic response of MPPT or MEPT strategies [15]. As a fast energy conversion is one of the main focuses in this thesis (see 1.2), a speed regulator is required in the SS-CAES system and is reviewed in this section in terms of mechanics and power electronics.

A mechanical speed regulation is a traditional technique that may be implemented by using a governor to measure the limited speed of a machine, such as a diesel engine or a gas turbine together with a generator. The regulator tries to maintain the desired speed by adjusting the fuel input [47,48,49]. The dynamic response (either transient or steady state) of a hydraulic governor system using an electric controller is faster than a system using a mechanical controller [50,51]. However, the drawback of governor control is the requirement for a non-linear input actuator (the air/fuel flow control valve) that produces losses in such a device.

Power electronics is a more recent method of speed regulation. A common regulator used for renewable energy conversion employs power electronics. In [6,52,53,54], power electronics are alternatively used in wind and solar energy conversion systems in order to extract the power maximum of the wind turbine and solar panel. For example, a power converter is used to control voltage/current in a PV system [15,55] and speed in a wind system [56,57,58,59,60,61].

In the SS-CAES system, power electronics are used to increase the performance efficiency of MEPT algorithm. It is controlled by a full bridge converter with a PI controller [3]. The system

model is based on a small signal DC motor with a power converter model for estimating the close loop controller. Simulation results were experimentally validated. However, it was noted that the power converter in this system would not start up without being connected to a DC bus or external DC sources. This point is in accordance with [62].

Taking into account the similar characteristics between the SS-CAES and wind systems and a very limited study of the SS-CAES, the speed regulation in the wind system is considered for the application to the SS-CAES system. Xia *et al.* [57] investigated speed regulation in a wind system. A permanent magnet (PM) synchronous generator was coupled with a turbine and a boost converter was used to control speed. An input-output feedback linearization method was proposed and compared with a basic PI controller, based on the average state-space (SSA) model. Simulation and experimental results indicated that even though the system under the proposed method can improve the dynamic performance, it cannot refer to the generator side for developing the MPPT strategy. On the contrary, a PI controller can be simply designed and provides good applicability (i.e. it is applicable to other models); but it requires a small-signal model of the system to design the parameters of the controller. However, the small-signal model of the SSA is used to determine the system model that requires considerable matrix algebra manipulation to obtain the relevant gains [57]. It was difficult to clearly understand the behaviour of the power converter [63].

According to Xia *et al.* [57], a power converter can control speed in the wind system with a simple control system structure (PI controller) and low cost. This thesis applies a conventional power converter (buck, boost, and buck-boost converters) with PI controllers to control speed in the SS-CAES system. As a small-signal model is required for the controller, the modelling approaches are presented next.

There are three approaches for designing a small-signal model. One of these is the average state-space (SSA) as seen in Xia *et al.* [57] above. The analysis of pulse-width modulation (PWM) switch is another approach which is used to obtain the general small-signal models of dc-dc converters. The equivalent circuit (PWM-switch) model has also been reported by Vorpérian [64]. The advantages of equivalent circuit modelling are simplicity and clearer insight into converter behaviour. Since not all the circuit equations are linearized as in the SSA method, less mathematical development is required [64,65]. A further approach is the absorbed injected current (AIC) method, which is used to obtain dynamic models [66,67,68]. Similar to the PWM-switch technique, the AIC method applies linearization principles only to the nonlinear part of the circuit. The main improvement of this method is the simplicity of the mathematical manipulations, which are even easier than those used for the PWM-switch technique. The small-signal model of this approach can be represented either by an electrical equivalent circuit or by a functional block diagram, which cannot be done with the PWM-switch technique. The block diagram is more suitable than the equivalent circuit for computer simulation (Matlab/Simulink) in order to design the control circuit. However, the AIC method based on the averaged input current refers to the

output of a conventional converter which is established by taking into account the duty cycle parameter. The small-signal model may increase the numerical error and complexity of the closed loop design, when the AIC method is applied to the diode current of a boost converter or a buck-boost converter.

In this thesis, the absorbed injected current method is used to analyse a small signal model of SS-CAES system for controlling a buck converter. Figure 2.1 below illustrates the configuration of the speed regulator used in the SS-CAES system. The SS-CAES system comprises of an air motor which drives the PM DC generator for the pneumatic to electrical conversion. The output of the conversion is controlled by a buck converter to deliver a resistive power during the expansion process when the ball valve is opened. This system is used with different MEPT and MPPT strategies presented in Chapter 3 to Chapter 5.

Figure 2.1 Configuration of the speed regulator of the SS-CAES system

The next section illustrates the SS-CAES system model and how this model is transformed to a small signal model.

2.3 SS-CAES System model

To control the speed of the SS-CAES system, the pneumatic to electrical conversion of the system is considered, including an air motor and PM DC generator cascaded with a buck converter. The large cylinder is assumed to discharge enough mass flow of perfect gas at isothermal condition with no losses (e.g. kinetic, friction, and core). The pressure of a cylinder is, therefore, proportional with the air motor characteristics (e.g. the mechanical torque output, mass flow, and power as seen in Appendix A). This section illustrates the mathematical system model of power conversion from air input power to electric power output (2.3.1) and its small signal model (2.3.2).

Figure 2.2 Equivalent circuit of the discharge process with buck converter

2.3.1 Permanent magnet DC generator-buck converter models

Figure 2.2 shows the equivalent circuit of the PM DC generator with buck converter driven by an air motor. Throughout this thesis, the output power from the generator is controlled by a buck converter. The dynamic behaviour of the PM DC generator driven by a prime mover (air motor) is obtained by Newton's 2nd law.

$$T_{am} = T_{eg} + B_t \omega_r + J_t \frac{d\omega_r}{dt}. \quad (2.1)$$

The back emf (torque) constant of the generator is given by

$$e_{ag} = K_m \omega_r. \quad (2.2)$$

The load torque for the air motor is the generator's electromagnetic torque, i.e.,

$$T_{eg} = K_e i_{ag}, \quad (2.3)$$

where ω_r is the angular velocity of the air motor and the generator; i_{ag} is the generator armature current; K_e is the generator's torque constant; K_m is back emf constant; B_t is the total of the viscous

friction coefficients of the combined air motor and generator and J_t is the combined moment of inertia of the air motor and the generator.

The steady-state dc voltage transfer function is also known as the dc voltage conversion ration or the dc voltage gain of a dc-dc power converter (Kazimierczuk, 2008: 5). It is shown below:

$$M_v = \frac{V_o}{E_{ag}}, \quad (2.4)$$

where V_o and E_{ag} are the Laplace transforms of the average load output voltage v_o and the input voltage of the back emf e_{ag} respectively.

The overall efficiency of the buck converter can be presented as a function of duty cycle D and dc voltage transfer function M_v , as shown below [63],

$$\eta_c = \frac{M_v}{D}. \quad (2.5)$$

The inductance required to maintain the continuous mode [69] for the duty cycle is

$$L = \frac{v_o(1-D)}{f_s \Delta i_L}. \quad (2.6)$$

The filter capacitance required to reduce a load voltage is estimated by [69]. It is given by

$$C_o = \frac{(1-D)v_o}{8f_s L \Delta v_o}, \quad (2.7)$$

where f_s is switching frequency, v_o is load output voltage, R_L is resistance load, Δi_L is inductor ripple current and Δv_o is output ripple voltage.

2.3.2 A small signal model

The small signal model is created based on the frequency domain transformation of (2.1) to (2.5) and the total output impedance C_o and R_L (see Figure 2.2). The voltage output of buck converter and inductor current are taken as Laplace transforms. It is given by

$$I_L(s) = \left(\frac{R_L}{sR_L C_o + 1} \right) V_o(s). \quad (2.8)$$

Figure 2.3 is an averaged model using the AIC method under the continuous mode condition [68]. This model has already been analysed in Appendix B and reported in [13,70,16]. The inductor current in the frequency domain $I_L(s)$ therefore, is given as

$$I_L(s) = G_1(s)E_{ag}(s) + G_2(s)V_o(s) + G_3(s)D(s). \quad (2.9)$$

The rate of power generation to storage conversion is then estimated based on (2.5) and is further simplified in terms of the armature and inductor currents at the ideal conversion efficiency of $\eta_c=1$, as given below:

$$I_{ag}(s) = M_v I_L(s). \quad (2.10)$$

Figure 2.3 Block diagram of the transfer function of PM-DC generator with buck converter under continuous mode

According to equation (2.8), the transfer function input voltage source $E_{ag}(s)$ is the disturbance effective from the air motor speed to the inductor current $I_L(s)$ which is given by

$$G_1(s) = \frac{M_v}{2\tau L_t} \left(T\tau(2 - M_v) + G_{com}(s) \right).$$

The transfer function of the output voltage $V_o(s)$ to $I_L(s)$ is

$$G_2(s) = -\frac{1}{2\tau L L_t} \left(\tau T \left(M_v^2 (L_t - L) - 2M_v (L_t - L) + L_t \right) - \left((M_v (L - L_t) + L_t) G_{com}(s) \right) \right).$$

The transfer function of the duty cycle $D(s)$ to $I_L(s)$ is

$$G_3(s) = \frac{1}{2\tau} \left(\frac{V_o L_t + L(E_{ag} - V_o)}{L L_t} - \frac{I_m}{\tau} \right) \left(2\tau T(1 - M_v) + G_{com}(s) \right),$$

where

$$G_{com}(s) = \frac{(M_v^2 T - 2M_v \tau + 2\tau)}{\left(s + \frac{M_v}{\tau}\right)}.$$

The exponential functions of the injected current in this converter topology are approximated using Taylor series up to the second term, as analysed in Appendix B. τ is the time constant (L_t/r_{ag}), L_t is the sum of inductance of the basic converter in continuous mode L and the inductance of the generator rotor winding L_{ag} , C_o is the output capacitance, I_m is the minimum inductor current ($I_m > 0$), T is the time period of switching, R_L is the load resistance and K_m is the back EMF constant.

Cascaded PI controllers are used for regulating the inductor current and speed, details of which are explained in the next section.

2.4 Speed regulator controller

This section designs a speed regulator controller based on a small signal model presented in Figure 2.3, using cascaded PI controllers. Figure 2.4 shows a block diagram of a speed controller which provides the speed reference to cascaded PI controllers in the SS-CAES system. It consists of two main parts for achieving the required speed command, including a small signal model of the PM-DC generator with buck converter (on the right hand side) and two cascaded PI controllers (on the left hand side).

Figure 2.4 The block diagram of the speed regulator controller

The speed regulator controls the speed of the air motor to match that set by the MEPT and MPPT. The regulator has two cascaded PI loops: an inner feedback loop of the inductor current and an outer speed feedback loop as shown in Figure 2.4. These are designed in the following manner.

2.4.1 The inner-current loop

In the inner-current loop, PI controller is chosen from the final-value theorem to control the inductor current of the buck converter (i_L) to be zero error. The controller generates the duty cycle to adjust the voltage output of the buck converter (v_o). It means that the delivered resistive power is consumed while maintaining a constant inductor current i_L . It is also related to the corresponding armature current of the DC generator (i_{ag}) within the duty cycle of the buck converter, designed for obtaining the electric torque. As this point, the electric torque can be indirectly manipulated, using the buck converter.

On the drawback of current mode control, the subharmonic oscillations are produced when the duty cycle D is more than 50% [71]. The oscillations are also caused from of the back electromotive force (EMF) voltage of the DC generator. This noise has a significant impact on the algorithm performance and consequently on the energy utilization, especially with small step-sizes for the P&O technique where the system response to noise is comparable to that of the MPPT perturbation of the PV system [15]. In the PV systems, an input ripple problem can be minimised using a large inductor and high switching frequency. However, this solution involves massive filter requirements, high costs and more switching losses [72]. To reduce this high-frequency noise which affects the MPPT performance and the accuracy of an energy conversion, a low-pass (LP) filter is required.

To modify the control strategy in a flexible manner, digital control is used without the need for a significant hardware modification. The inductor current data from a Hall-effect sensor is filtered, using a digital LP filter. The digital LP filter used for shaping the inductor current data is given by

$$H_f(z) = \frac{1 - e^{\omega_{cf}T_{sc}}}{z - e^{\omega_{cf}T_{sc}}}, \quad (2.11)$$

where ω_{cf} is a cut-off frequency (rad/s) and T_{sc} is a sampling period.

The cut-off frequency is estimated by analysing the inductor current data, using the fast Fourier transform (FFT) with a sampling interval of 50 microseconds. Figure 2.5 (a) shows the results from FFT. In this figure, the amplitude of the ripple inductor current Δi_L is the frequency of 10 kHz. The pure DC inductor current i_L is pointed at zero Hz. At the low frequency, the noise pick up from the auxiliary power supply and the electronic devices. Figure 2.5(b) illustrates the inductor current data is filtered with a cut-off frequency 10 rad/s. As can be seen, the high amplitude of Δi_L data is eliminated while the noise of auxiliary power supply and the electronic devices are reduced.

Figure 2.6 represents the actual inductor current when the air motor power is delivered at the resistive load (100W) under the pressure 6 bar (green curve). The low-pass filter with ω_{cf} of about 10 rad/s gives a fast dynamic of inductor current signal, but still provides slightly fluctuated signal

(red dash line). The LP filter with ω_{cf} of about 1 rad/s can eliminate a rippled signal, but the signal suffers from a long settling time (black solid line). These trends affect lower system relative stability and slow down the settling time of the response. They are also related to the outer-speed loop performance, which is discussed in the next section.

Figure 2.5 The fast Fourier transform (FFT) of inductor current signal within low-pass filter

Figure 2.6 The dynamic oscillation of inductor current signal in the different cut-off frequency of LP filters

Turning to the design of PI controller of $G_{ci}(s)$, these conditions are considered. The main controller is assumed to have a sufficiently fast computational speed and data acquisition in the analogue to digital converter and digital to analogue converter. The time delay T_d in the controller

caused by the computational time, which is modelled as $e^{T_d s}$, can be neglected. A sampling frequency ($1/T_{sc}$) of 20 kHz is selected to be at least ten times faster than the current-loop bandwidth [73], but this sampling frequency should be at least equal to the PWM switching frequency when it is used in the controller of a high switching frequency ($>100\text{kHz}$) for the power converter [74]. Furthermore, a digital PWM in combination with the converter power stage can be viewed as a digital to analogue power conversion (DAC), taking the digital command D^* as an input and producing the converter voltages/currents (square-waves) as analogue outputs to drive the power switching [75]. Assuming that a very high-resolution digital PWM with fast-clocked counters is used, the digital PWM block can be simplified using a unity gain amplifier under the PI controller design condition [75].

The PI controller can be designed by using the open-loop input duty cycle to output inductor current transfer function of converter $G_{ip}(s)$ based on Mason rules [76] as shown:

$$G_{ip}(s) = \frac{I_L(s)}{D(s)} = \frac{G_3(s)}{1 + \Delta_1}, \quad (2.12)$$

where $\Delta_1 = G_2(s)G_{st}(s) + MK_m K_e G_1(s)G_d(s)$, $G_{st}(s) = \frac{R_L}{R_L C_o s + 1}$, and $G_d(s) = \frac{1}{J_t s + B_t}$.

Figure 2.7 The Bode plot design of open-loop transfer function of $G_{ip}(z)$ and $G_{ip}(z) G_{ci}(z) H_f(z)$

Then, the open loop transfer function (2.12) is cascaded with low pass filter (2.11). It is discretised, using a zero-order hold (ZOH) to $G_{ip}(z)H_f(z)$ and plotted on the Bode diagram. Typically, an open-

loop stable system is also stable in a closed-loop form if the open-loop frequency response magnitude has a gain of less than 0 dB at the frequency where the phase of the frequency response is 180° [77]. Satisfactory performance for every system requires a gain margin of $\geq 8\text{dB}$ and a phase margin between 30° and 60° [78,79]. In this case, the phase margin 40° and the gain margin more than 20 dB are selected on Bode diagram to determine the parameters of the $G_{ci}(z)$, as shown in Figure 2.7. As can be seen, the open-loop of the inner loop $G_{ip}(z)$ shown by the solid black line (uncompensated system) is reshaped by compensating the PI controller $G_{ic}(z)$, as shown by the blue line (compensated system) of the stable open-loop $G_{ic}(z) G_{ip}(z) H_f(z)$. The compensated system can achieve the phase and gain margins required.

2.4.2 The outer-speed loop

In the outer-speed loop, the DC generator speed (ω_r) is controlled by maintaining the speed error as small as possible, ideally equal to zero. To achieve this result, the PI controller is chosen from the final value theorem. It provides the inductor current reference of the inner-current loop. However, the outer loop is to control the generator speed with a proposed small signal model (see Figure 2.4) which is different from the motor speed control of a DC drive. There are a few papers that concern PI controller for speed regulation. For example, [80] used a boost converter with PI controller to regulate the terminal voltage (speed sensorless) of the wind generator in a hybrid PV-wind system. The linearised system model is designed using MATLAB Control System Toolbox which gives negative gains K_p and K_i of the PI controller. Xia *et al.* [57] used a PI controller based on the average state-space of a wind system model. A negative K_p and positive K_i were provided to the controller. In their models [57] and [80], they cannot, however, indicate whether the negative gain of K_p is significant in the system stability design.

In order to stabilise the speed control of a DC generator, the PI controller should be discussed by describing a root locus. The open-loop transfer function of the outer speed $G_\omega(s)$ or the duty cycle to output generator speed transfer function in Figure 2.3 is determined by

$$G_\omega(s) = \frac{\omega_r(s)}{D(s)} = -\frac{MK_e G_3(s) G_d(s)}{1 + \Delta_1}, \quad (2.13)$$

where $\Delta_1 = G_2(s) G_{st}(s) + MK_m K_e G_1(s) G_d(s)$.

In the single-loop, a negative unity feedback system of equation (2.13) is given by the characteristic equation by obtaining the constant K as shown:

$$1 + KG_\omega(s) = 0. \quad (2.14)$$

Equation (2.14) and the parameters of the system in Appendix E are used to plot the root locus in various K values, as shown in Figure 2.8.

It can be seen that the close-loop system is not stable when $K>0$, i.e., the red line at the positive real axis, as shown in the root locus of Figure 2.8 (a). Using the negative gain, the root locus in Figure 2.8 (b) indicates that the system can be stabilised with only $K<0$ which is the left hand side of the negative real axis. It is suggested that the outer loop should obtain a negative gain K_p for controlling the unity feedback. Therefore, K_p is considered in the K_I estimation of the PI controller.

According to system stability with negative gain, the design of the PI controller can be applied which is based on

$$G_c(s) = K_p + \frac{K_I}{s} = K_p \left[\frac{s + \tau_c}{s} \right], \quad (2.15)$$

where $\tau_c = K_I/K_p$ and K_p is the proportional gain and K_I is the integral gain which are to be determined.

Figure 2.8 Root locus plot of the outer-speed loop controller

The stability analysis of negative gain of $K_p < 0$ in (2.15) presented a possibility for the system to be stable which is to added a zero ($s + \tau_c$) on the left hand side of the root locus, when the value of gain K_I is less than zero ($K_I < 0$) [81]. Therefore, to ensure the stability of the system, the negative gain of the generator mode when using positive K_p and K_I values for the PI controller of the outer loop will simplify the negative speed reference and the positive speed feedback, as shown in Figure 2.4.

Figure 2.9 The actual speed signal and FFT of actual speed

In order to design a PI controller of $G_{c\omega}(s)$, the actual speed is measured and analysed by the FFT. It appears that there is a low noise in the data acquisition as shown in Figure 2.9. The fast computational speed is used to manipulate the data acquisition. Therefore, the LP filter and time delay $e^{T_d s}$ are neglected. A high-resolution digital PWM with fast-clocked counters is assumed by using a unity gain for the digital to analogue converter. Further, a sampling frequency of 20 kHz is used based on the bandwidth of $G_{ip}(s)$ because it is more than those of the open loop of the outer-speed loop $G_{op}(s)$. Therefore, Figure 2.4 is simplified by replacing the unity feedback of the outer-speed loop, as shown below:

Figure 2.10 Block diagram of outer-speed loop with unity feedback control

In Figure 2.10, the open loop transfer function of the input inductor current reference to the output speed $G_{op}(s)$ is included with the inner loop controller which is given by

$$G_{\omega p}(s) = \frac{\omega_r(s)}{I^*(s)} = \frac{-MK_e G_{ci}(s)G_3(s)G_d(s)}{1 + \Delta_2}, \quad (2.16)$$

where $\Delta_2 = G_2(s)G_{st}(s) + MK_m K_e G_1(s)G_d(s) + G_{ci}(s)G_3(s)H_f(s)$.

The frequency response design methods, unlike root locus methods, can be implemented conveniently without a computer. The Bode plots are an alternative way of visualising and implementing concepts to estimate the outer loop controller by reading values such as gain and phase margins off the plots.

The parameters of the system in Appendix E, ZOH, and the Bode diagram are used for selecting the parameter of $G_{\omega p}(z)$ controller loop at phase margins of 60° and gain margin greater than 20 dB, as shown in Figure 2.11. It is important to point out that the open-loop crossover frequency of either inner or outer loop transfer functions needs to be related to gain crossover frequency. That is the gain of the inner loop controller must be higher than that of the outer loop controller to obtain a faster dynamic response according to the guidelines for tuning cascaded PI controllers [78]. It can be seen that the outer speed loop controller can complete the required phase and gain margins. The uncompensated $G_{\omega p}(z)$ is stabilised by cascading the PI controller $G_{c\omega}(z)$, as shown by the blue line representing the compensated $G_{c\omega}(z)G_{\omega p}(z)$.

Figure 2.11 The Bode plot design of open-loop transfer function of speed $G_{\omega p}(z)$ and $G_{\omega p}(z) G_{c\omega}(z)$

2.5 Simulation results

The mathematical model of the SS-CAES system is implemented using the SimPowerSystem of Matlab/Simulink [82] for the speed regulator, as seen in D.2 and D.3.2, in Appendix D. The system parameters are illustrated in Appendix E. The speed and inductor current data from sensors are sampled using the zero order hold (ZOH) at a frequency of 20 kHz. For the inner loop of the cascade PI controller, the low-pass filter with the cut-off frequency of 10 rad/s is used for rejecting any added noise in the inductor current signal. The inductor current corresponding to the electric torque of the PM DC generator is also maintained by employing the PI controller. The outer loop controller is fed back using the PM DC generator speed without the low-pass filter for regulating the speed. Here, it is assumed that perfect gas in a large cylinder is discharged at isothermal conditions. Kinetic and frictional losses are ignored. Therefore, the mass flow of air that is released to the air motor is proportional only to pressure changes within the cylinder.

Figure 2.12 Simulation results of the speed, the torque and the power output in various speed command and constant pressure conditions

Figure 2.12 shows the pressure, the air motor speed, torque and power under varying step speed command conditions. For the speed against time graph, the green speed curve represents the speed commands set by the step speed changes from 150 rad/s to 140 rad/s and then back to 160 rad/s. The black speed curve is the measured speed controlled using the speed regulator. As can be seen,

using cascade PI controllers, the speed regulator has effectively followed the demand speed at a constant pressure of 6 bar.

Figure 2.13 Simulation results of the speed, the torque and the power output under varying pressure conditions

For varying pressure conditions, the results of the speed, the torque and the power are obtained using the speed regulator, as shown in Figure 2.13. The actual speed can be maintained at 150 rad/s in the speed versus time graph. It can be seen that the speed regulator has successfully controlled under varying pressure conditions.

2.6 Experimental setup

The PM DC generator was a LEMAC/65167-008, (24V, 3000 rpm, 250 W). An Atlas Copco LZB 14 AR034 (100W) air motor was directly coupled to the generator. The MOSFET switching at 10 kHz was used in a buck converter (100VA) for selecting each components (L and C_o) and delivering power to a resistive load (R_L) at continuous mode. The system also set an inlet pressure level of the air motor by using a pressure regulator for observing the dynamic response of power fluctuation. In order to isolate the SS-CAES system and controller, and hence prevent an electrical fault [83], a reflective object sensor (OPB704), a Hall-effect sensor (LAH 25-NP) and an optical isolation (TLP250) were used, as shown in Figure 2.14.

Figure 2.14 An isolation of the SS-CAES and speed controller

Speed and current data were also sampled at a frequency (f_{sc}) of 20 kHz using a microcontroller within dSPACE MicroAutoBox II. The frequency components of the speed square wave data was determined using a DIO TP3 F2D module of DS1511 as seen in Figure F.8. Low-pass filters with a cut-off frequency (ω_{cf}) of around 1 rad/s and 10 rad/s were used to filter the current signals within the speed regulator controller for observing the dynamic response of the air motor speed. The speed regulator with cascade PI controllers was simulated using Matlab/Simulink that can be graphically programmed into MicroAutoBox II DS1511, as seen in Appendix F. The duty cycle of the PWM from the speed regulator was set to drive a power MOSFET switch within the SS-CAES system for supplying power to the resistive load. Furthermore, in the strain gauge pressure transducer, flow sensors and a low-pass filter with ω_{cf} of roughly 1 rad/s were used for monitoring the system dynamics, see Figure 2.15.

Figure 2.15 Experimental rig for the SS-CAES system

- (1) Permanent Magnet DC Generator
- (2) Air Motor
- (3) Resistive Load
- (4) Buck Converter
- (5) Voltage and Current Sensors
- (6) Pressure Regulator
- (7) Pressure Transducer
- (8) Flow Sensor
- (9) Inlet Air Pressure
- (10) dSPACE
- (11) Personal Computer

2.7 Experiment results

The experimental results focus on the speed regulator of the SS-CAES system under constant pressure condition of 6 bar and varying pressure level. The inductor current data is low-pass filtered using two cut-off frequencies ω_{cf} of 1 rad/s and 10 rad/s.

Figure 2.16 shows the dynamic response of the air motor speed that is controlled using PI-cascade controllers for speed command values of 150 to 140 and 160 rad/s. The settling time of the actual speed corresponding to the step speed changes can be seen.

For similar speed command values of 150, 140 and 160 rad/s, the dynamic response of the air motor speed through a low-pass filter, with a cut-off frequency ω_{cf} of 10 rad/s (see Figure 2.17) is slightly faster than those of 1 rad/s (see Figure 2.18). As for the accuracy, there is a small fluctuation in the actual speed, which is an effect of the use of the higher cut-off frequency in the inner loop in accordance with the discussion in 2.4.1. The output power is shown in, Figure 2.16- Figure 2.17 and the air motor characteristics are examined in Chapter 3.

Figure 2.16 Experimental results of the speed regulator through a low-pass filter, with a cut-off frequency ω_{cf} of 1 rad/s at a constant pressure of 6 bar

Figure 2.17 Experimental results of the speed regulator through a low-pass filter, with a cut-off frequency ω_{cf} of 10 rad/s at a constant pressure of 6 bar

The use of the higher cut-off frequency further affects the dynamic response of the air motor speed and the accuracy of the speed regulation for given disturbed pressure levels of 6 bar to 4 bar and back up to 6 bar again (see Figure 2.18–Figure 2.19). That means, for the dynamic response, a higher cut-off frequency ω_{cf} of 10 rad/s (see Figure 2.19) gives a slightly faster recovery to the speed command (around 150 rad/s) than ω_{cf} of 1 rad/s (see Figure 2.18). For the accuracy of the speed regulation, the fluctuation of the steady state response of the air motor speed is still around the reference speed, as depicted in Figure 2.18.

The small fluctuations in the actual speed, as seen from the black curves in Figure 2.16-17, are compared to find average errors with the speed command between the speed 140 and 160 rad/s, as shown in Table I.

Table I The percentage of the steady state error of the air motor speed for the speed regulator

Cut-off frequency (rad/s)	Speed error (%)
1	± 0.5
10	± 0.6

Figure 2.18 Experimental results of the speed regulator through a low-pass filter, with a cut-off frequency ω_{cf} of 1 rad/s for pressure changes

Figure 2.19 Experimental results of the speed regulator through a low-pass filter, with a cut-off frequency ω_{cf} of 10 rad/s for pressure changes

As can be seen, the air motor speed error is related to the cut-off frequency of the low-pass filter. In Chapter 4, this criterion is used to minimise the step-size in the speed changes of the proposed MPPT-algorithm. However, the main mechanical parameters, such as moment of inertia and pressure fluctuations are considered in the thesis. There are many possible sources of error in the simulation results, especially for the dynamic speed response which is quicker than in the experiment results. For example, the dynamic air motor model, the metering equipment (pressure regulator, flowrate sensor) and the starting of the system with the ball valve are neglected. Another possible source of error is the thermodynamic processes which are not modelled in detail.

Future work should therefore investigate these problematic effects in the calculation of the SS-CAES system model.

2.8 Summary

SS-CAES is developed from the large scale CAES by pressurising air into the vessel. Concerning the dynamic response of the MPPT performance, the speed regulator is applied to the SS-CAES system. An air motor is used to drive a PM DC generator, which output is controlled by a buck converter supplying power to a resistive load at the required speed of the air motor during the decompression process.

The cascaded PI controller of the speed regulator is investigated to control the PM DC generator speed, using a buck converter under the varying speed and pressure conditions. However, the cascaded PI controller requires a small signal model of the SS-CASE system to select the parameters of the controller. The small signal system model can be established using the absorbed injected current method in the continuous mode. It is then used to stabilise the system and set the parameters of the cascaded PI controllers in the inner-current loop and the outer-speed loop. The small signal system model indicates that the speed control requires a negative gain of K_p and K_i to stabilise the system at the stable region of the phase margin 30° - 60° and gain margin greater than 20 dB. Furthermore, the inductor current loop control should be faster than the speed loop control in order to obtain the faster dynamic response. This can be achieved by setting the inner loop gain higher than the gain of the outer loop.

The use of a buck converter as the speed regulator to control the air motor speed of the SS-CAES system has several advantages. It has a simple control system structure and the lowest cost of the conventional dc-dc power converters, and hence is popular. The system's behaviour can be also well understood and this makes easier for modelling and design. Moreover, the PI estimation in the Matlab programme can be applied to the proposed system modelling.

However, some drawbacks still remain in that the cascaded PI controller cannot effectively operate when there is a massive overshoot in the starting period as an effect of the negative speed error. It

seems to be the case that the speed controller produces the negative duty cycle to drive a buck converter. Further, the settling time for a high-order system is set by measuring the actual air motor speed response under the highest step speed change condition. It is the basis of the speed tracking of the MPPT system in Chapters 4 to 6. Furthermore, the low-pass filter slows down the settling time of the dynamic response and might affect the system stability. Importantly, the speed regulator cannot operate without load.

The proposed speed regulator can be applied in the wind system or in the power management in vehicle system of [84,85,86]. In this thesis, it is applied in the MPPT strategies which are shown in Chapters 3 to 5.

Chapter 3: MEP and MPP of SS-CAES

This chapter describes the modelling of a pneumatic to mechanical energy conversion system via modifying the existing curve fit equations of an air motor's air consumption and by adapting a suitable model for a buck converter with a PM DC generator (speed regulator) for the SS-CAES system. A linearised model of the air motor is investigated for the MEP and MPP and compared for their different speed operating points. The model is also characterised to control the MEP and MPP. Finally, the practical implementation of the controller and experimental results are discussed.

3.1 Maximum efficiency or power point of SS-CAES

In a conversion of power and efficiency, different operating points result in different power and efficiency values. In [87,88], for example, a fuel cell model indicates that the operating point of the current density provides different MPP and MEP. The air motor in SS-CAES also provides a different operating point for speed [13]. The maximum efficiency point tracking (MEPT) and the maximum power point tracking (MPPT) are thus essential to increase the efficiency (MEPT) and the power (MPPT) of the conversion [5,12,13,16,70].

Figure 3.1 Configuration of the proposed discharging process with MEPT/MPPT

This chapter aims to propose the MEPT and the MPPT for improving the maximum efficiency and the maximum power conversion in the different speed operating points. It uses a linearised model of the air motor together with the speed regulator (Chapter 2). Figure 3.1 above shows the

configuration of the MEPT and MPPT used in the SS-CAES system during the discharging process when the ball valve is opened.

The air motor model is firstly characterised to point out the different operating points of the speed and this is presented in the next section.

3.2 The air motor model

The air motor LZB 14 AR034 (100W) [89] is used in this thesis. The air motor's mechanical output torque (T_{am}) as a function of inlet pressure p_i and air motor speed (ω_r) changes is given by:

$$T_{am} = T_o(p_i) \left(1 - \frac{\omega_r}{\omega_{ro}(p_i)} \right). \quad (3.1)$$

The mechanical output power of the air motor (P_{am}) is derived using (3.1), as:

$$P_{am} = T_{am} \omega_r = T_o(p_i) \left(\omega_r - \frac{\omega_r^2}{\omega_{ro}(p_i)} \right). \quad (3.2)$$

Based on the air motor characteristics, the following expression for air flow dV_a/dt , in (lit/s) can be derived:

$$\frac{dV_a}{dt} = \frac{dV_{max}(p_i)}{dt} \exp \left(- \left(\frac{(\omega_r - c_1)}{c_2} \right)^2 \right). \quad (3.3)$$

In the above equations, the stall torque is given by $T_o(p_i) = c_{t1} \cdot p_i + c_{t2}$, the free speed is given by $\omega_{ro}(p_i) = c_{n1} \cdot p_i^2 + c_{n2} \cdot p_i + c_{n3}$, where the free speed is the speed at which the outgoing shaft rotates under no load, and the maximum air flow is given by $dV_{max}(p_i)/dt = c_{a1} \cdot p_i + c_{a2}$, where, c_{t1} , c_{t2} , c_{n1} , c_{n2} , c_{n3} , c_{a1} , c_{a2} , c_1 and c_2 are real constants determined using curve fitting of the experimental performance curves of the air motor (see Appendix A).

3.3 Maximum efficiency point and maximum power point of SS-CAES system

The air motor model is characterised to maximise the SS-CAES system performance in terms of its power and efficiency points. These are addressed below.

3.3.1 Maximum efficiency point

Using equations (3.1)-(3.3) and (3.4), the efficiency-speed-pressure characteristics of the air motor can be plotted, as shown in Figure 3.2. As can be seen in this figure, the maximum efficiency line

of the air motor is obtained from the measured efficiency surface characteristics. The maximum efficiency line can be estimated as will now be described.

Figure 3.2 Maximum efficiency line on the efficiency-speed-pressure characteristics of the air motor

To determine the maximum efficiency line of the efficiency-speed-pressure characteristics of the air motor, the conversion efficiency of the air motor (η_{am}) can be shown to be given by the ratio of the shaft power to the expanded air power under isentropic conditions [3],

$$\eta_{am} = \frac{T_o(p_i) \left(\omega_r - \frac{\omega_r^2}{\omega_{ro}(p_i)} \right)}{\frac{\gamma}{\gamma-1} p_a \frac{dV_a}{dt} \left[\left(\frac{p_i}{p_a} \right)^{\frac{\gamma-1}{\gamma}} - 1 \right]}, \quad (3.4)$$

where p_i is the inlet pressure, p_a is the atmospheric pressure and the ratio of specific heats (γ) is the ratio of the heat capacity at constant pressure (c_p) to heat capacity at constant volume (c_v). This thesis uses $\gamma = 1.4$ at the temperature of 20°C .

The derivative of the conversion efficiency in (3.4) with respect to speed changes is given by error (e) as,

$$e = \frac{d\eta_{am}}{d\omega_r} = K_1(1 - K_2\omega_r), \quad (3.5)$$

where the K_1 and K_2 are defined as:

$$K_1 = f_1(p_i, \frac{dV_a}{dt}) = \frac{T_o(p_i)}{\frac{\gamma}{\gamma-1} p_a \frac{dV_a}{dt} \left[\left(\frac{p_i}{p_a} \right)^{\frac{\gamma-1}{\gamma}} - 1 \right]}, \text{ and } K_2 = f_2(p_i) = \frac{2}{\omega_{ro}(p_i)}$$

In the frequency domain, (3.5) will be transformed to

$$sE(s) = K_1 - K_1 K_2 s \omega_r(s). \quad (3.6)$$

Again, the Laplace transform of (2.1) is shown below:

$$s\omega_r(s) = \frac{1}{J} (T_{opt}(s) - T_{eg}(s) - B\omega_r(s)). \quad (3.7)$$

The initial air motor speed $\omega_r(t=0)$ in the above is assumed to be zero, the optimum air motor torque T_{opt} is estimated using the curve fitting of the experimental performance curves of the air motor at the maximum efficiency. It is given by $T_{opt}(p_i) = f_3(p_i) = c_{op1} p_i + c_{op2}$, where c_{op1} and c_{op2} are real constants.

It is important to note that the non-linear nature of the selected air motor makes the formulation of the maximum efficiency line difficult. Data from a pressure sensor, an air flow meter, a speed sensor and current sensor are used for controlling the maximum efficiency, as seen in (3.6), (3.7), (2.3), (2.5) and (2.10). Malab/Simulink is used to create the MEPT controller, as shown in section 3.4.

3.3.2 Maximum power point

The maximum output power of the air motor. A 3D representation of the air motor power is given in Figure 3.3 that is plotted using (3.1), (3.2) and (3.9). The figure shows that the maximum power line of the air motor (on the power surface characteristic) strongly depends on pressure and speed.

To estimate the maximum power line of the power-speed-pressure characteristics of the air motor, the derivative of the shaft power of the air motor in (3.2) with respect to speed changes is

$$\frac{dP_{am}}{d\omega_r} = T_{am}(p_i) \left(1 - 2 \frac{\omega_r}{\omega_{ro}(p_i)} \right). \quad (3.8)$$

By equating the above derivative to zero we obtain

$$\omega_r = \frac{\omega_{ro}(p_i)}{2}. \quad (3.9)$$

Equation (3.9) shows that MPPT control can be achieved by using a pressure sensor to set the reference speed to half the free speed ω_{ro} as shown in section 3.4.

Figure 3.3 Maximum power line on the power-speed-pressure characteristics of the air motor

3.3.3 A comparison between the MPP and the MEP

To compare the different operating points of speed, the torque, air consumption, power and efficiency characteristics of the air motor can be plotted, using equations (3.1)-(3.3), (3.9), and (3.4) on Figure 3.4. As can be seen, the maximum power and the maximum efficiency lines of the air motor characteristics clearly occur at slightly different speeds. They are also strongly dependent on pressures.

Furthermore, the MPP and MEP lines (optimal power speed and optimal efficiency speed) based on the inlet pressure changes are used to measure the performance of MEPT and MPPT strategies in sections 3.5 and 3.7 and again in Chapters 4 to 5.

Figure 3.4 Maximum efficiency point (MEP) and power point (MPP) lines on the air motor characteristic curves

3.4 The maximum point controller

The MEPT/MPPT controller is shown in Figure 3.5. Either MPPT or MEPT can be selected. When the MPPT is selected, the speed reference of the regulator is set to be half the free speed of the measured pressure according to equation (3.9). When the MEPT is selected, the reference speed is set such that the derivative of the efficiency is calculated using equations (3.5) and (3.6).

Figure 3.5 The MEPT/MPPT controller

3.5 Simulation results

The Malab/Simulink of the SS-CAES system is shown in Appendix D (D.2 and D.3.3), which includes an air motor coupled with a PM DC generator, a buck converter, and the MEPT/MEPT strategies with the speed regulator controller. The system parameters are presented in Appendix E. The air motor is modelled by fitting the air motor characteristics (see Appendix A and D.1) to provide the mechanical torque. The conventional buck converter is supplied with varying voltage input by connecting it to the PM DC generator which is fed from the air motor torque in its generation mode [82]. The generator's speed and the inductor current are sampled at a frequency of 20 kHz for regulating the speed, as per the discussion in Chapter 2. Data from the speed sensor, pressure transducer and flow sensor within the period of 50 μ s are also used to estimate the reference speed from the proposed MEPT/MPPT strategies.

To test the performance of the system, the conditions of constant and varying pressures are implemented by the resistive load changing from R_L to $2R_L$. For the expansion process, it is assumed that perfect gas in a large cylinder is discharged at isothermal conditions. Kinetic and frictional losses are ignored. Therefore, the mass flow of air that is released to the air motor is proportional only to pressure changes within the cylinder.

Figure 3.6 Simulation results of the proposed MEPT strategy under varying pressure conditions

The results in Figure 3.6 show the dynamic response of the air motor efficiency, the power output and the speed under varying pressure from 6 to 4 and then back to 6 bar. It can be seen that the computed speed (dashed green) is provided by the MEPT strategy and the actual speed (black) is achieved via the maximum efficiency of the dash green curve of the air motor characteristics.

Under the varying pressure conditions of the MPPT strategy, the transient response of the speed, the power and the efficiency are illustrated in Figure 3.7. On the speed versus time graph, the optimal speed curve (dashed red) is the speed at which the power is maximum for a given pressure, as estimated from half the free speed of the air motor characteristics. The green speed curve is the command speed estimated by the proposed strategy, and the black curve is the actual measured speed. It can be seen that the MPPT strategy has successfully produced the command when the pressure changes from 6 to 4 and back to 6 bar again.

In the constant pressure condition, the responses of the speed, the duty cycle, the power and the efficiency are shown, under different load conditions for both MEPT and MPPT modes of operation, in Figure 3.8. It can be seen that the actual speed required to achieve maximum efficiency is different from that needed to achieve maximum power.

Figure 3.7 Simulation results of the proposed MPPT strategy under varying pressure conditions

Figure 3.8 Simulation results of the system response under MPPT and MEPT strategies

3.6 Experimental setup

The speed regulator for the SS-CAES system was implemented using a cascaded PI controllers, as per the discussion in Chapter 2. It also is applied in the proposed MEPT/MPPT strategies to achieve the desired MEP and MPP. A speed sensor, a pressure transducer and a flow sensor were used for isolating the SS-CAES system from the controller. Data from the sensors were sampled at a frequency of 20 kHz, and obtained from the low-pass filter with a cut-off frequency ω_{cf} of 1 rad/s, as seen in Figure 3.9. The load resistances R_L and a $2R_L$ were monitored to characterise the system. The systems parameters in Appendix E and the Matlab/Simulink are graphically programmed by embedding the relevant C code in to dSPACE, see Appendix F.

Figure 3.9 An isolation of the SS-CAES and MEPT/MPPT with speed regulator controller

3.7 Experiment results

The results in Figure 3.10 show the response of the system under different load conditions for both MEPT and MPPT modes of operation. In the speed versus time graph, the green speed curve is the speed command calculated by the proposed MPPT/MEPT strategies, and the black curve is the actual measured speed by the speed regulator. It is clear that the reference speed needed to achieve the maximum efficiency is different from that needed to achieve the maximum power. Furthermore, the power output corresponds to the duty cycle of the buck converter, which in turn resulted from the increased resistive load.

The results also show that the system is capable of coping with variable load conditions. Figure 3.11 shows a good agreement between the theoretical and experimental maximum power and maximum efficiency operating lines.

Figure 3.10 Response of the system under MPPT and MEPT strategies at constant inlet pressure of 6 bar

Figure 3.11 Experimental and theoretical maximum power and maximum efficiency operating lines

3.8 Summary

This chapter focuses on the maximum efficiency and maximum power points of the air motor. An analysis based on a linearised air motor model, indicates that the maximum efficiency and the maximum power conversion have different speed operating points. However, they produce very close efficiencies, the MEP is 1% higher than that at the MPP at a constant inlet pressure of 6 bar. To track the maximum power, the reference speed of the air motor needs to be half the free speed (no-load) for a given pressure. The air motor speed corresponding to maximum efficiency can also be calculated from the motor characteristics and measurement of speed, air flow and pressure. These MEPT and MPPT strategies were validated experimentally together with the speed regulator. An important point to note is that these strategies require careful characterization of the air motor and also require the use of speed and pressure sensors. The next chapter investigates alternative strategies that do not require air motor characterization and use fewer sensors. Furthermore, the strategies must improve the starting of the system.

Chapter 4: MPPT algorithm

This chapter aims to propose a novel P&O MPPT algorithm. It commences with a review of its performance and limitations in order to understand the algorithm. The SS-CAES system is then set up for later implementation and finding limitations of a conventional P&O algorithm particularly in the SS-CAES system. Next, the principle concept of the P&O MPPT algorithm is combined with the behaviours of a power converter to consider the characteristics of an air motor power-speed curve and duty cycle-speed curve. A confused search direction is studied afterwards in relation to the SS-CAES system, followed by the explanation of a novel hybrid P&O MPPT algorithm for preventing a search direction confusion during the input power fluctuations and a measurement of power losses estimation. Finally, simulation and experimentation of the proposed novel P&O MPPT algorithm are presented.

4.1 Review of maximum power point tracking (MPPT)

This section reviews a number of studies on MPPT in order to understand its performance and how the strategy operates, how it can be applied to the SS-CAES system and also its limitations.

In Lemofouet-Gatsi [3], the performance of a hydro-pneumatic system is improved by using a suitable maximum efficiency point tracking (MEPT) algorithm along with heat exchangers. The system under investigation operates with a hydraulic motor with an efficiency of over 94% at 350 bar. The MEPT of the system is based on the perturb and observe (P&O) technique and improved by controlling the output of the pneumatic to electrical conversion based on the hydraulic motor characteristics. Such a system uses pressure, flow rate and speed transducers to track the maximum efficiency point of the hydraulic/pneumatic motor.

Although efficiency is important, the maximum efficiency point (MEP) is difficult to measure or estimate accurately in real time. It relies on a model of the system and an accurate estimation of loss. In many applications, maximum power point tracking (MPPT) is employed to improve a system's efficiency. MPPT is easy to determine because the output power can be measured directly. Moreover, the air motor characteristic of the maximum power point (MPP) is also close to the maximum efficiency point (MEP) as seen in section 3.3.3. Therefore, the loss of efficiency when the air motor operates at MPP is small compared to when operating at MEP.

Amongst the many researchers that have studied MPPT, Martínez *et al.* [5] investigated the control of a hybrid energy storage system using compressed air and supercapacitors. They used P&O to achieve MPPT of a pneumatic to electric power converter. A pressure transducer is used in [5] to provide an estimation of the initial speed of the pneumatic motor. The paper presents only the theoretical simulation results. The P&O method used by Martínez *et al.*, increments or decrements

speed by a fixed step and checks whether the power has increased or decreased. In other words, it effectively calculates the derivative of the power with respect to speed. Any change to the speed is made in the direction towards the MPP.

In [70], a hybrid P&O method is used. The derivative of power with respect to both speed ($dP/d\omega$) and the dc-dc converter duty cycle (dP/dD) are calculated. Two step speed changes are employed. A small step change is used in the fine tuning region, i.e., in the vicinity of the MPP together with using the $dP/d\omega$ to decide the direction of the next speed step change. A course step change is used away from the MPP together with dP/dD to determine the direction of the next speed step change. This method was validated using both simulation and experiment.

Generally, the MPPT of photovoltaics system using the P&O techniques is known to have the drawback of the operating point oscillating around the MPP at steady state [90,52]. The step-size selection of this method also directly affects the accuracy and speed of convergence to MPP. It means that a large step-size can speed-up the convergence to MPP, but it also results in a large number of inaccuracies. In contrast, a small step-size can provide a high level of accuracy but slow convergence in response to rapid changes of the operating conditions [91]. Furthermore, these methods can cause wrong decisions to be made about the required directions of the reference voltage or current values [15,55]. This results in undesired energy losses during the confused direction and recovery periods. As can be seen later in the results presented in this chapter, this could also occur in a SS-CAES system.

According to the reviewed studies above, it is obvious that the P&O algorithm is used in MEPT/MPPT. This algorithm is simply and popularly implemented but the limitations are the accuracy and speed of convergence to MPP with only a fixed step-size and loss of search direction in response to the power input fluctuations. This thesis, therefore, discusses the design and implementation of an MPPT controller for the discharge process of a SS-CAES system, as illustrated in Figure 4.1. In this system, an air motor is used to drive a permanent magnet (PM) DC generator. Pneumatic to electrical energy conversion is controlled to deliver power to a resistive load using a buck converter. Unlike the MPPT method presented in Chapter 3, the real-time MPPT algorithm proposed in this technique does not require a priori knowledge of the air motor characteristics or the use of a pressure transducer. It employs a novel hybrid perturb and observe (P&O) approach using coarse and fine speed steps to improve the convergence and accuracy of the MPPT. The algorithm can ensure that the correct direction of speed step change is obtained under transient input power fluctuations. The system is analysed using a small signal model. A digital speed regulator is designed to control the output power of the DC generator such that the desired MPPT is achieved. The MPPT algorithm is simulated and implemented experimentally in section 4.6 and section 4.8 respectively.

Figure 4.1 Configuration of the proposed discharging process with MPPT

4.2 Control system

A system incorporating MPPT, when using a regulator, produces a faster dynamic response than when directly applying duty cycle control at rapidly changing irradiance, as shown in [15,55,92]. In this thesis, the speed regulation is applied for adjusting the speed at the MPP and also delivering a resistive load power using a buck converter. The speed regulator is designed using basic cascade PI controllers along with the small-signal model of Figure 2.2. The system model is averaged by using the absorbed-injected current method [68] under the continuous mode condition to design the inductance and capacitance of the buck converter [69]. The digital cascade PI controllers are obtained by using a low-pass filter, which is designed via a Bode diagram using a stable phase margin of 30° - 60° . The chosen switching frequency is at least ten times that of the current loop bandwidth to estimate the parameters of the controllers, as discussed in Chapter 2.

Figure 4.2 shows a block diagram for a novel MPPT-P&O controller and the speed regulator within cascaded PI controllers in the SS-CAES system. For MPPT controllers, the actual speed, inductor current and duty cycle of the power converter are the recorded data with a sampling frequency based on the settling time of the speed regulator, as shown in section 2.7. Further, P&O algorithm also monitors the system dynamic, i.e., a fast speed convergence and prevention of search direction confusion, in response to power fluctuations.

Figure 4.2 Block diagram of MPPT-P&O algorithm system with speed reference control

4.3 Principle of maximum power point tracking (MPPT)

To discuss the operation principle of the MPPT controller, the power-speed and duty cycle-speed curves that are shown in Figure 4.3 are considered. In this figure, equation (3.2) was used to plot the air motor shaft power at the rated pressure and as a function of speed. From (2.5) and (2.2), the air motor power can be expressed in terms of the converter's output power, the duty cycle of the buck converter, motor speed, the resistive load R_L and both mechanical and electrical losses as:

$$P_{am} = \frac{v_o^2}{R_L} + P_{fc} + i_{ag}^2 r_{ag}. \quad (4.1)$$

Equation (4.1) is revised using (2.2), time domain of (2.4) and (2.5), as follows:

$$P_{am} = \frac{(\eta_c K_m \omega_r)^2}{R_L} D^2 + P_{fc} + i_{ag}^2 r_{ag}. \quad (4.2)$$

The duty cycle versus air motor power can be then plotted in Figure 4.3 from (3.1) (3.2) and (4.2) as a function of speed. In Figure 4.3 the duty cycle-speed curve assumes that the air motor produces the shaft power from 0-100 W under the varying speed, the buck converter efficiency is 90% and the total power losses (P_{fc} : friction and copper losses) are negligible. Below a certain speed, the duty cycle of the buck converter increases above 95%, which is outside the limited practical range of D from 5% to 95% due to resolution [63], thus the power controller becomes unstable. Accordingly, the MPPT controller sets the reference speed to a minimum value of Nr_{min} if the duty cycle increases above 95%. In practice, the reference speed is also initially set to its minimum value when the system starts. The basic principle of the P&O algorithm is to increase the speed in constant step-sizes when the operating point is on the low speed side of the MPP or to decrease it if the operating point is on the high speed side of the MPP, until the rate of change of power with respect to speed becomes zero. To identify the operating point on the air motor power-speed and duty cycle-speed curves, Figure 4.3 illustrates an overview direction of the operating

point when a slope is estimated using either $dP_{am}/d\omega_r$ or dP_{am}/dD . As can be seen in the figure, the slope of $dP_{am}/d\omega_r$ can easily be addressed on the left or right hand sides of the MPP when the operating point is on the slope of $dP_{am}/d\omega_r > 0$ or $dP_{am}/d\omega_r < 0$, respectively. However, the slope of dP_{am}/dD will be considered using the *chain rule*, as follows:

$$\frac{dP_{am}}{dD} = \frac{dP_{am}}{d\omega_r} \cdot \frac{d\omega_r}{dD} \quad (4.3)$$

To recognise the operating point on the duty cycle-speed curve, the derivative of the duty cycle with respect to changes in speed $dD/d\omega_r$ has a negative sign on both sides of the MPP. It substitutes then into (4.3). As can be seen, the slope of $dP_{am}/dD < 0$ when the operating point is on the low speed side of the MPP, and vice versa, as shown in Figure 4.3.

Figure 4.3 Basic MPPT on air motor power and buck duty cycle versus speed curve

According to the criteria used for a fast MPPT by implementing an incremental inductance (INC) and a fuzzy logic techniques [93,94], the rate of change of P_{am} in (3.2) with respect to changes in speed is used in terms of the derivative *product rule*. It is given by

$$\frac{dP_{am}}{d\omega_r} = T_{am} + \omega_r \frac{dT_{am}}{d\omega_r}. \quad (4.4)$$

Again, the derivative product rule of the shaft power of the air motor with respect to duty cycle is given by

$$\frac{dP_{am}}{dD} = T_{am} \frac{d\omega_r}{dD} + \omega_r \frac{dT_{am}}{dD}. \quad (4.5)$$

The slopes in (4.4) and (4.5) are employed to plot the curves in Figure 4.4. It can be seen that the operating point position can be identified using the slope until the MPP is achieved. For example, if the operating point has a slope of $dP_{am}/d\omega_r > 0$ or $dP_{am}/dD < 0$ which is the low speed side of the MPP, the constant step- size ($\Delta\omega_{com}$) will increase the speed. It is decreased when the slopes of $dP_{am}/d\omega_r < 0$ or $dP_{am}/dD > 0$ are on the high speed side.

Figure 4.4 The slope of the output power of the air motor with respect to speed and duty cycle

As the operating point approaches the MPP, the speed step changes ideally need to be reduced in magnitude so that the MPP is not overshoot. In Figure 4.5, the region in the vicinity of the MPP, where the speed step changes are small, is labelled as the fine tuning area. Areas outside this region are labelled as coarse tuning areas; in these areas the speed step changes are large.

Figure 4.5 The proposed MPPT of the air motor power and buck duty cycle versus speed

4.4 MPPT algorithm confusion due to power disturbances

There are differences between a CAES system and a PV system; the dynamic response of the CAES is much slower than that of the PV, for example. However, there are many similarities. The shape of the power-voltage (P-V) curve of the PV is similar to the power-speed (P- ω_r) curve of the CAES. Pressure fluctuations in the CAES system produce a similar effect on the P- ω_r curve to the effect of irradiance fluctuations on a P-V curve of a PV system.

It is well known that irradiance fluctuation can cause MPPT confusion as discussed earlier [15,55,95]. For instance, Elgendy *et al.* [15] found that under certain conditions the MPPT algorithm can get confused when, for example, irradiance increases where the operating point is on the right-hand side of the original P-V curve and the new operating point moves to the left-hand side of the new higher irradiance P-V curve.

Confusion could also occur in the SS-CAES system due to pressure fluctuations. Figure 4.6 shows an example of this when using the P&O MPPT algorithm in [70]. The speed sampling period was 2s and equation (4.4) was used to calculate $\Delta P_{am}/\Delta \omega_r$.

Figure 4.6 Experiment results obtained when using $\Delta P_{am}/\Delta \omega_r$ MPPT-algorithm showing direction confusion during pressure transients

At $t = 50\text{s}$, a step change of pressure from 5 bar to 2.5 bar occurs as shown in Figure 4.6 a. The power speed characteristics of the air motor change from curve A to curve B and the operating point changes from x to y (see Figure 4.6 g). The motor slows down due to loss of pressure. As a result, both ΔP_{am} and $\Delta \omega_r$ will be negative which gives $\Delta P_{am}/\Delta \omega_r > 0$ as shown in Figure 4.6 c, which will cause the MPPT to increase the reference speed rather than decrease it as shown in Figure 4.6 e, with a resulting loss of power as shown in Figure 4.6 f.

However, if the algorithm uses the $\Delta P_{am}/\Delta D$ in Figure 4.6 d, it will make the correct decision at $t=50\text{s}$ [16].

During the steady state, when the pressure is nominally constant at 2.5 bar, the air motor output power and speed continue to fluctuate. On the occasion when high amplitudes of $\Delta P_{am}/\Delta \omega_r$ and $\Delta P_{am}/\Delta D$ are observed around the MPP, when the $\Delta \omega_r$ and ΔD are small, which is a known issue due to division by small numbers. This point is returned to in Chapter 5 for the fuzzy logic control.

4.5 Correct search direction in MPPT algorithm

In order to define the correct search direction for the maximum power point, possible speed responses due to input power fluctuations during a sampling interval, caused by pressure fluctuations, must be estimated. The dynamic of the air motor speed around the MPP (ω_{mpp}) is provided using the speed regulator with the MPPT system which is assumed to be the optimum speed ω_{op} , as shown in Figure 4.7. Such fluctuations could be caused by variations of the power input to the compressor which could be from solar or wind sources.

In Figure 4.7 (a) and (b), the input power is decreasing as indicated by the downward arrows, and in sub-figures (c) and (d) it is increasing as indicated by the upward arrows. In Figure 4.7 (a), the MPPT controller demands an increase in speed at instant k. Without the input disturbance, the speed is expected to follow the demand (the square wave curve). But if the air motor power reduces during that interval ($\Delta P_{am} < 0$), then the speed at instant k+1 may be less or greater than the previous speed reference. The figure illustrates two cases: the first case, labelled as “small positive”, is when the final speed at instant k+1 is greater than the speed at k; the second case, labelled as “small negative”, is when the final speed at instant k+1 is less than the speed at instant k. If the final speed is slightly less than the value at the previous sampling instance k then the speed change ($\Delta \omega_r = \omega_r[k+1] - \omega_r[k]$) will be slightly negative (SN) and the resultant derivative of power with respect to speed will be a big positive (BP) value and the MPPT will decide to increase the speed. However, if the speed at k+1 is slightly positive (SP) then the derivative of power with respect to speed $\Delta P_{am}/\Delta \omega_r$ will be a big negative value (BN) and the MPPT will decide to decrease the speed. If the operating power point was on the right of the MPP, then the correct decision would be to decrease the speed. In other words an MPPT algorithm using $\Delta P_{am}/\Delta \omega_r$ could

potentially make the wrong decision about the direction of the speed change due to transient power changes. A relevant argument can be made for Figure 4.7, (b-d): a power fluctuation could result in the MPPT losing direction.

Figure 4.7 Speed responses to power disturbances during a sampling interval

Figure 4.8 illustrates the air motor power and the converter duty cycle versus speed curves at different pressures of 6 bar and 4 bar; the curves were plotted using (3.1), (3.2) and (4.2). It can be seen that ΔD and $\Delta\omega_r$ are related. If $\Delta\omega_r$ decreases, ΔD will also decrease. In the same vain, ΔD will increase if $\Delta\omega_r$ goes up. For example, the “small positive” scenario in Figure 4.7 (a), the operating point is assumed to be in the vicinity of MPP1 when the pressure reduces and as a result the operating point moves to a lower level on the power speed curve. If the speed increases to point P_1 (and the duty cycle decreases to D_1), then the derivative $\Delta P_{am}/\Delta\omega_r < 0$ ($\Delta P_{am}/\Delta D > 0$) and the MPPT controller will make the correct decision to decrease the speed towards MPP2. If however, the speed reduces to point P_2 (duty cycle moves to D_2), the $\Delta P_{am}/\Delta\omega_r > 0$ ($\Delta P_{am}/\Delta D > 0$), and the controller will make the wrong decision to increase the speed, thus moving away from MPP2. However, in either case, the duty cycle D of the converter decreases and the derivative $\Delta P_{am}/\Delta D$ will be positive, suggesting that the speed should be decreased and a MPPT algorithm based on this derivative will not make a wrong decision about the direction of change of speed.

Figure 4.8 The MPP tracking with fluctuating air motor power

Table II the direction results

Descriptions	Decreased Power ($\Delta P_{am} < 0$)			Increased Power ($\Delta P_{am} > 0$)		
	scenarios			scenarios		
	a)		b)	c)	d)	
$\Delta \omega_r$	SP	SN	N	P	SP	SN
$\Delta P_{am} / \Delta \omega_r$	BN	BP	P	P	BP	BN
$\Delta \omega_{com}[k+1]$	N	P	P	P	P	N
ΔD	SN	SN	N	P	SP	SP
$\Delta P_{am} / \Delta D$	BP	BP	P	P	BP	BP
$\Delta \omega_{com}[k+1]$	N	N	N	N	N	N
$\Delta \omega_d$	N			P		

Similar discussion can be had about the remaining scenarios in Figure 4.7, when the increased power and the resultant derivatives are summarised in Table II. In some cases, using $\Delta P_{am}/\Delta \omega_r$ could also cause the algorithm to lose track. However, using the $\Delta P_{am}/\Delta D$ will consistently result in the wrong decision being made if the criteria based on Figure 4.4 are used. Fortunately, this can be corrected by observing the sign of ΔD as suggested in Table II. If $\Delta P_{am}/\Delta D > 0$ but $\Delta D > 0$, then the speed is increased. If, however, $\Delta D < 0$ then the speed is correctly decreased.

A flowchart of the hybrid P&O MPPT algorithm is illustrated in Figure 4.9. The initial speed reference is set to the minimum value. At every time step, the speed and the inductor current are measured. The speed regulator controller computes the duty cycle from (2.5). This is then used to estimate the torque and power of the air motor based on the discrete forms of equations (2.1) and (3.2). The changes in speed, power, torque, and duty cycle are then calculated by taking the difference between their current values and their values during the previous time step. If the duty cycle is greater than 95%, then the speed reference is set to the minimum speed. Based on the value of σ the controller determines whether it is in the fine or coarse tuning area. According to Table II, the derivative $\Delta P_{am}/\Delta D$ and ΔD are used to determine whether to increment or decrement the reference speed. In the coarse tuning region when $(|\Delta P_{am}| > \sigma)$, if the derivative $\Delta P_{am}/\Delta D$ is positive and ΔD is negative then the reference speed is decremented by an amount of $\Delta \omega_c$ and if the derivative $\Delta P_{am}/\Delta D$ is either negative or positive and ΔD is positive, then the reference speed will be increased by the same amount. If the absolute value of the different air motor power is below a certain threshold σ ($|\Delta P_{am}| < \sigma$), then the controller will assume that it is in the fine tuning area, and the derivative $\Delta P_{am}/\Delta D$ and ΔD are also used to determine the direction of the speed change, i.e., the speed will be incremented or decremented by a smaller value $\Delta \omega_f$. Therefore, the big step size $\Delta \omega_c$ and small step size $\Delta \omega_f$ are provided for fast convergence and accuracy to MPP. In this work, σ is the maximum change in the air motor power, which is defined around 2% of the rated air motor power. $\Delta \omega_c$ is defined as less than the width of the points between MPP and Nr_{min} related to the duty cycle 95% (see Figure 4.5) while $\Delta \omega_f$ is set at roughly 10% of $\Delta \omega_c$ and it is not less than the steady state error fluctuation of PI cascade controllers in Table I.

Figure 4.9 MPPT Flow chart

4.6 Steady state power loss estimation

The proposed MPPT strategy reduces the oscillation around the MPP in the steady state condition that is introduced by the experimental results, and adapts the steps during a transient to accurately track the MPP (using a hybrid approach) for reducing power losses. The power losses in different stages of the MPPT (steady state or transient) are given by different expressions of a PV system in [52,96]. The power harvested (P_h) in terms of the root mean square (r.m.s) values of speed ripple $\omega_{r(r.m.s.)}$ is related to the available power (P_{mpp}) in the steady state for the MPPT algorithm of the SS-CAES system. Therefore, the power reduction can be written using (3.1), (3.2) and (3.9) with respect to the power at the MPP as:

$$\frac{P_h}{P_{mpp}} = \frac{\omega_{r(r.m.s.)} T_{am}(\omega_{r(r.m.s.)})}{\omega_{mpp} T_{am}(\omega_{mpp})} = \frac{4\omega_{r(r.m.s.)} (\omega_{ro}(p_i) - \omega_{r(r.m.s.)})}{\omega_{ro}^2(p_i)}. \quad (4.6)$$

Expression (4.6) can be rewritten in the following form:

$$\frac{P_h}{P_{mpp}} = 2\lambda - \lambda^2, \quad (4.7)$$

where the speed ratio λ is given by

$$\lambda = 2 \frac{\omega_{r(r.m.s.)}}{\omega_{ro}(p_i)} = \frac{\omega_{r(r.m.s.)}}{\omega_{mpp}}. \quad (4.8)$$

To discuss the power loss caused by the P&O technique due to oscillations around the MPP at steady state conditions, we should consider the power reduction-speed ratio curve that is shown in Figure 4.10. In this figure, equation (4.7) is employed to plot the fraction of the air motor r.m.s power value over the characteristics of the air motor power output at the MPP. It can be seen that the position of the speed ratio λ will indicate the capability of the P&O MPPT algorithm. The speed ratio λ depends on the measurement speed in (4.8). It means that λ has a high capacity at around one, whereas when λ is far from one, and the MPP tracker will produce high power losses.

Figure 4.7 presents the air motor speed against the DC-shifted square wave of the SS-CAES system, a result of the MPPT-P&O algorithm using a hybrid tracking method in [70], including a period with input power fluctuations and a transient. This wave form can be estimated using the r.m.s. method. The air motor speed is given by

$$\omega_r(t) = \begin{cases} \omega_{mpp} \pm \omega_{re} + \frac{\Delta\omega_{com}}{2}; & 0 < t < \frac{T_{sm}}{2} \\ \omega_{mpp} \pm \omega_{re} - \frac{\Delta\omega_{com}}{2}; & \frac{T_{sm}}{2} < t < T_{sm} \end{cases}, \quad (4.9)$$

where ω_{re} is the difference between the optimal speed ω_{op} set by the MPP tracker of Chapter3 and the air motor speed at maximum power ω_{mpp} , $\Delta\omega_{com}$ is the constant speed step-size, and T_{sm} is the sampling period time of the MPPT algorithm.

Figure 4.10 The power reduction versus speed ratio

The DC-shifted square wave in (4.9) is determined the r.m.s. speed value, as given bellow:

$$\omega_{r(r.m.s.)} = \sqrt{\frac{1}{2T_{sm}} \int_0^{2T_{sm}} \omega_r(t)^2 dt} = \sqrt{\left(\omega_{mpp} \pm \omega_{re}\right)^2 + \left(\frac{\Delta\omega_{com}}{2}\right)^2}. \quad (4.10)$$

For example, $\Delta\omega_{com}$ is 5% of air motor speed at maximum ω_{mpp} (see half the free speed ω_{ro} in Appendix E), ω_{re} is a zero (the perfect tracking control $\omega_{op} = \omega_{mpp}$). These $\Delta\omega_{com}$ and ω_{re} are used to determine the r.m.s. speed value in (4.10) for the power reduction in (4.7) under constant pressure (6.3 bar) conditions. By using the proposed P&O, the power reduction is around 0.03%, which means that the oscillations around the MPP cause a power loss of 0.03%.

4.7 Simulation results

The mathematical models of the discharging process, including the proposed MPPT algorithm and the speed regulator are implemented using the SimPowerSystems of Matlab/Simulink as shown in Appendix D. The system parameters are shown in Appendix E. The inductor current and the generator's speed are sampled at a frequency of 20 kHz. In order to avoid the estimation of the power output during the transient response of the air motor, the sampling period of the MPPT system T_{sm} is set to be greater than the settling time of the speed regulator. For the system under investigation here, a settling time of approximately 1 s is chosen which is subsequently used for the recording of the MPPT parameters. The MPPT algorithm is fed by the measured data from the inductor current and the generator's speed, sampled at $T_{sm} = 2$ s intervals. This information is used to power the air motor by the controller. It is assumed that perfect gas in a large cylinder is discharged at isothermal conditions. Kinetic and frictional losses are ignored. Therefore, the mass flow of air that is released to the air motor is proportional only to pressure changes within the cylinder.

Figure 4. 11 Simulation results of the SS-CAES system under varying pressure conditions

Figure 4. 11 shows the speed, power and torque changes under varying pressure conditions. In the speed versus time graph, the optimal speed red curve is the speed at which the power is maximum for a given pressure as calculated from the air motor characteristics. The green speed curve is the demand speed calculated by the proposed algorithm, and the black curve is the actual measured

speed. As can be seen, following a short transient, the MPPT algorithm has successfully produced correct speed demands when pressure changes from 6 to 4 to 2 to 3 and then to 5 bar again. It should be noted that the hybrid tracking uses $|\Delta P_{am}|$ to set the coarse and fine tuning areas for changing the step size of the speed. Hence, when pressure changes from 4 to 2 bar, the speed convergence is slow as the width of the fine tuning area (based on the air motor characteristic) is greater at low pressure than at high pressure.

4.8 Experimental results

The experimental implementation of the SS-CAES system with a buck converter is controlled using a dSPACE MicroAutobox II system that can be programmed graphically using Matlab/Simulink (see Figure 4.2). The PM DC generator is a LEMAC/65167-008, (24V, 3000 rpm, 250 W). An Atlas Copco LZB 14 AR034 (100W) air motor was directly coupled to the generator. Data from an optical encoder OPB704 and current sensor LAH 25-NP were sampled at a frequency of 20 kHz. A low-pass filter with a cut-off frequency of about 10 rad/s was used to filter the current signals within the speed regulator controller. The cascade PI-speed controllers were designed as discussed earlier. The MPPT controller provides the optimal speed reference by using a sampling period time $T_{sm} = 2$ s, which was determined by estimating the settling time of the actual speed from the speed regulator design, as discussed earlier. The 100 VA buck converter used a MOSFET switching at 10 kHz and delivered power to a resistive load ($R_L=0.25\Omega$). The system parameters are as shown in Appendix E.

The efficiency of the air motor used in the experiments is 12% at 6 bar and at the maximum power point. The overall efficiency of the system from air input to electric power output is about 7%. This is similar to the efficiency of the laboratory system described in [12] which uses a similarly small air motor. The efficiency of these small CAES system is very low compared to those claimed in the literature for large systems; efficiencies of 72% were claimed in [9] and [97] as mentioned earlier. The low efficiency is primarily due to the poor efficiency of the small air motor that is used in the experiments. Higher efficiencies are possible with larger CAES systems using multi-stage turbines with preheating between expansion stages using highly efficient heat exchangers [25,26].

The experimental results of the proposed hybrid-MPPT algorithm are shown in Figure 4.12. The absolute value of the different air motor power of $\sigma=2W$ was used such that the width of the fine tuning region was $\Delta\omega_c$. Again, using $\Delta P_{am}/\Delta\omega_r$ can result in the MPPT direction of search confusion, as illustrated in Figure 4.12(c). Furthermore, $\Delta P_{am}/\Delta D$ on its own can result in MPPT confusion, as illustrated in Figure 4.12(d). However using both $\Delta P_{am}/\Delta D$ and ΔD in Figure 4.12 (e), produces the correct search direction and results. This occurs after a short transient in finding the maximum power point following each of the step pressure changes.

Figure 4.12 Experimental results obtained using the proposed MPPT-algorithm

Figure 4.13 shows the comparison of the average speed for the simulation and the experimental results using the proposed MPPT algorithm. It can be seen that the experimental and the simulation results are very close to each other, particularly for medium pressure changes and both accurately track the optimal speed curve. The tracking errors can be reduced by improving the estimation of system characteristics such as mechanical losses.

Figure 4.13 Comparison of the average speed curve between simulation and experimental results against pressure changes

Figure 4.14 The percentage of power reduction between simulation and experimental results against pressure changes

The simulation and experimental results for power losses due to the use of the MPPT-P&O algorithm at steady state is shown in Figure 4.14. In this figure, which is based on equations (3.9), (4.7), (4.8), (4.10), the constant speed step-size of about 3 rad/s and the different air motor speeds between simulation/measured and optimal speed at the MPP are used to plot the percentage of power reduction for varying pressure levels. It can be seen that the range of power reductions for the experimental results is around zero to 0.08W and for simulations it is roughly 0-0.045W.

4.9 Summary

This chapter discusses the P&O MPPT algorithm to understand its performance and its limitations in terms of the SS-CAES system. It is found that this algorithm relies on a fixed step size which affects the accuracy and dynamic convergence of the MPPT. This algorithm can also cause a wrong decision to be made when there are input power fluctuations. Using the rate of change of power with respect to speed commonly causes a loss of search direction as a result of compressed air pressure fluctuations. Using the rate of change of power with respect to the duty cycle of the dc-dc converter, it is found that the direction performs better in this respect, but it still loses the correct search direction under certain circumstances. In addition, there is an oscillation around the MPP in steady state conditions.

This thesis proposes a novel hybrid P&O algorithm. It is implemented by improving the accuracy and speed convergence of the MPP. Small speed step changes are used in the vicinity of the MPP to improve the accuracy of the search algorithm. However, relatively coarse speed step changes are used when the operating point is far from the MPP to improve the dynamic response of the controller and to increase its speed of convergence. Furthermore, the prevention of search direction when the input power fluctuates is also presented, using the rate of change of power with respect to the duty cycle of the dc-dc converter and corrected by the sign changes in the duty cycle. However, using the P&O techniques is known to have the drawback of the operating point oscillating around the MPP at steady state. This can be eliminated by the fuzzy logic control and is shown in the next chapter.

In the implementation, the duty cycle of the buck converter increases above 95%. The buck converter fails to control when the system is started and the large step pressure increases at the low speed side of the air motor power–speed curve. In rare cases (at high speed) when the duty cycle is less than 5%, it will also cause a power controller unstable. The buck converter is used to regulate the air motor speed, which requires the reference speed to be reset a minimum in order to restart the MPPT.

The overall efficiency of the system is comparatively low but this can be increased by applying multi-stage turbines with preheating between expansion stages and/or using highly efficient heat exchangers. The proposed P&O algorithm can also be applied to PV or wind turbine systems.

Chapter 5: MPPT-Fuzzy Logic Control

This chapter focuses on a fuzzy logic control approach with variable step size for MPPT in the SS-CAES system. The proposed MPPT-FLC is developed based on the MPPT-algorithm of Chapter 4: for preventing search direction confusion due to both step and ramp changes of the input power (see Figure 5.1). The proposed MPPT-FLC is validated by simulation and experimentation.

5.1 Review of variable step size MPPT techniques

This section reviews a number of studies on MPPT techniques that use a variable step size to achieve the MPP. The review can provide an understanding of their performance and limitations as well as how these techniques can be developed in a SS-CAES system.

In both [5] and [70], the P&O method, in which fixed speed step changes are used, results in the estimated MPPT fluctuating or oscillating. The estimated speed at the MPP will exhibit a limit cycle or large dither which is not desirable. Using the fine step in [70] improves this but small fluctuations remain.

To speed up convergence and reduce oscillations a variant of the P&O method is used by Liu *et al.* [98], where a variable step incremental conductance (INC) MPPT method is applied to a PV system. The step size is set to be proportional to the derivative of power with respect to voltage; if the operating point is far from the MPP, the slope of the power-voltage curve will be high and the step size will therefore be large. Near the MPPT, the slope and the step size are small.

Fuzzy logic control (FLC) is another technique that has been used for MPPT of wind energy conversion [99], and PV systems [60,91,100,101,102]. The fuzzy rule in these papers is based on P&O or its INC variant. A variable speed step size is also commonly used. Fast and accurate MPPT using a FLC based P&O with variable step size has already been demonstrated [103].

However, conventional P&O based methods suffer from losing direction or becoming confused, i.e., moving away from the maximum power point instead of moving towards it. This confusion is caused by fluctuations of the input power due to shading in the case of PV system [15], [55] and [95], pressure fluctuations when coupled to a CAES [5,12,13].

One of the drawbacks of the FLC based MPPT algorithm presented by Shiau *et al.* [94] for a PV system is that it tends to make the wrong judgment about the direction of search. This occurs as a result of input power fluctuations due to irradiance variations. This was solved by decreasing the step-size of the perturbations [104].

Recently Paz and Ordonez [52] and Kadri *et al.* [105], presented P&O based MPPT methods for PV systems that avoid search direction confusions. This is achieved by indirectly detecting a ramp change of irradiances by measuring the PV output voltage regulator error and adjusting the reference voltage in proportion to that error. Simulation and experimental results are projected which demonstrate the efficacy of the proposed algorithm, resulting in improved overall efficiency of the PV system. However, it is not clear whether this algorithm will be able to cope with step irradiance changes as they are expected to cause search direction confusion [15].

Because of the limitations of the fixed and variable step sizes, a fuzzy logic control approach and vector-fuzzy logic approach with variable step size are used for MPPT of a SS-CAES in this thesis. The proposed novel algorithm prevents search direction confusion due to both step and ramp changes of input power, as shown in Figure 5.1 below. The proposed algorithm is validated by simulation and experiment.

Figure 5.1 Configuration of the proposed discharging process with MPPT fuzzy logic

5.2 Control system

Figure 5.2 shows a block diagram of the proposed MPPT-Fuzzy logic system. In this system the MPPT-FLC uses the actual speed, the inductor current and the duty cycle of the buck converter to set the reference speed of the speed regulator. Speed regulation was chosen as it gives a faster dynamic response to disturbances e.g. irradiance fluctuations in a PV system, compared with the alternative duty cycle control method [15,55]. The speed regulator comprises two loops: an inner current loop and an outer speed loop using PI controllers.

The switching frequency of the buck converter was selected to be at least ten times the bandwidth of the current loop. A small signal averaged model of the buck converter based on the absorbed injected current method [68] was used to determine the values of the inductor [69] and to design the controllers to give the designed phase margin [78], as discussed in Chapter 2.

Figure 5.2 Block diagram of MPPT-FLC with speed reference control

5.3 MPPT-FLC of wrong judgment

Situations where the MPPT FLC has made wrong judgments in a PV system are reported with solar irradiance changes causing the loss of direction [94]. The SS-CAES system is therefore investigated for the loss of direction of the MPPT-FLC under transient pressure. For the controller, the speed, current and duty cycle from the speed regulator are sampled within 1s to estimate an increment of the air motor power and speed (ΔP_{am} and $\Delta \omega_r$) from (3.2). The triangular shape of the membership functions in [99] and the symmetrical fuzzy rule in [99,94,106,107] are used to obtain the MPPT-FLC under the input variables. The input variables of ΔP_{am} and $\Delta \omega_r$ are firstly inferred using the Sugeno method. The calculated speed reference based on the P&O method is set for the speed regulator to achieve the MPP and the MPPT-FLC confusion under a transient pressure condition, as seen in Figure 5.3.

Figure 5.3 The calculated speed reference of MPPT-FLC using the inputs of ΔP_{am} and $\Delta \omega_r$

The simulation results in Figure 5.5 illustrate the dynamic response and speed when the pressure changes from 6 to 4 bar. As can be seen, during pressure transient, the MPPT-FLC based on the

input variables ΔP_{am} and $\Delta \omega_r$ has provided the wrong speed direction, which results in slower conversion to the optimal speed (red curve).

For the other input variables, the $\Delta P_{am}/\Delta \omega_r$ in (4.4) and $\Delta \omega_r$ are also set to operate under similar transient pressures conditions, as shown in Figure 5.4. The dynamic response of $\Delta P_{am}/\Delta \omega_r$, $\Delta \omega_r$ and speed are shown in Figure 5.6 under transient pressure conditions. It can be seen that the MPPT-FLC method also leads to a wrong direction, but its deviation is somewhat shorter than when using the input variables ΔP_{am} and $\Delta \omega_r$.

Figure 5.4 The calculated reference speed of MPPT-FLC using the inputs of $\Delta P_{am}/\Delta \omega_r$ and $\Delta \omega_r$

For the issue of the slope calculation, this scenario can be found in a SS-CAES system. When using the P&O method, high amplitudes of $\Delta P_{am}/\Delta \omega_r$ and $\Delta P_{am}/\Delta D$ are obtained around the MPP with very small $\Delta \omega_r$ and ΔD values at the steady state conditions, as shown in Figure 4.6(c-d).

According to the drawbacks of the FLC based MPPT algorithm presented by Shiau *et al.* [94] for a PV system, the operating point dithers at steady state due to error caused by the division of small numbers when calculating the derivation of power with respect to voltage near the MPP. The problems could also occur in an SS-CAES system. The high amplitude at the steady state is therefore monitored by injecting a small $\Delta \omega_r$ into the MPPT-FLC controller. The simulation results indicating the dynamic response of $\Delta \omega_r$ and $\Delta P_{am}/\Delta \omega_r$ under constant pressure condition are shown in Figure 5.7. It can be seen that the injection of a small $\Delta \omega_r$ at 25s can build the high amplitude of $\Delta P_{am}/\Delta \omega_r$, as shown in Figure 5.7(b)-(c), respectively. In the speed versus time graph, the speed command (green) is estimated by the MPPT-FLC controller, the optimal speed (red) is the speed at which the power is maximum for a given pressure, and the actual speed (black) is measured. It can be seen that the high amplitude of $\Delta P_{am}/\Delta \omega_r$ at steady state produces the wrong judgment of speed change which results in high power losses and slow conversion to optimal speed.

Figure 5.5 Simulation results obtained when using the ΔP_{am} and $\Delta\omega_r$ into MPPT fuzzy logic control showing the direction confusion during pressure transient

Figure 5.6 Simulation results obtained when using the $\Delta P_{am}/\Delta\omega_r$ and $\Delta\omega_r$ into MPPT fuzzy logic control showing the direction confusion during pressure transient

Figure 5.7 Simulation results obtained when using the $\Delta P_{am}/\Delta\omega_r$ and $\Delta\omega_r$ into MPPT fuzzy logic control showing the wrong judgment during a small $\Delta\omega_r$.

5.4 The MPPT–FLC based on correct direction

The proposed fuzzy logic controller maintains the correct MPP search direction despite air motor input power fluctuations. It uses a variable speed step size: a large step away from the MPP and a small step when close to the MPP. The flowchart of the MPPT-FLC is therefore illustrated in Figure 5.8. The initial speed reference is set to the minimum value Nr_{min} . At every time step, the speed and the inductor current are measured. The speed regulator computes the duty cycle. This is then used to estimate the air motor torque and power based on the discrete forms of equations (2.1) and (3.2). The changes in air motor power and duty cycles (ΔP_{am} and ΔD) are then calculated by taking the difference between their current values and their values during the previous time step. If the duty cycle is greater than 95%, then the speed reference is set to the minimum speed value, as discussed earlier. In the rare cases (at high speed) when the duty cycle is less than 5%, the MPPT controller also resets the reference speed to a minimum in order to restart the tracking.

As discussed in section 4.4, in relation to Figure 4.6, under condition of fluctuating input pneumatic power due to pressure fluctuation the wrong search direction of the MPPT algorithm is indicated. For example, using $\Delta P_{am}/\Delta \omega_r$ results in the MPPT losing direction (or becoming confused). The sign of $\Delta P_{am}/\Delta D$ on the other hand gives the correct direction with the sign of ΔD . The proposed fuzzy logic MPPT therefore uses ΔP_{am} and ΔD to determine the direction of search i.e. whether to increase or decrease the reference speed.

Furthermore, to overcome the problem of noise amplification resulting from the division of small numbers when calculating $\Delta P_{am}/\Delta D$ near the MPP as discussed earlier and shown in Figure 4.6 d, the proposed system uses an alternative quantity related to ΔP_{am} , ΔD and $\Delta P_{am}/\Delta D$.

Figure 5.8 MPPT-FLC Flowchart

Instead of using $\Delta P_{am}/\Delta D$ directly, which could have a false high amplitude near the MPP due to the division of small quantities, the proposed system uses

$$\Delta P^* = \text{sign}(\Delta P_{am} / \Delta D) \times \left| \frac{\Delta P_{am}}{\Delta P_{am,\max}} \right|. \quad (5.1)$$

The above ensures that ΔP has the correct sign but prevents its magnitude from becoming large due to noise amplification. ΔP^* will have a value between -1 and 1 when operating in the variable speed step region. $\Delta P_{am,\max}$ is defined in Figure 5.10.

For convenience, the change in the duty cycle D is also normalised, as follows:

$$\Delta D^* = \frac{D[k] - D[k-1]}{\Delta D_{\max}} = \frac{\Delta D}{\Delta D_{\max}}, \quad (5.2)$$

where $\Delta D_{\max} = |D_{\max} - D_o| = |D_o - D_{\max}|$, as defined in Figure 5.10. This results in $|\Delta D|$ being less than 1 in the variable speed region in Figure 5.10.

Figure 5.9 shows the membership functions of the variable ΔP^* and ΔD^* as well as the normalised change in speed $\Delta \omega_r^*$, which is defined as:

$$\Delta \omega_r^* = \frac{\omega_r[k] - \omega_r[k-1]}{\Delta \omega_{r\max}}, \quad (5.3)$$

where $\Delta \omega_{r\max} = |\omega_{r\max} - \omega_o| = (\omega_o - \omega_{r\max})$.

There are 8 graphical shapes in the membership functions for ΔP^* or $\mu(\Delta P^*)$. Symmetrical Triangular functions are used for Negative Medium (NM), Negative Small (NS), Zero (Z) and Positive Small (PS), Positive Medium (PM). A trapezoidal function is used for the Negative Big (NB) membership. The PB function uses an asymmetric triangular function between 2/3 and 1. The Positive Extra (PE) is a rectangular membership function including ΔP^* value between 1 and 3. The rationale for selecting the shape and range of these membership functions will become clear later.

The membership function of ΔD^* or $\mu(\Delta D^*)$ includes two symmetric triangular functions NS and PS, two asymmetric triangular functions NZ, PZ and two trapezoidal functions P and N.

Singleton membership functions are used for $\Delta \omega_r^*$ or $\mu(\Delta \omega_r^*)$. Singletons are recommended to speed up the response of the controller [108,109].

The value of three membership functions, $\mu(\Delta P^*)$, $\mu(\Delta D^*)$ and $\mu(\Delta \omega_r^*)$ is between 0 and 1.

Figure 5.9 The corrected membership functions for (a) the input of change in air motor power (b) the input of change in duty cycle (c) the output variable step-size speed

5.5 Fuzzy rule

The fuzzy rule is a design of the relationship between ΔP^* in (5.1) and ΔD^* in (5.2) to set $\Delta \omega_r^*$ in (5.3) which is presented in the table rule. This rule will be designed by considering the fuzzy rule based on constant pressure and the power disturbance, as discussed in the following section.

5.5.1 Fuzzy rule under constant power

The fuzzy rules relating $\Delta \omega_r^*$ to ΔP^* and ΔD^* are shown in Table III. In the absence of pressure fluctuations, the curve in Figure 5.10 will not change and the operating points will correspond to the speed reference value under steady state condition, when ΔP^* is negative, the system will be operating either in Region 1 or Region 1F in Figure 5.10. Under these conditions, regardless of the value of ΔD^* , $\Delta \omega_r^*$ must increase to move the operating point towards the MPP i.e., $\Delta \omega_r^*$ must be positive in these regions. The higher the values of ΔP^* and ΔD^* , the bigger the value of $\Delta \omega_r^*$ as shown in the first 3 columns of Table III. When ΔP^* is positive, the operating point will be on the right hand side of the MPP in Regions 2 and 2F and, regardless of the value of ΔD^* , the speed needs to be decreased. In other words, it should be negative but its value depends on how far it is from the MPP. The higher the values of ΔP^* and ΔD^* , the larger the value of $\Delta \omega_r^*$. For example, when ΔP^* is PB and ΔD^* is N then $\Delta \omega_r^*$ will be NB. If ΔP^* is PS and ΔD^* is NS then $\Delta \omega_r^*$ will be NS. When the operating point is near the MPP, i.e., ΔP^* is within the Z region, $\Delta \omega_r^*$ will be also in the Z region (Region 3), i.e., very small.

Table III Fuzzy rule

$\Delta \omega_r^*$	ΔP^*						
ΔD^*	NB	NM	NS	Z	PS	PM	PB
N	PB	PM	PS	Z	NS	NM	NB
NS	PM	PS	PS	Z	NS	NS	NM
NZ	PM	PS	PS	Z	NS	NS	NM
PZ	PM	PS	PS	Z	NS	NS	NM
PS	PM	PS	PS	Z	NS	NS	NM
P	PB	PM	PS	Z	NS	NM	NB
Region	Region 1, Region 1F,			Region 3	Region 2, Region 2F

Figure 5.10 Fuzzy logic control membership functions mapped onto the air motor power and duty cycle – speed curve

5.5.2 Fuzzy rule in power disturbance

Under severe pressure fluctuations, the operating curves of the air motor power and the converter duty cycle will change as illustrated in Figure 5.11. In this figure, it is assumed that there was a sudden loss of pressure and the characteristics changed from curves a and a_1 to b and b_1 . Assuming that the system was already at the MPP on curve A, the loss of pressure results in the operating point moving to the right-hand side of the new power curve at point b when the system settles into steady state constant speed operation again. Constant speed is maintained by the controller through the reduction of the duty cycle from point a_1 to point b_1 . The change in ΔP_{am} is therefore negative and so is the change in ΔD . As a result $\Delta P_{am}/\Delta D$ and hence ΔP^* will be positive. Under this condition, the FL-MPPT rules will make $\Delta \omega_r^*$ negative-NB or NM depending on the value of ΔD^* and ΔP^* .

Figure 5.12 illustrates a scenario when the pressure increases suddenly, or when the system starts. Under this condition, $\Delta P_{am} > 0$ and $\Delta D^* > 0$ and hence $\Delta P^* > 0$. Therefore, the right-hand side of the MPP will be corrected in the positive extra region, as shown in Table IV. If ΔP^* is in the PE region, then the fuzzy rules will make a correction by increasing the reference speed, i.e., by assigning $\Delta \omega_r^*$ to be PM or PB depending on the value of ΔD^* .

Figure 5.11 The MPP tracking with decreased air motor power

Figure 5.12 The MPP tracking with increased air motor power

Table IV Fuzzy rule for correcting the search direction

$\Delta\omega_r^*$	ΔP^*							
ΔD^*	NB	NM	NS	Z	PS	PM	PB	PE
N	PB	PM	PS	Z	NS	NM	NB	NB
NS	PM	PS	PS	Z	NS	NS	NM	NM
NZ	PM	PS	PS	Z	NS	NS	NM	NM
PZ	PM	PS	PS	Z	NS	NS	NM	PM
PS	PM	PS	PS	Z	NS	NS	NM	PM
P	PB	PM	PS	Z	NS	NM	NB	PB
Region	Region 1, Region 1F			Region 3	Region 2, Region 2F			Fluctuated pressure or staring

However, if ΔP^* is less than PE, then the system will become confused and will temporarily move in the wrong direction. However, this is expected to be a run occurrence and when it occurs under say small pressure fluctuation conditions, the operating point will still be close to the MPP and the loss of efficiency will be small.

Defuzzification is the last step in the MPPT-FLC controller. A quantifiable result is converted into a single number as $\Delta\omega_r^*$. The membership weighted average (WTA) [108] is

$$\Delta\omega_r^* = \frac{\sum_{i=1}^N \alpha_i \mu(\Delta\omega_{ri}^*)}{\sum_{i=1}^N \alpha_i}, \quad (5.4)$$

where $\mu(\Delta\omega_{ri}^*)$ of Figure 5.9(c) is the position of singleton output in rule i , α_i is the firing strength of AND operator which uses the minimum value between $\mu(\Delta P_i^*)$ and $\mu(\Delta D_i^*)$ of Figure 5.9(a-b) in rule i , and N is the number of rules (in this work, $N=48$).

The adaptive speed reference is also determined using a scaling factor ($\Delta\omega_{r\max}$) to update in real-time with current actual speed for accuracy and fast convergence to the MPP, as shown:

$$\omega_{ref} = \omega_r + \Delta\omega_{r\max} \cdot \Delta\omega_r^*. \quad (5.5)$$

As can be seen, the operating point is far from MPP when the large step-size is defuzzified by $\Delta\omega_r = \pm 1$.

5.6 A vector-fuzzy logic method

For the MPPT-FLC described in section 5.4, the method is somewhat complicated with asymmetrical membership functions and rules and it does not fully solve the confusion problem. A vector-fuzzy logic is alternatively proposed in this section to eliminate the confusion under pressure fluctuations. The standard fuzzy rule of the MPPT table is conceptually vectorised into four quadrants, as shown in Figure 5.13 and Table III. In this figure the ΔP^* - ΔD^* plane is based on the air motor power and the duty cycle-speed curves of Figure 5.10 and Table III, divided into several regions corresponding to the different operating regions of the MPPT. Region 1P (P is represented by ΔD^* and is positive, as seen in Table III) corresponds to the case when the operating point is on the left-hand side of the MPP (ΔP^* is negative and ΔD^* is positive) when the direction of $\Delta \omega_r^*$ is positive, as shown by an arrow up. Region 2P (P is represented by ΔD^* and is positive, as seen in Table III) in the fuzzy rule table is when ΔP^* is positive (operating point on the right-hand side) and ΔD^* is also positive when the downward arrow is the negative direction of $\Delta \omega_r^*$. Region 2FN is when the operating point is in the fixed step region with ΔD^* being negative and ΔP^* being positive, as shown by the arrow down. Region 2N and Region 1N occur when ΔP^* is positive and negative, respectively. But ΔD^* is negative in all cases. In Figure 5.13, the MPP occur at the origin of the ΔP^* - ΔD^* plane. When say ΔP^* is NB and ΔD^* is P, the operating point in the ΔP^* - ΔD^* plane will be the (1,-1) point. The MPPT system will aim to move from approximately the (1,-1) point to the MPP at (0, 0) along the dashed red arrow.

Figure 5.13 The vector of speed output $\Delta \omega_r^*$ consequence under input power fluctuations conditions

Figure 5.14 The membership function of a vector-fuzzy for a) the input of ΔP^* b) the input of ΔD^* and c) the output of $\Delta \omega_r^*$

The membership functions of ΔP^* consist of five symmetrical triangular functions: NM, NS, PS, PM and Z. The NB and PB use the trapezoidal functions. The membership function of ΔD^* also uses two symmetrical triangular functions for NS and PS. One of those is a symmetrical triangular function Z which combines both PS and NS. Singleton membership functions are also used in this technique, as shown in Figure 5.14.

Under normal conditions, when there are no rapid fluctuations of air pressure or air motor input power, the fuzzy rules in Table III are also used. However, these rules are modified under the condition of input power fluctuations to avoid confusion. If there is a sudden decrease of pressure as illustrated in Figure 5.11, then $\Delta P^* < 0$, $\Delta D^* < 0$ and the system will therefore be either in Region 2FN or Region 2N (see Figure 5.15). Using the rules in Table III, the speed will be reduced and the operating point will move along the Region 2FN or Region 2N vector in Figure 5.15 to point c in Figure 5.11. As a result both ΔP^* and ΔD^* will become positive. Accordingly, if the system continues to move along the Region 2FN and 2N vector, it will make the wrong judgment. To avoid this, the system must switch to regions 2P and move along the corresponding vector to the MPP. If the system overshoots the MPP, ($\Delta P^* < 0$, $\Delta D^* > 0$), then the system should operate using the Region 1P rules. i.e., switch from vector 2P to vector 1P.

If the input pressure and power increase suddenly as illustrated in Figure 5.12, then $\Delta P^* > 0$ and $\Delta D^* > 0$ and the operating point will be in the first quadrant of the $\Delta P^* - \Delta D^*$ plane and $\Delta \omega_r^* > 0$ (as a result of the increased pressure). But if the corresponding Region 2P rules are used, then a wrong judgement will be made and the MPPT will be confused. In this case, the system should use the region 1P rules (Quadrant IV) or Region 1N rules (Quadrant III) to direct the search towards the MPP by correcting with the negative ΔP^* in (5.1) or negative both ΔP^* in (5.1) and ΔD^* in (5.2), as shown in the right hand side of Figure 5.15.

Figure 5.15 The data input management with a vector-fuzzy logic

5.7 Simulation results

The mathematical models of the discharging process including the proposed MPPT-FLC and the speed regulator were implemented using the SimPowerSystems and Fuzzy Logic Toolbox of Matlab/Simulink [82,109], as shown in Appendix D. The system parameters are shown in Appendix E. The inductor current and the generator's speed are sampled at a frequency of 20 kHz. The MPPT-FLC is fed by the measured data from the inductor current and the generator's speed, sampled at $T_{sm} = 1$ s intervals (greater than the settling time of the speed regulator as seen in Chapter 2). It is assumed that perfect gas in a large cylinder is discharged at isothermal conditions. Kinetic and frictional losses are ignored. Therefore, the mass flow of air that is released to the air motor is proportional only to pressure changes within the cylinder.

5.7.1 MPPT-FLC based on correct direction results

Figure 5.16 shows the speed, power and torque results under varying pressure conditions. In the speed versus time graph, the optimal speed red curve is the speed at which the power is maximum for a given pressure as calculated from the air motor characteristics. The green dashed curve is the demand speed calculated by the proposed algorithm, and the black speed curve is the actual speed.

Figure 5.16 Simulation results obtained using the MPPT-FLC

As can be seen, following a short transient, the MPPT-FLC has successfully produced correct speed demands when pressure changes from 6 to 4 to 2 to 3 and then to 5 bar again. During the

steady state, the actual speed of the air motor is very smooth with negligible fluctuation compared to a system with fixed speed step. This clearly illustrates the benefits of the variable speed step fuzzy logic approach.

5.7.2 Vector-fuzzy logic results

The simulation results of the vector fuzzy logic method are shown in Figure 5.17. The problem vector in quadrant I was moved to quadrant IV using a quadrant selection (QS). The value $QS = -1$ was used to correct a ΔP^* under increased pressure or starting conditions. The SS-CAES system was tested by setting with a large step pressure change from a starting pressure to 5 bar and then decreasing to 3 bar at 20s. The pressure turned back to 6 bar again at around 40s. The small step pressure changes can be seen at 10s and 30s (see Figure 5.17 a). The value of $\Delta P_{am,max} = 1.5 \text{ W}$ was used to define the width of the varying step size area. Again, using $\Delta P_{am}/\Delta D$ can result in the conventional MPPT direction of search confusion as illustrated in Figure 5.17 (c). However, using both ΔP^* and ΔD^* in Figure 5.17 (d-f), produced the correct search direction and they needed a quadrant selection to correct themselves during the increased pressure changes. After a short transient, the vector-fuzzy logic results in finding the maximum power point following each of the step pressure changes. The performance of the vector-fuzzy logic approach can provide a high performance MPPT as a result of the elimination of confusion under input power fluctuation conditions.

Figure 5.17 Simulation results obtained using the proposed vector-fuzzy logic

5.8 Experimental results

The experimental implementation of the discharging process took place with a buck converter using a dSPACE MicroAutobox II system that could be programmed graphically using Matlab/Simulink, as shown in Figure 5.2. The PM DC generator was a LEMAC/65167-008, (24V, 3000 rpm, 250 W). An Atlas Copco LZB 14 AR034 (100W) air motor was directly coupled to the generator. Data from an optical encoder OPB704 and current sensors LAH 25-NP were sampled at a frequency of 20 kHz. A low-pass filter with a cut-off frequency of about 10π rad/s was used to filter the current signals within the speed regulator controller. The cascade PI-speed controllers were designed as per the discussion in Chapter 2. The MPPT controller provided the optimal speed reference by using a sampling period time of $T_{sm} = 1.5$ s, which was determined by estimating the settling time of the actual speed from the speed regulator design, as seen in Figure 2.16. The 100 VA buck converter used a MOSFET switching at 10 kHz and delivered power to a resistive load ($R_L=0.25\Omega$). The system parameters are shown in Appendix E.

The experimental results of the proposed MPPT-FLC are shown in Figure 5.18. The value of $\Delta P_{am} = 2$ W was used such that it determined the width $\Delta\omega_{r,max}$. Again, using $\Delta P_{am}/\Delta\omega_r$ can result in MPPT direction of search confusion as illustrated in Figure 5.18 (c). $\Delta P_{am}/\Delta D$ on its own can also result in MPPT confusion as illustrated in Figure 5.18(d). However using both ΔP and ΔD^* in Figure 5.18 (e) and (f), produces the correct search direction and results in a short transient in finding the maximum power point, following each of the step pressure changes.

Figure 5.18 Experiment results obtained using the proposed FLC-MPPT

For the steady state condition, the MPP-FLC can eliminate the speed oscillation around the MPP, as shown in Figure 5.19. It can be seen that the short transient and smooth speed are achieved using a variable step-size of MPPT-FLC when pressure suddenly drops from 5 bar to 2.5 bar.

MPPT-FLC experimental results can be kept in the same direction when the pressure dramatically changes from 6 bar to 2 bar and then back to 6 bar, as shown Figure 5.20. It can be seen that the large step-size in speed changes can maintain the fast searching direction, either due to decreased or increased pressure. The small step-size in speed changes is also switched to use when the pressure is around the constant value of 2 bar.

The average speeds for the simulation and the experimental results using the proposed MPPT-FLC are compared in Figure 5.21. It can be seen that the experimental and simulation results are close to each other, particularly from low to medium pressure changes and both accurately track the optimal speed curve. The tracking errors can be reduced by improving the estimation of the system characteristics such as mechanical losses.

Figure 5.19 Experiment results obtained when using the proposed FLC-MPPT showing the improvements in transient and steady state for step pressure changes

Figure 5.20 MPPT-FLC experimental test under a ramp of pressure changes

Figure 5.21 Comparison of the average speed curve between simulation and experimental results against pressure changes

Figure 5.22 The percentage of power reduction between simulation and experimental results against pressure changes

Figure 5.22 demonstrates the power losses of the simulation and experimental results of the MPPT-FLC at steady state conditions. In this figure, equations (3.9), (4.7), (4.8), and (4.10) are used to plot the percentage of power reduction for varying pressure levels. It can be seen that the range of power reduction for both experimental and simulation results is highly accurate around middle pressure values. The proposed tracker has a high efficiency with power losses of around 1% for experimental results and 0.2% for simulation at low pressure values. The efficiency losses of the MPPT tracker at high pressure values are lower which are roughly 0.6% for measurement and 0.5% for simulation. The differences between the simulation and measured results may be caused by the freezing of water vapour in the air motor and the power converter efficiency drop which happened a number of times during the experiment.

5.9 Summary

The reviewed variable step size MPPT techniques indicated that confused direction and wrong judgement commonly occurred in a FLC based on the P&O method in a PV system. These limitations also happened in the SS-CAES system, according to the simulation results in section 5.3. Fuzzy logic control was then applied with MPPT in the SS-CAES system in order to eliminate these problems. In doing so, two key approaches were focused on and these were fuzzy logic control and vector-fuzzy logic control. The fuzzy logic control was used to solve the confused direction using $\Delta P_{am}/\Delta D$ and ΔD to determine the direction of search. Unfortunately, the calculation of $\Delta P_{am}/\Delta D$ that was close to the MPP caused noise amplification due to the division by a small number. ΔP_{am} and sign of $\Delta P_{am}/\Delta D$ were thus together taken to be ΔP^* for preventing the noise amplification rather than only using $\Delta P_{am}/\Delta D$. The fuzzy rule and membership function were used based on ΔP^* and ΔD^* (where: ΔD^* is per unit of ΔD) to design the variable step size $\Delta \omega$. However, if ΔP^* is less than the positive extra (PE) region of the membership function, the system will then confuse its direction under small pressure fluctuation conditions. The operating point will still lose its direction towards the MPP, but the loss of efficiency will be small.

Vector-fuzzy logic approach was next used to simplify the previous approach in that the standard fuzzy rule was vectorised into four quadrants and hence a vector problem was solved under input power fluctuations. The problematic vector can be found at quadrant I when the operating point is moved up to the new higher pressure (including small and large pressure fluctuations) of the power-speed curve. The problematic vector can be moved into the similar direction of quadrant III or quadrant IV to achieve the MPP tracking.

The power losses were further reduced around 1% when the system operated at low pressure. Although the MPPT-FLC can smooth the speed around the MPP, but the accuracy of the tracking power is lower than the MPPT-P&O algorithm. This happened because the average value of the

MPP was defuzzified based on the employed weighted average method, while the P&O-algorithm measured the output power directly to set the MPP.

The proposed MPPT-FLC may also be used in PV or wind turbine systems.

Chapter 6: Improved SS-CAES using a buck-boost converter, a hybrid P&O and an incremental inductance INC-MPPT

The limitation of the buck converter with regard to the controllable speed-range can be overcome by using a buck-boost converter instead. This chapter presents the initial work and an improved P&O MPPT system is also presented. The system uses an incremental inductance (INC) approach. This system eliminates the problematic operating point dither.

6.1 Speed regulator for SS-CAES system

The speed regulator for SS-CAES system is developed from Chapter 2: due to the fact that the increased duty cycle of the buck converter above 95 % band forces the power controller to become unstable. It further causes the fixed step area of the left hand side of the power-speed curve to be narrow especially if the efficiency of the buck converter is low. Alternative converters such as buck-boost and boost converters have different characteristics and further work is needed to explain the potential for using these to improve the performance of the speed regulator. The following section discusses this in more detail.

6.2 Power converter under duty cycle criteria conditions

To discuss the conventional power conversion of the speed regulator controller, consider the power-speed and duty cycle-speed curves that are illustrated in Figure 6.1. In this figure, the air motor shaft power at the rated pressure is plotted as a function of speed using equation (3.2). For the duty cycle of the power converter versus speed graphs, the mechanical to electrical power conversion is determined by delivering the output power to a resistive load R_L and obtaining the power losses, i.e.,

$$P_{am} = \frac{(K_m \omega_r M_v)^2}{R_L} + P_{losses} , \quad (6.1)$$

where M_v of a buck converter is $\eta_c D$, M_v of a boost converter is $\eta_c/(1-D)$ and M_v of a buck-boost is given by $\eta_c D/(1-D)$ [63].

The duty cycle of buck, boost and buck-boost converters are then plotted as a function of speed in Figure 6.1 using (6.1), (3.2) and (3.1) under the rated pressure of the air motor condition. In Figure 6.1, the duty cycle-speed curves assume that the output power is 100 W, the power converter efficiencies are 90% and friction losses (P_{losses}) are negligible. It can be seen that the duty cycle of

the buck converter curve (blue), the boost converter curve (pink) and the buck-boost converter curve (red) are restricted by the stability of the speed regulator for maintaining the duty cycle criteria within 5% to 95%. Its obvious affect is that the controller cannot set the reference speed to maintain the speed of the buck converter which is less than the minimum value of Nr_{min} at the low speed side and when the duty cycle is above 95%. For the high speed side, the boost converter cannot regulate the speed more than the maximum reference speed of Nr_{max} , if the duty cycle of the boost converter is less than 5%. These unstable areas will correspond to the decreased efficiency of the buck converter and the selected voltage ratios of the boost converter. It seems that the buck-boost converter can solve the problem of maintaining both low and high speed sides.

Figure 6.1 Air motor power and duty cycle of buck, buck-boost and boost converters versus speed

6.3 Power converter under power fluctuation conditions

Due to the fact that the power converter can only operate under a limited duty cycle (5%-95%), this will principally affect the speed regulator performance when there are high power fluctuations. The conventional power converter should therefore account for a suitably wide range of speed control. The air motor power and the comparison of the duty cycle curves between a buck converter and a buck-boost converter as a function of speed under decreasing pressure from 6 to 2 bar and again returning to 6 bar conditions are shown in Figure 6.2. In the duty cycle versus speed graphs, the duty cycles of the buck and buck-boost converters change their operating points from D_1 , D_2 , D_3 , D_4 to D_1^* , D_2^* , D_3^* , D_4^* in order to maintain the speed at MPP1 and MPP2 of the air motor power

curves for 6 bar and 2 bar. It can be seen that the stable points of D_1 and D_3 of the buck and buck-boost converters are reduced to D_1^* and D_3^* , respectively for regulating the speed at the MPP1, when the air motor power is decreased from 6 to 2 bar. Both converters can work well under the discharging pressure from the cylinder. For increased air motor power, the buck-boost converter can be stabilized under the increased duty cycle D_4 to D_4^* from the similar speed curve at its MPP2 of the air motor power curve 2 bar to 6 bar. However, the buck converter cannot maintain the speed when the duty cycle points D_2 at the MPP2 and moves up to above 95% of D_2^* on the air motor power curve of 6 bar. For this scenario in [16] it has been suggested that the speed reference should turn it to the minimum value of $N_{r_{min}}$. The MPPT algorithm will result in slower conversion to the optimal speed and an increase in power losses. Furthermore, the system will be unstable when the efficiency of the buck converter is decreased due to an increase in the heating up of the power switch.

Figure 6.2 Air motor power and duty cycle of buck and buck-boost converters versus speed under power fluctuation

The boost and buck-boost converters under similar conditions are now discussed. The duty cycle of both converters and the air motor power curves are plotted as a function of speed in Figure 6.3. The duty cycle of buck-boost and boost converters at D_3 , D_4 , D_5 , D_6 points are moved to D_3^* , D_4^* , D_5^* , D_6^* points on MPP1 and MPP2 under decreased/increased pressure conditions. Both converters can maintain the speed at MPP2 under increased pressure from 2 bar to 6 bar. In response to a decrease in air motor power, the boost converter cannot maintain the speed at MPP1 when the reduction in

duty cycle from D_5 to D_5^* is less than 5%. This situation is dealt with in [80] by setting a reference speed at the lower speed side for keeping the wind system stable, when the MPPT strategy works at high-wind velocities. However, the proposed MPPT is normally applied at the wind speed below the rated value, but the algorithm fails to optimize the MPP due to large fluctuations in the wind power [59]. The results also show an increase in the slow conversion to the MPP and increased power losses.

Figure 6.3 Air motor power and duty cycle of boost and buck-boost converters versus speed under power fluctuation

Therefore, the buck-boost converter is going to suit maintaining speed regulation under a wide range of air motor power fluctuations.

6.4 Control system

According to the limitations of the buck and boost converter above, in this section an absorbed injected current method is directly applied to a buck-boost converter cascaded with the PM DC generator of an SS-CAES system (see Figure 6.4) which is analysed without using the Taylor series estimation (mainly, for avoiding numerical errors). The small signal of the overall model can be designed using close loop controllers with directly measured parameters such as the generator speed. The proposed speed regulator and an improvement on the MPPT strategy in [16] will be presented to validate the simulation results in the last section

6.4.1 Small signal model of the overall system

The small signal model was created based on the frequency domain transformation of (2.1), (2.2) and the buck-boost converter model. It is given by

Figure 6.4 The speed regulator with buck-boost converter for a SS-CAES system

$$M_v = \frac{V_o}{E_{ag}} = \frac{\eta_c D}{1 - D}. \quad (6.2)$$

The peak-to-peak inductor ripple current is chosen to approximate the inductor of the buck-boost converter [69]. It given by

$$\Delta i_L = \frac{E_{ag} D T_s}{L}. \quad (6.3)$$

The high capacitor value is used to filter a load voltage [69]. It is determined by

$$C_o = \frac{i_o D T_s}{\Delta v_o}. \quad (6.4)$$

Neglecting the copper losses within the DC generator, the switching waveform of the diode current (i_d) is related to the armature current (i_{ag}) in Ang S. and Oliva A. (2005:44) [69] which is simplified as a function of the voltage transfer function. It is given by

$$I_{ag}(s) = \frac{M_v}{\eta_c} I_d(s). \quad (6.5)$$

The output impedance (C_o and R_L in parallel) is given by

$$G_{st}(s) = \frac{V_o(s)}{I_d(s)} = \frac{R_L}{1 + sR_L C_o}. \quad (6.6)$$

It is also based on the average diode current (i_d) in Figure 6.4, using the injected-absorbed current method under the continuous mode condition [63]. The PM DC generator with buck converter model in [16] is an improved model using the buck-boost converter, as follows:

The transfer function of the input voltage source $E_{ag}(s)$ is the disturbance effective from the air motor speed to the diode current $I_d(s)$ which is given by

$$G_1(s) = \frac{1}{r_{ag}(1+M_v)} \left(1 - e^{\frac{-M_v T}{\tau(1+M_v)}} \right) \left(1 + \frac{1}{T} G_{com}(s) \right). \quad (6.7)$$

The transfer function of the output voltage $V_o(s)$ to $I_d(s)$ is

$$G_2(s) = -\frac{1}{L(1+M_v)^2} \left(\frac{T}{2} + G_{com}(s) \right). \quad (6.8)$$

Finally, the transfer function of the duty cycle $D(s)$ to $I_d(s)$ is

$$G_3(s) = \left(\frac{1}{r_{ag}} \left(\left(\frac{T}{\tau(1+M_v)} + 1 \right) e^{\frac{-M_v T}{\tau(1+M_v)}} - 1 \right) E_{ag} \right) + \frac{G_{com}(s)}{\tau(1+M_v)} \left(\frac{E_{ag}}{r_{ag}} e^{\frac{-M_v T}{\tau(1+M_v)}} - e^{\frac{-M_v T}{\tau(1+M_v)}} I_m + \frac{\tau V_o}{L} \right), \quad (6.9)$$

$$- \left(\left(\frac{T}{(1+M_v)} + 1 \right) e^{\frac{-M_v T}{\tau(1+M_v)}} I_m + \frac{TV_o}{L(1+M_v)} \right)$$

where

$$G_{com}(s) = \frac{e^{\frac{-M_v T}{\tau(1+M_v)}}}{\left(s - \frac{1}{T} \left(e^{\frac{-M_v T}{\tau(1+M_v)}} - 1 \right) \right)},$$

τ is the time constant (L_t/r_{ag}), L_t is the sum of inductance of the basic converter in continuous mode L and the inductance of the generator rotor winding L_{ag} , C_o is the output capacitance, i_o is the average output current, I_m is the minimum inductor current ($I_m > 0$), T is the time period of switching, R_L is the load resistance and r_{ag} is the armature resistance. The overall system model consists of equation (2.1), (2.2), (6.2) and (6.9) that are established from the block diagram shown on the right-hand side of Figure 6.5.

Figure 6.5 Speed regulator with PI controller and the small-signal of SS-CAES system

6.4.2 PI controller

For reference speed control, an output speed is measured from the proposed system model to adjust the duty cycle ratio of the buck-boost converter, as shown in Figure 6.5. The open loop transfer function of the input duty cycle to the output speed $G_{\omega p}(s)$ is

$$G_{\omega p}(s) = \frac{\omega_r(s)}{D(s)} = \frac{-M_v K_e G_3 G_d}{\eta_c (1 + (G_2 G_{st}) + (M K_m K_e G_1 G_d))}, \quad (6.10)$$

where

$$G_d(s) = \frac{1}{J_t s + B_t}.$$

In this section, root locus is presented for a ranges of stabilities and instabilities when the closed-loop system parameter is varied in the graphical format. A closed-loop feedback control system of (6.10) is shown by

Figure 6.6 Closed-loop system of SS-CAES

According to Figure 6.6, the PI controller is determined, using the final value theorem to estimate the steady-state error when the speed reference is a step input, i.e.,

$$e_{step}(\infty) = \frac{1}{1 + \lim_{s \rightarrow 0} G_{\omega p}(s)}. \quad (6.11)$$

The PI controller, represented by $G_{c\omega}(s)$, is given by

$$G_{c\omega}(s) = K_P + \frac{K_I}{s} = K_P \left(\frac{s + (K_I / K_P)}{s} \right), \quad (6.12)$$

where K_P is the proportional gain and K_I is the integral gain.

The pure gain K_P of (6.12) is monitored by assuming a zero value for K_I . The characteristic equation of Figure 6.6 is

$$1 + K_P G_{\omega p}(s). \quad (6.13)$$

The system parameters in Table E.4 and (6.13) are plotted for the root locus as shown in Figure 6.7.

Figure 6.7 Root locus for a reference speed control utilizing a positive and negative gain K_P of the proportional controller

It can be seen that the system is unstable for $K_P \geq 0$ but stable for $K_P < 0$, as shown in Figure 6.7 (a) and (b), respectively. However, the system needs an integral K_I controller that can be determined

by estimating the steady state error of (6.11). According to the stability criteria in Figure 6.7, the negative values of both K_P and K_I in (6.12) can therefore stabilize the system.

To select the parameter K_P and K_I , a phase margin between 30° and 60° and a gain margin greater than 8 dB are required using a Bode plot design [78,79]. A sampling frequency (f_{sc}) of 1 kHz was selected to be at least ten times faster than the open-loop bandwidth [73]. The discrete transfer functions of the system were derived assuming that a zero-order hold (ZOH) was used, and the Bode diagram method was used to select the parameters of the $G_{c\omega}(z)$ controller. Equation (6.10) was plotted on a Bode diagram with discrete transfer functions of the system with negative gain - $G_{\omega p}(z)$, as shown in Figure 6.8. It can be seen that the system $G_{\omega p}(z)$ is stabilised by including the negative of the controller $G_{c\omega}(z)$, to achieve the required stable gain and phase margins [78,79]. In this case, the design values of the PI controller based on the open loop transfer function of the negative $G_{\omega p}(z)$ provide the gain of $K_P=0.0074$ and $K_I=0.0425$ at the selected phase margin of 50° and crossover frequency of 8.26 rad/s.

Figure 6.8 Bode plot design of the open-loop transfer function of the speed with the negative gain $G_{\omega p}(z)$ and obtaining controller $G_{\omega p}(z) * G_{c\omega}(z)$

6.4.3 MPPT controller

To improve the performance of the speed regulator under wide input power fluctuation conditions, the MPPT-P&O algorithm in [16] is developed for giving a fixed speed and variable speed step-sizes, as will now be discussed in this section.

Conventional MPPT strategies have been used for searching the MPP by periodically changing the speed and measuring the output power. It is generally accepted that wrong directions of MPPT strategies are obtained under power fluctuations. This results in energy losses during the confused direction and recovery periods. In [16] a hybrid searching of the P&O method has been proposed that prevents a confused direction due to the input power fluctuation occurring in the time interval of the speed data sampling of SS-CAES systems. The method uses fine and coarse search steps to increase the speed of convergence with high accuracy. This algorithm uses big step sizes in the speed change, when the search point is far from the MPP. The small step sizes in speed changes are then continuously used to increase the precision, when the operating point gets close to the MPP. For preventing movement in the wrong direction, the derivative of the air motor power with respect to the duty cycle changes ($\Delta P_{am}/\Delta D$) was implemented along with the observed direction of ΔD . However, the drawback of the oscillation around the MPP was still observed at steady state conditions.

Figure 6.9 The hybrid P&O and INC –MPPT flowchart

In order to eliminate the imperfect operation at the steady state of a P&O technique, the incremental conductance (INC) algorithm, which is simply a variable step-size method, has been proposed. The conventional INC provides a variable step-size which is based on the product of the power to voltage derivative ($\Delta P_{PV}/\Delta V_{PV}$) of the PV system [92]. However, the estimated denominator of the slope will cause the undesirable results of wasted energy when ΔV_{PV} is very small. In this chapter, the MPPT-P&O algorithm of [16] is improved using the INC technique when the operating point is near the MPP. The issue of division calculations is avoided using the absolute value of the step change in the air motor power which is given by

$$\omega_{ref} = \omega_r \pm \Delta\omega_f \cdot |\Delta P_{am}|. \quad (6.14)$$

The MPPT flowchart in Figure 6.9 illustrates the hybrid P&O and INC algorithms. The initial speed reference is set to the minimum value of ω_{min} , which is based on the voltage ratio and the limit duty cycle design in Figure 6.1. The speed and the armature current are measured using the analog to digital conversion with f_{sc} Hz. The speed regulator controller computes the duty cycle from (6.2). The air motor torque and power are discretized from (2.1) and (3.2). The changes in speed $\Delta\omega_r$, power ΔP_{am} , torque ΔT_{am} and duty cycle ΔD are then calculated by taking the differences between their current values and their values during the previous time step. Instability can be avoided when the duty cycle is exactly equal to the buck mode at 95% or the boost mode at 5%. The algorithm then sets the speed reference at ω_{min} which is approximated from (6.2) and (2.2). The fine or coarse tuning areas are set by employing the value of σ that is determined in the controller. In the operation of the P&O method in [16], the derivative $\Delta P_{am}/\Delta D$ and ΔD are conceptually used to decide whether to increment or decrement the reference speed (ω_{ref}). For the coarse tuning region ($|\Delta P_{am}| > \sigma$), if the derivative $\Delta P_{am}/\Delta D$ is positive and ΔD is negative then the reference speed is decremented by the fix step-size of $\Delta\omega_c$ and if the derivative $\Delta P_{am}/\Delta D$ is either negative or positive and ΔD is positive, then the reference speed will be increased by the same value of $\Delta\omega_c$. In the fine tuning area ($|\Delta P_{am}| < \sigma$), the direction of the variable speed step-size is determined using the same derivative operators $\Delta P_{am}/\Delta D$ and ΔD . The small incremented or decremented variable speed step-size of $\Delta\omega_f$ is scaled by multiplying it by the absolute values of different air motor power, as seen in (6.14). Therefore, the fast convergence and accuracy of reaching MPP are solved using the big step size $\Delta\omega_c$ and variable step-size $\Delta\omega_f \cdot |\Delta P_{am}|$. This MPPT algorithm will be used to examine the performance of the speed regulator under high input power fluctuation conditions, as shown in the next section.

6.5 Simulation results

The mathematical models of the SS-CAES system design in Matlab/Simulink are implemented using the SimPowerSystem as shown in Figure 6.10. The system includes the air motor model, the

buck-boost converter, the speed regulator and the MPPT algorithm. The power converter components are selected according to the values presented in Table E.4.

Figure 6.10 SS-CAES system model in Matlab/Simulink

The generator's speed and inductor current are sampled at a frequency of 1 kHz. The PI controller was selected from section 6.4.2. The MPPT algorithm is fed by the measured data from the inductor current, the generator's speed and the duty cycle from the speed regulator controller, sampled at $T_{sm} = 1$ s intervals. This value is approximated by the settling time of the speed regulator. The proposed MPPT-algorithm based on the flowchart in Figure 6.9 was programmed into the embedded block function for determining the air motor speed command. The speed regulator is then used to maintain the air motor speed for achieving the MPP. To monitor the system operation, it is assumed that perfect gas in a large cylinder is discharged and charged under isothermal conditions. Kinetic and frictional losses are ignored. Therefore, the mass flow of air that is released to the air motor is proportional only to pressure changes within the cylinder.

The result of simulation for the hybrid P&O and INC algorithm is illustrated in Figure 6.11, under high-pressure fluctuation conditions. The operating parameters include the threshold of σ , the sign derivative $\Delta P_{am}/\Delta D$, $\Delta P_{am}/\Delta \omega_r$, the sign change in the duty cycle, the speed and the power output. The MPPT algorithm keeps going in the correct direction, when the inlet pressure changes from 6 bar to 2 bar and returns to 6 bar again at times of about 15s and 30s, as seen in Figure 6.11 (a). These input power fluctuations produce the dynamic speed issues that are shown in Figure 6.11 (g-h) and the wrong estimation of direction points of $\Delta P_{am}/\Delta D$ and $\Delta P_{am}/\Delta \omega_r$ in Figure 6.11 (c-d)

Figure 6.11 Simulation results obtained using the MPPT algorithm under input pressure changes from 6 bar to 2 bar and turn it to 6 bar

which can result in confusions in the search for MPPT direction. Furthermore, the stability of the speed regulator with boost and buck converters are also affected due to high pressure changes. It can be seen that using both $\Delta P_{am}/\Delta D$ and ΔD produces the correct search direction and short transients within the big step-size of $\Delta \omega_c$ and wide speed changes, as shown in Figure 6.11 (f). According to the conventional P&O MPPT techniques, the oscillation from the speed step-size around the MPP in Figure 4. 11 is due to the increase in power losses. To reduce the oscillations of the proposed MPPT algorithm, the variable speed step-size is used when the $|\Delta P_{am}| < \sigma$ in Figure 6.11 (b). In this work, σ is the maximum air motor power change which is defined to be around 2% of the rated air motor power. It can be seen that the speed regulator can keep the slightly constant speed at the MPP, although there will be high amplitudes of the derivative $\Delta P_{am}/\Delta D$ and $\Delta P_{am}/\Delta \omega_r$ when ΔD and $\Delta \omega_r$ are small.

The tracking efficiencies of the hybrid P&O in [16] and the proposed hybrid P&O and INC MPPT algorithm here are compared by the plots in Figure 6.12. It is apparent that both methods can improve the short term dynamics, while the proposed algorithm consistently provides high efficiency both at high pressure and low pressure values and an efficiency of close to 100% at steady state conditions.

Figure 6.12 Efficiency of the air motor for using a) the hybrid P&O algorithm and b) the hybrid P&O and INC under high level pressure changes

6.6 Summary

This chapter has investigated the improvement of the speed regulation and the hybrid MPPT-algorithm for a SS-CAES system. Using a speed regulator with a buck-boost converter can increasingly improve the performance of the speed range control under wide input power fluctuation conditions. The MPPT-algorithm gives a fast convergence to and high accuracy at the MPP, by using a big step-size of the P&O method and a variable step-size of the INC method. The algorithm can also prevent a wrong search direction by employing the derivative of the air motor power with respect to the duty change and observing the sign of the steps in duty cycle changes. Avoiding slope calculations resulted in the increased efficiency in steady state conditions by employing the absolute values of step changes in the air motor power. This, however, should be implemented experimentally in order to validate the simulated results here.

The proposed speed regulator and MPPT-algorithm may also be used in the power management of an electric vehicle, a PV or a wind turbine system.

Chapter 7: Conclusion and future work

7.1 Conclusions

As outline in section 1.4, this thesis has focused on the MPPT for a SS-CAES system.

In Chapter 2, the design, implementation and performance of a speed regulator were investigated. Controlling the reference speed by the MPPT rather than the duty cycle of the converter is known to result in a fast convergence to the MPP. A simplified small-signal of the SS-CAES system with a buck converter was modelled, using the absorbed-injected current method to help with the selection of the parameters of the controllers. Some drawbacks were found associated with speed regulation using a buck converter. The speed regulator cannot operate either in the low speed region where the duty cycle is more than 95% or in the high speed region where the duty cycle is less than 5%. This affects the system start-up large step pressure fluctuations. Slight inductor current fluctuations were found to be caused by the back EMF ripple of the DC generator. This was eliminated using a low-pass filter, but resulted in a slower dynamic response. From the simulation results, the mechanical parameters (the moment of inertia and the viscous friction coefficients) were modelled for the SS-CAES system. The model was then used to simulate the dynamic response of the system under constant and varying pressure conditions. It was found that the speed results were faster than those of the experimental results under similar conditions. This was probably caused by the unaccounted thermodynamic processes in the model.

In Chapter 3, the air motor characteristics were used to determine the maximum power/efficiency points under pressure levels. The maximum power points strongly depend on pressures and occur when the air motor speed is half its free speed (no-load) value. However, the air flow rates at different pressures are required to be measured to achieve the MEP. It was found that the MEP is very close in efficiency to the MPP; the efficiency of the MEP is 1% higher than that at the MPP at the constant inlet pressure of 6 bar. It is noted that these strategies required careful characterization of the air motor and also required the use of speed, air flow rates and pressure sensors. These strategies have been implemented for specific systems at high cost.

Considering the very small differences of MEP and MPP efficiencies mentioned above and the difficulty of the MEP real time measurements (see section 4.1), the MPPT was employed to improve the system efficiency. MPPT is easy to determine because it relies on measurement of the output power directly. Also, the loss of efficiency when the air motor operates at MPP is small compared to its operation at MEP, as mentioned earlier.

In Chapter 4, a real-time MPPT algorithm which does not require a priori knowledge of the air motor characteristics or the use of a pressure transducer was proposed. It employed a novel hybrid

P&O approach using coarse and fine speed steps to improve the convergence and accuracy of the MPPT technique. Using the rate of change of power with respect to speed was found to cause the commonly used P&O MPPT algorithm to lose its direction of search as a result of compressed air pressure fluctuations. Applying the rate of change of power with respect to the duty cycle of the dc-dc converter results in better performance in this respect, but it still loses the correct search direction under certain circumstances. This however could be corrected by using the sign changes in the duty cycle. Experiments were successfully carried out to validate the simulated results of the proposed algorithm. The results indicated the accuracy and effectiveness of the proposed strategy under input pressure changes. In addition, it was shown that an important capability of the MPPT algorithm was to carry out highly efficient tracking with a power loss of less than 0.08%. The MPPT algorithm has been successful in dynamic tracking. However, the limitation of the MPPT is that it fails to track the MPP when the operating point search direction is on the right hand side of the power-speed curve at constant pressure. This can be resolved by defining a different step-size for $\Delta\omega_f$ (positive $\Delta\omega_f < \text{negative } \Delta\omega_f$) when the operating point is in the fine tuning area, noting that this will result in the slow tracking of the MPP. Furthermore, the steady state oscillation around the MPP was still presented when using the P&O algorithm. These were enhanced using a variable step-size version of the MPPT-FLC algorithm.

To improve the P&O algorithm for the SS-CAES system, the variable step-size approach was adapted using a real-time MPPT-FLC (fuzzy logic) – see Chapter 5. The MPPT-FLC addresses two obvious limitations for the SS-CAES system, namely confusion and wrong judgement. Confusion occurs under input power fluctuation conditions while wrong judgement is caused by noise amplification due to the division by small numbers when calculating the slope near the MPP. Two fuzzy approaches were applied to eliminate the problems: a fuzzy logic approach and a vector-fuzzy logic method.

Confusion is solved by the fuzzy logic control method using $\Delta P_{am}/\Delta D$ and ΔD to determine the direction of search. When the calculation of $\Delta P_{am}/\Delta D$ was close to the MPP, the noise amplification due to the division by a small number was overcome by defining an alternative per unit quantity ΔP^* related to ΔP_{am} and the sign of $\Delta P_{am}/\Delta D$. The fuzzy rule and membership function were used based on ΔP^* and ΔD^* (a per unit of ΔD) to determine the variable step size $\Delta\omega_f$ used by the MPPT. The system however becomes confused under small pressure fluctuation condition when ΔP^* is small.

The vector-fuzzy logic method was designed to eliminate confusion under pressure fluctuations. The fuzzy rule was vectorised into four quadrants of the $\Delta P^* - \Delta D^*$ plane. The problematic vector of Region 2P can be found at quadrant I, which was the cause of confusion when this vector was commonly used under increased and decreased input power conditions. The problematic vector of increased input power can be solved by moving it to a similar direction of quadrant III (with

negative ΔP^*) or quadrant IV (with negative both ΔP^* and ΔD^*) to achieve the correct MPP tracking.

In Chapter 6, it was shown that using a buck-boost converter can improve the controllable speed-range of a SS-CAES system. The duty cycle of 95% that was driven by a buck converter determines the width of the fixed step area on the low speed side of the MPP. This area will be narrow, particularly if the efficiency of the buck converter is low. On the high speed side, the boost converter operates at the duty cycle of 5%. It will cause failure in the tracking of the MPPT when the input power is decreased. The improved SS-CAES system using a buck-boost converter was implemented along with the hybrid P&O and the INC-MPPT. The MPPT system was adapted from Chapter 4 to eliminate the operating point dither by using an absolute of the ΔP_{am} in the variable step-size area. Experimental work is still required to validate the encouraging predictions in this chapter.

In practice, MPPT systems use a dc-dc converter to deliver the output power to a dc-link. The constant dc-link voltage will be controlled by the other converter downstream. In this work, it is difficult to observe the dynamic change in a duty cycle in the constant dc-link when applying the MPPT strategies. This may imply that the MPPT system will fail to track the MPP if the strategy applies either a two-loop speed regulator or a direct duty cycle for a dc-dc converter. This problem will be resolved by adding an inner voltage loop (three cascaded loop) for a speed regulator, as seen in previous publication [13]. The MPPT system should however be conceptually redesigned with the other parameters instead of using a duty cycle to reproduce its MPPT system, such as the rate of change of the converter's output power with respect to its inductor current/armature current. The MPPT system will be improved with a fixed dc-link.

The MPPT strategies developed in this work can also be applied to a PV or a wind turbine system.

7.2 Future work

Apart from establishing and implementing the power electronics controllers introduced this thesis, the efficiency of a SS-CAES system can be further improved in the following three key ways.

7.2.1 Improving shortcomings in an MPPT controller

For a high-order system, the settling time of the actual speed from the speed regulator is chosen by considering the dynamic response of the large step speed change at the maximum change in air motor power. Therefore, fixed-sampling period time based on the settling time of the actual speed from the speed regulator is set to implement the MPPT system. As a result of doing this, the settling time of the actual speed gives a short period when the step speed change is small. However, the settling time is much longer when the speed step size change is large. This can cause a slow

dynamic convergence to the MPP which results in a loss of power. Therefore, a varying sampling period will improve the dynamic response of the MPPT controller by using a change in speed. For example, the change in speed can occur in response to an error between the reference speed of the MPPT system and the actual speed from the speed regulator. If the error is zero, the MPPT system will act to determine the parameters of the algorithm, i.e., change the air motor power and duty cycle. The zero error will eliminate confusion which is caused by power disturbances during the sampling interval of section 4.5 in Chapter 4.

The confusion will return when the input power disturbances occur during the dynamic response of the MPPT strategies (the operating point is not already at the MPP). For example, if the operating point moves from the air motor power on a low pressure speed curve to a new point on the high pressure power-speed curve, under increased pressure fluctuations. In other words, during the process of the MPPT, the operating point is suddenly pulled down to the left-hand side of the power curve again when the pressure is rapidly decreased. Ideally, this can be resolved by checking the tracking error from the speed controller (PI controller). The error will be used and integrated into the MPPT algorithms.

7.2.2 Heat and power management

The SS-CAES system should completely integrate the compression stage of the operations with suitable thermodynamic heat exchangers. In fact, the grid-connection requires the enhanced performance of the system either for delivering the power back on peak demand or as an emergency power system or for storing power within cylinders. Efficient heat management is essential to increase the added value of the system. For example, the heat energy from the charging process is stored in the thermal energy storage system. The high pressure air and heat energy are recombined to drive an air motor, when the energy is required. The air outlet is then used again to extract the heat energy from the power switching of converter and electrical load such as a generator, a battery or a supercapacitor, which produces power. Power management is another important investigation for supporting the design of a hybrid storage device that may include components such as a bank of batteries, a supercapacitor and other storage devices. By efficient power management, the power quality will be improved using hybrid storage devices in response to various output load levels. Eventually, the interest and investment in the production of SS-CAES will significantly increase when a manufacturer/entrepreneur can easily make a decision by evaluating the power performance of a system based on a number of storage devices which are combined properly.

Appendices

Appendix A Air motor model

A.1 Air motor characteristics

The conversion of pneumatic to mechanical energy covers the analysis of an air motor model, under either constant or varying pressure. In order to achieve maximum efficiency or maximum power of the air motor, its individual characteristics should be measured and characterized. Before starting the analysis of the air motor model, firstly an air motor needs to be selected so that all the physical characteristics involved in the energy conversion process can subsequently be modelled. Basically, the air motor model can be analysed by considering its important physical characteristics, which are the air consumption, torque, speed, power and the efficiency of the pneumatic to mechanical energy conversion (see Figure A.1).

Figure A.1 Block diagram of the pneumatic-to-mechanical energy conversion process

These physical characteristics, related to the energy conversion process, are difficult to extract directly from the manufacturers' data sheets. In order to obtain the correct set of data, the most extensively used range of pneumatic motors in the world, known as Atlas Air Motor, are used here by downloading the programme "Atlas Copco Air Motor" from the manufacturer's website [89].

For this study, the air motor 'LZB14 AR034' is selected since it provides a linear stall torque during the speed change which conveniently results in linear characteristic equations. However, the remaining physical characteristics, including air consumption, power and efficiency are necessarily estimated from their relationships to the speed change.

Figure A.2 (a)-(b) shows typical information on the selected air motor 'LZB14 AR034'. The relationship of the air motor characteristics (torque, power, and air consumption) with speed change is represented in Figure A.2 (a) while Figure A.2 (b) indicates the values of these characteristics when the air motor gives maximum power at rated pressure 6.3 bar [89]. In Figure A.2 (c)-(d), the characteristics torque, power and air consumption in relation to speed are illustrated under different pressure values of 4, 4.5, 5, 5.5, 6 and 6.3 bar. It is obvious that the values of torque and air consumption depend on the pressure in that they tend to increase according to the raised pressure, as shown in the black arrow on their figure.

Appendix A

In order to derive a mathematical model, all these characteristics of the selected air motor ‘LZB14 AR034’ in [89] are assumed to be relevant to the inlet constant and varying pressure, which will now be analysed in detail in the following two parts.

Figure A.2 Characteristics of the air motor LZB 14 AR034 (100W)

A.2 Analysis of the air motor model under constant pressure

All the characteristics of the selected air motor are firstly analysed under constant pressure in order to obtain the main equations for mechanical torque, mechanical power and air consumption with respect to speed changes. These will then be used to create a mathematical model of the air motor under varying pressure. As was mentioned above, the selected air motor provides the linear stall torque with respect to speed changes. A linear characteristic equation can therefore be used to model this torque of Figure A.2(a):

$$T_{am} = T_o \left(1 - \frac{\omega_r}{\omega_{ro}} \right), \quad (A.1)$$

where T_{am} is the mechanical torque, T_o is the stall torque, ω_r is the rotational speed and ω_{ro} is the free speed (speed at which the outgoing shaft rotates when no load is applied). It is worth noting that Lemofouet-Gatsi [3], who also investigated the mathematical model of the same motor,

estimated the equation of the linear stall torque by using a curve fit and gave a similar formula to equation (A.1). Next, the mechanical power (P_{am}) related to torque and angular velocity as

$$P_{am} = \omega_r \cdot T_{am} = T_o \left(\omega_r - \frac{\omega_r^2}{\omega_{ro}} \right). \quad (A.2)$$

Finally, the motor air consumption (dV_a/dt) varies nonlinearly with regard to speed. This characteristic can be analysed based on a Gaussian function in which dV_{max}/dt is the maximum air consumption at 6.3 bar (see equation (A.3)). In Lemofouet-Gatsi [3], however, the exponential function is utilized for the analysis of the air consumption characteristic, which results in a different formula than this study. A Gaussian function is chosen here because it is a natural exponential function, capable of defining a minimum or maximum value with the constant coefficient, and the solution of an ordinary differential equation (ODE), which is the basic physical model. The constant coefficient can be defined using the maximum air consumption dV_{max}/dt . Therefore, the air consumption equation with respect to speed changes is presented below:

$$\frac{dV_a}{dt} = \frac{dV_{max}}{dt} \exp \left(- \left(\frac{(\omega_r - c_1)}{c_2} \right)^2 \right) \quad (A.3)$$

where c_1 and c_2 are real constants, calculated from different points on the air consumption characteristic curves at 6.3 bar by using the curve fitting tools in MATLAB. All the derived equations (A.1)–(A.3) are then used to produce a mathematical model of the air motor under varying pressure, which will be given in detail in the following section.

A.3 Analysis of the air motor model under variable pressure

In this part, all the derived equations (A.1)–(A.3) are modified into a family curve in order to account for the variable pressure (p_i) experienced by the air motor. From the extreme boundaries of the following parameters in Figure A.2 (c-d); stall torque T_o , free speed ω_{ro} and the end of the air consumption dV_{max}/dt (or $\dot{V}_{max}$) tended to heighten their parameters when the pressure increased. Therefore, the initial stall torques to start air motor are estimated to be a straight line of $T_o(p_i)$ under the increased pressure condition, as shown in Figure A.3. The straight line of the free speed when no load is applied is also determined in various pressures as seen at the bottom of Figure A.3, where the free speed Nr_o is illustrated in rpm unit. The air consumption for an air motor increases with the air motor speed and thus is highest at free speed. The maximum air consumption points of Figure A.4 are plotted in the straight line of $\dot{V}_{max}(p_i)$ for the variable pressure (p_i).

Figure A.3 Estimated functions $T_o(p_i)$ and $\omega_{ro}(p_i)$ from the boundary parameters

Figure A.4 Estimated function f_a from boundary parameters

Thus, the estimated linear fit of Figure A.3 for the stall torque is $T_o(p_i) = c_{t1} p_i + c_{t2}$, the free speed is $\omega_{ro}(p_i) = c_{n1} p_i^2 + c_{n2} p_i + c_{n3}$, and Figure A.4 for the air consumption is $dV_{\max}(p_i)/dt = c_{a1} p_i + c_{a2}$ (Note: p_i = inlet pressure) where, c_{t1} , c_{t2} , c_{n1} , c_{n2} , c_{n3} , c_{a1} and c_{a2} are real constants determined from simple straight line fits. Equations (A.1) to (A.3) can then be modified under variable pressure (p_i), as follows:

$$T_{am}(p_i) = T_o(p_i) \left(1 - \frac{\omega_r}{\omega_o(p_i)} \right) \quad (A.4)$$

$$P_{am}(p_i) = T_o(p_i) \frac{\pi}{30} \left(\omega_r - \frac{\omega_r^2}{\omega_o(p_i)} \right) \quad (A.5)$$

$$\frac{dV_a(p_i)}{dt} = \frac{dV_{\max}(p_i)}{dt} \exp \left(- \left(\frac{(\omega_r - c_1)}{c_2} \right)^2 \right) \quad (A.6)$$

Equations (A.4) to (A.6) represent the mathematical model of the air motor under variable pressure due to speed changes. To reiterate, equation (A.4) is used for finding out the mechanical torque output, while equation (A.5) determines the air motor power output and equation (A.6) is used to determine the required air consumption.

A comparison of the results for torque, power and air consumption characteristics between the mathematical model and the manufacturer's data sheet is presented in Figure A.5 to Figure A.7.

Figure A.5 Model torque characteristics of air motor

Figure A.6 Model power characteristics of air motor

Figure A.7 Model air consumption characteristics of air motor

Evidently, for the selected air motor, the mathematical model exhibits similar results to the manufacturer's data sheet. It can, therefore, be concluded that the derived equations (A.4) to (A.6) prove the effectiveness of the boundary fit approach that has been introduced here. It is important to state that the creation of the model for the selected air motor in this work (LZB14 AR034) is somewhat different than the model presented in the work of Lemofouet-Gatsi [3]. In this thesis, a linear torque and a Gaussian function are utilized to create the equations for the mechanical energy output and the required air consumption, respectively. Both these characteristics are important in deriving the basic equations that lead to highly accurate results that can match those given in the manufacturer's datasheet.

A.4 Thermodynamic analysis of the air motor conversion efficiency

In this analysis, the first and second laws of thermodynamics in an open loop system are applied. The elementary energy δw_a of a unit mass of air is presented as [3]

$$\delta w_a \leq -dh + T_a ds, \quad (\text{A.7})$$

where dh and ds define the changes in specific enthalpy and entropy, respectively. The integration of equation (A.7) from the inlet to the outlet conditions of the air motor is defined as the specific work w_a , i.e.,

$$w_a \leq (h_i - h_o) - T_a(s_i - s_o), \quad (\text{A.8})$$

where h_i and h_o are respectively the specific enthalpy of inlet and outlet, and s_i and s_o are the specific entropies. The changes in enthalpy and entropy of an ideal gas are further given by:

$$h_i - h_o = c_p(T_i - T_o), \quad (\text{A.9})$$

and

$$s_i - s_o = c_p \ln\left(\frac{T_i}{T_o}\right) - R \ln\left(\frac{p_i}{p_o}\right), \quad (\text{A.10})$$

where p_i and p_o are respectively the inlet and outlet pressures, R the gas constant, T_i and T_o are the input and output temperatures, and c_p is the heat capacity at constant pressure.

Substituting equations (A.9) and (A.10) into equation (A.8) gives

$$w_a \leq RT_a \left[\ln\left(\frac{p_i}{p_o}\right) + \frac{\gamma}{\gamma-1} \left(\frac{T_i - T_o}{T_a} - \ln\left(\frac{T_i}{T_o}\right) \right) \right]. \quad (\text{A.11})$$

Appendix A

To obtain simpler equations, the air motor is assumed to operate at isothermal conditions ($T_i = T_a$), i.e., the ambient temperature equates to that of the inside of a cylinder. Therefore, from equation (A.11) the maximum energy of the air compressor can be written as:

$$w_a = RT_i \left[\ln \left(\frac{p_i}{p_o} \right) + \frac{\gamma}{\gamma-1} \left(1 - \frac{T_o}{T_i} - \ln \left(\frac{T_i}{T_o} \right) \right) \right], \quad (\text{A.12})$$

where $\gamma = c_p/c_v$ is the ratio of the specific heats at constant pressure (c_p) to heat capacity at constant volume (c_v). The compressed air power $\dot{W}_a$ is derived by multiplying the specific energy w_a by the mass flow rate, $\dot{m}_a$. Applying the continuity equation, gives:

$$\frac{dm_a}{dt} = \dot{m}_a = \rho \dot{V} = \frac{p_i}{RT_a} \dot{V}_i = \frac{p_a}{RT_o} \dot{V}_a. \quad (\text{A.13})$$

The volumetric flow rate is practically measured at the outlet and hence, the mechanical power is given by:

$$\dot{W}_a = w_a \dot{m}_a = p_a \dot{V}_a \frac{T_i}{T_o} \left[\ln \left(\frac{p_i}{p_a} \right) + \frac{\gamma}{\gamma-1} \left(1 - \frac{T_o}{T_i} - \ln \left(\frac{T_i}{T_o} \right) \right) \right]. \quad (\text{A.14})$$

Given the high motor speed, the air expansion can be considered as being adiabatic. Hence, the ideal gas relation $(T_i/T_o) = (p_i/p_a)^{(\gamma-1)/\gamma}$ is introduced into equation (A.14) and the following relationship is obtained:

$$\dot{W}_a = \frac{\gamma}{\gamma-1} p_a \dot{V}_a \left[\left(\frac{p_i}{p_a} \right)^{\frac{\gamma-1}{\gamma}} - 1 \right]. \quad (\text{A.15})$$

Lastly, the real time pneumatic-to-mechanical energy conversion efficiency η_{am} is derived from equations (A.5) and (A.15) as:

$$\eta_{am} = \frac{\dot{W}_m}{\dot{W}_a} = \frac{T_o(p_i) \frac{\pi}{30} \left(\omega_r - \frac{\omega_r^2}{\omega_o(p_i)} \right)}{\frac{\gamma}{\gamma-1} p_a \dot{V}_a \left[\left(\frac{p_i}{p_a} \right)^{\frac{\gamma-1}{\gamma}} - 1 \right]}. \quad (\text{A.16})$$

In conclusion, the air motor efficiency depends on three main characteristics, which are stall torque T_o , free speed ω_o , and pressure ratio (p_i/p_a). The stall torque relates the efficiency to the rated power of the air motor. If the rated power is high, the efficiency is then increased which implies higher stall torque values. As for the free speed, to achieve high efficiencies for the air motor, the ratio

$\omega_r^2 / \omega_o(p_i)$ in equation (A.16) can be adjusted to be close to zero by selecting a relatively high free speed $\omega_o(p_i)$. The pressure ratio (p_i/p_a) also influences the efficiency because it affects the air consumption of the motor. For instance, a low pressure ratio implies less air consumption, which then results in higher conversion efficiencies.

Appendix B Small signal model of the PM DC generator and buck converter

In order to control resistance R_L , an expression for the transfer function of the DC generator with the buck converter is obtained using the injected-absorbed current method. This transfer function can then be used for stability analysis of the speed regulation of the DC generator, as shown below:

Figure B.1 DC generator with buck converter model under switch-mode on-off conditions

In Figure B.1, a DC generator is cascaded with a buck converter which operates under switch-mode section in its topology for energy conversion. In the power electronic converter, topology refers to the analysis of the wave forms in the storage elements based on switching actions on/off for achieving the required output. The integration of the DC generator with buck converter under the mentioned condition is proposed here in order to determine the conversion stability. The analysis starts by considering an average inductor current (i_L) for the buck converter in continuous mode, as shown in Figure B.2:

Figure B.2 Inductor current waveform in heavy mode

The average inductor current, given by the area under the trapezoidal region in Figure B.2, is injected from the inductor L into the storage capacitor C_o and R_L simultaneously over the period T , as shown below:

$$i_L = \frac{i_m + i_M}{2T} t_c + \frac{i_M + i_f}{2T} t_d = \frac{1}{2} \frac{t_c}{T} i_m + \frac{1}{2} i_M + \frac{1}{2} \frac{t_d}{T} i_f \quad (\text{B.1})$$

where i_f is the value of the inductor current at the end of the considered period, i_m is the minimum inductor current, i_M is the maximum inductor current and T is the duration of this period (t_c and t_d are the duration of switch on/off respectively). According to Figure B.1, the buck converter with DC generator operates the switch MOSFET device at t_d second (state S_I =OFF) and provides the initial inductor current ($i_L(0) = i_M$), as seen in Figure B.2. In order to estimate the final inductor current, it is analysed as below:

$$L \frac{di_L}{dt} - v_o = 0. \quad (\text{B.2})$$

The equation (B.2) is integrated and given the final inductor current as:

$$i_L(t_d) = i_f = i_M - \frac{v_o}{L} t_d. \quad (\text{B.3})$$

Substituting equation (B.3) into (B.1), as follows:

$$i_L = \frac{1}{2} \frac{t_c}{T} i_m + \frac{1}{2} i_M + \frac{1}{2} \frac{t_d}{T} i_M - \frac{v_o}{2L} \frac{t_d^2}{T}. \quad (\text{B.4})$$

The relationship between the inductor current in state S_I =ON (t_c second) and the initial condition ($i_L(0) = i_m$) is analysed by Kirchhoff's voltage law (KVL) as given below:

$$\frac{di_L}{dt} + \frac{r_{ag}}{L_{ag} + L} i_L = \frac{e_{ag} - v_o}{L_{ag} + L}. \quad (\text{B.5})$$

Take Laplace into the equation (B.5), as follows:

$$sI_L(s) - i_L(0) + \frac{r_{ag}}{L_t} I_L(s) = \frac{e_{ag} - v_o}{sL_t}. \quad (\text{B.6})$$

The equation (B.6) at $i_L(0) = 0$ is then revised as given in:

$$I_L(s) = \frac{e_{ag} - v_o}{r_{ag}} \left(\frac{1}{s} - \frac{1}{(s + \frac{r_{ag}}{L_t})} \right) + \frac{i_m}{(s + \frac{r_{ag}}{L_t})}. \quad (\text{B.7})$$

Inverse Laplace of the equation (B.7) and consider time domain $t=t_c$, as follows:

$$i_L(t_c) = i_M = \left(\frac{e_{ag} - v_o}{r_{ag}} \right) + \left[i_m - \left(\frac{e_{ag} - v_o}{r_{ag}} \right) \right] e^{-\frac{r_{ag}}{L_t} t_c} \quad (\text{B.8})$$

where τ is the time constant of circuit (L_t/r_{ag}) and L_t is the total of L and L_{ag} . The time interval of interest is much shorter than this time constant. The exponential function in (B.8) can be approximated by a Taylor series in which only the linear term can be chosen, as shown below:

$$i_M = i_m \left(1 - \frac{t_c}{\tau} \right) + \left(\frac{e_{ag} - v_o}{L_t} \right) t_c. \quad (\text{B.9})$$

Equation (B.4) can now be rewritten by using equation (B.9), as follows:

$$i_L = i_m - \frac{1}{2} \frac{t_c}{\tau} \left[1 + \frac{t_d}{T} \right] i_m + \frac{1}{2} \left(\frac{e_{ag} - v_o}{L_t} \right) \left[1 + \frac{t_d}{T} \right] t_c - \frac{v_o}{2L} \frac{t_d^2}{T}. \quad (\text{B.10})$$

The time derivative of the injected current is then obtained as

$$\frac{di_L}{dt} = \frac{\partial i_L}{\partial i_m} \frac{di_m}{dt} + \frac{\partial i_L}{\partial t_d} \frac{dt_d}{dt} + \frac{\partial i_L}{\partial e_{ag}} \frac{de_{ag}}{dt} + \frac{\partial i_L}{\partial v_o} \frac{dv_o}{dt} + \frac{\partial i_L}{\partial t_c} \frac{dt_c}{dt}. \quad (\text{B.11})$$

The switching period T is constant ($t_c + t_d = T$) which is analysed in the derivative as shown:

$$\frac{dt_d}{dt} = -\frac{dt_c}{dt}. \quad (\text{B.12})$$

Appendix B

Equation (B.12) is replaced by (B.11) and this is further applied by the Laplace transformation in under initial condition $i_L(0)=i_m(0)=e_{ag}(0)=v_o(0)=t_c(0)=0$ and $T_c^*(s)/T(s)=D^*(s)$. The result is expressed below:

$$I_L^*(s) = \frac{\partial i_L}{\partial i_m} I_m^*(s) + \frac{\partial i_L}{\partial e_a} E_{ag}^*(s) + \frac{\partial i_L}{\partial v_o} V_o^*(s) + T \left(\frac{\partial i_L}{\partial t_c} - \frac{\partial i_L}{\partial t_d} \right) D^*(s). \quad (B.13)$$

The coefficients of partial derivative contained in (B.13) can be obtained by the following relatively straightforward differentiations of (B.10) as seen:

$$\begin{aligned} \frac{\partial i_L}{\partial i_m} &= \frac{1}{2} \left(\frac{2\tau - 2DT + D^2T}{\tau} \right) \\ \frac{\partial i_L}{\partial t_c} &= \frac{1}{2} [2 - D] \left[\left(\frac{E_{ag} - V_o}{L_t} \right) - \frac{1}{\tau} I_m \right] \\ \frac{\partial i_L}{\partial t_d} &= \frac{1}{2} \left[D \left(\frac{E_{ag} - V_o}{L_t} \right) - \frac{2V_o}{L} (1 - D) - \frac{D}{\tau} I_m \right]. \\ \frac{\partial i_L}{\partial e_a} &= \frac{DT}{2L_t} [2 - D] \\ \frac{\partial i_L}{\partial v_o} &= -\frac{T}{2} \left[\frac{D}{L_t} [2 - D] + \frac{(1 - D)^2}{L} \right] \end{aligned} \quad (B.14)$$

Step the estimation $I_m^*(s)$

To simplify (B.13), the $I_m^*(s)$ will be eliminated using the approximate quotient of the increment in frequency domain. The time derivative of the minimum current i_m is therefore approximated by a quotient of the increment that i_m is acquired during the switching period.

$$\frac{di_m}{dt} \approx \frac{i_f - i_m}{T} = f(t_c, t_d, e_a, v_o, i_m). \quad (B.15)$$

Hence, the total differential of (B.15) is

$$d \frac{di_m}{dt} = \frac{\partial f}{\partial t_c} dt_c + \frac{\partial f}{\partial t_d} dt_d + \frac{\partial f}{\partial e_a} de_{ag} + \frac{\partial f}{\partial v_o} dv_o + \frac{\partial f}{\partial i_m} di_m. \quad (B.16)$$

By replacing equation (B.12) by (B.16), the result is obtained the Laplace transform at condition $i_m(0)=i'_m(0)=t_c(0)=t_d(0)=e_{ag}(0)=v_o(0)=t_c(0)=0$ and $T_c^*(s)/T=D^*(s)$ as follows:

$$I_m^*(s) = \frac{1}{\left(s - \frac{\partial f}{\partial i_m}\right)} \left[T \left(\frac{\partial f}{\partial t_c} - \frac{\partial f}{\partial t_d} \right) D^*(s) + \frac{\partial f}{\partial e_{ag}} E_{ag}^*(s) + \frac{\partial f}{\partial v_o} V_o^*(s) \right]. \quad (B.17)$$

To determine the coefficients of partial derivative in (B.17), the (B.3) and (B.8) are substituted in the (B.15) as

$$f(t_c, t_d, e_a, v_o, i_m) = \frac{di_m}{dt} = \frac{1}{T} \left[\left(1 - e^{-\frac{r_{ag}}{L_t} t_c} \right) \left(\frac{e_{ag} - v_o}{r_{ag}} - i_m \right) - \frac{v_o}{L} t_d \right]. \quad (B.18)$$

The Taylor series of exponential is also applied in (B.18) as shown:

$$f(t_c, t_d, e_a, v_o, i_m) = \frac{di_m}{dt} = \frac{1}{T} \left[\left(\frac{t_c}{\tau} - \frac{t_c^2}{\tau 2!} \right) \left(\frac{e_{ag} - v_o}{r_{ag}} - i_m \right) - \frac{v_o}{L} t_d \right]. \quad (B.19)$$

Therefore, the partial derivatives of (B.19) as shown:

$$\begin{aligned} \frac{\partial f}{\partial i_m} &= -\frac{D}{\tau} \left(1 - \frac{DT}{2} \right) \\ \frac{\partial f}{\partial t_c} &= \frac{1}{T\tau} \left[\left(\frac{E_{ag} - V_o}{r_{ag}} - I_m \right) (1 - DT) \right] \\ \frac{\partial f}{\partial t_d} &= -\frac{1}{T} \frac{V_o}{L} \\ \frac{\partial f}{\partial e_{ag}} &= \frac{D}{L_t} \left(1 - \frac{DT}{2} \right) \\ \frac{\partial f}{\partial v_o} &= -\left[\frac{D}{L_t} \left(1 - \frac{DT}{2} \right) + \left(\frac{1-D}{L} \right) \right] \end{aligned} \quad (B.20)$$

where the period time switching T , t_c and t_d on/off switching are represented by

$$\overline{D} = 1 - D. \quad (B.21)$$

The equation (B.17) multiplies with $\partial i_b / \partial i_m$ as shown:

$$\frac{\partial i_b}{\partial i_m} I_m^*(s) = \frac{\frac{\partial i_b}{\partial i_m}}{\left(s - \frac{\partial f}{\partial i_m}\right)} \left[T \left(\frac{\partial f}{\partial t_c} - \frac{\partial f}{\partial t_d} \right) D^*(s) + \frac{\partial f}{\partial e_a} E_{ag}^*(s) + \frac{\partial f}{\partial v_o} V_o^*(s) \right]. \quad (B.22)$$

Yields

$$I_L^*(s) = G_1(s)E_{ag}^*(s) + G_2(s)V_o^*(s) + G_3(s)D^*(s). \quad (B.23)$$

Substituting equation (B.22) into (B.13) which is based on (B.23) yields as

$$G_1(s) = \frac{\partial i_L}{\partial e_{ag}} + \left(\frac{\frac{\partial f}{\partial e_{ag}} \frac{\partial i_L}{\partial i_m}}{s - \frac{\partial f}{\partial i_m}} \right) \quad (B.24)$$

$$G_2(s) = \frac{\partial i_L}{\partial v_o} + \left(\frac{\frac{\partial f}{\partial v_o} \frac{\partial i_L}{\partial i_m}}{s - \frac{\partial f}{\partial i_m}} \right) \quad (B.25)$$

$$G_3(s) = T \left[\left(\frac{\partial i_L}{\partial t_c} - \frac{\partial i_L}{\partial t_d} \right) + \left(\left(\frac{\partial f}{\partial t_c} - \frac{\partial f}{\partial t_d} \right) \frac{\frac{\partial i_L}{\partial i_m}}{s - \frac{\partial f}{\partial i_m}} \right) \right] \quad (B.26)$$

The transfer function of input voltage $E_{ag}^*(s)$ to output voltage $V_o(s)$, and the transfer function of duty cycle ratio $D^*(s)$ to output voltage which are estimated by substituting (B.14) and (B.20) into (B.24), (B.25) and (B.26) as

$$G_1(s) = \frac{D}{2L_t} \left[(2-D)T + \frac{1}{2\tau} (2-DT) \frac{(2\tau - 2DT + D^2T)}{\left(s + \frac{D}{\tau} \left(1 - \frac{DT}{2} \right) \right)} \right] \quad (B.27)$$

$$G_2(s) = -\frac{1}{2\tau} \left[\tau T \left[\frac{D}{L_t} (2-D) + \frac{(1-D)^2}{L} \right] + \left[\left[\frac{D}{L_t} \left(1 - \frac{DT}{2} \right) + \left(\frac{1-D}{L} \right) \right] \frac{(2\tau - 2DT + D^2T)}{\left(s + \frac{D}{\tau} \left(1 - \frac{DT}{2} \right) \right)} \right] \right] \quad (B.28)$$

$$G_3(s) = (1-D)T \left[\left(\frac{E_{ag} - V_o}{L_t} \right) + \frac{V_o}{L} - \frac{1}{\tau} I_m \right] + \frac{1}{2\tau} \left[\left[\left(\frac{E_{ag} - V_o}{L_t} \right) (1-DT) + \frac{V_o}{L} - \frac{(1-DT)}{\tau} I_m \right] \frac{(2\tau - 2DT + D^2T)}{\left(s + \frac{D}{\tau} \left(1 - \frac{DT}{2} \right) \right)} \right]. \quad (B.29)$$

According to the Figure B.1 the relationship of inductor current and the parallel of the storage capacitor C_o and R_L is

$$i_L(t) = C_o \frac{dv_o}{dt} + \frac{v_o}{R_L}. \quad (B.30)$$

Therefore, the transfer function model of DC generator with buck converter is

Figure B.3 The small signal model of a constant-frequency buck converter with DC generator source in continuous mode

Appendix C Terminology of fuzzy logic approach

This section briefly describes some of specialist terms that appear when discussing MPPT-fuzzy logic and vector-fuzzy in Chapter 5.

Fuzzy logic control is a problem-solving control system methodology which involves computing the linguistic variable. Normally, the fuzzy logic process consists of a fuzzification, a fuzzy inference system and a defuzzification, as follows:

Fuzzification is the process of generating membership values for a fuzzy variable using membership functions.

Membership function (MF) is a graphical shape that defines how each input is related to a membership value (or grade) between 0 and 1.

Fuzzy inference system (FIS) is a system that formulates the mapping from a given input to an output using fuzzy logic. An example of a Sugeno inference system is shown in [108] for computing the output of this FIS given the inputs. This system consists of a fuzzy rule and a database.

Fuzzy rule is defined as a conditional statement in the form IF–THEN rule.

Database is defined as the membership functions of the fuzzy sets used in the fuzzy rules. The sign of the derivative of the air motor power with respect to the duty cycle change and the correct direction with the sign of a change in duty cycle are used for inferring the reference speed in the fuzzy rules.

Defuzzification is the process of producing a quantifiable result (the aggregate output fuzzy set).

Weighted average (WTA) is a method of defuzzification used in this work.

Singleton output function is an output function that is given by a spike at a single number rather than a continuous curve. In the Fuzzy Logic Toolbox of the MATLAB-Simulink it is only supported as part of a zero-order Sugeno model.

Firing strength is the result of an AND operation of the input MFs, and this value is passed to the singleton output function for the rule.

AND operator is defined as the minimum value of the input MFs.

Vector-fuzzy is defined as a conditional statement that is mapped from the fuzzy rules to a graphical vector representation.

Appendix D Simulation of SS-CAES system

This part highlights all the mathematical models derived from previous analyses; the selected air motor, DC generator and buck converter for converting pneumatic to electrical energy at the speed requirement. These models will be integrated in order to specify the appropriate input and output of each stage of pneumatic-mechanical (air motor), mechanical-electrical (PM-DC generator) and electrical to electrical (dc-dc converter) energy conversion and further utilized to select the experimental rig. In addition, the cascade PI controllers will be utilized for regulating air motor speed at the maximum efficiency/power in pressure level.

D.1 Air motor model

In this stage, the selected air motor model rated power 100 W is on a focus to convert pneumatic to mechanical energy conversion. The input of the selected air motor is specified as pressure and air consumption while its output is the speed and torque. It is assumed that the pressure and air flow outlet of a cylinder are equal to the pressure inlet and air consumption of the air motor respectively. Losses in piping are also neglected for a simple consideration of the conversion system. The integrated mathematical model of the selected air motor with other two devices as mentioned above is, therefore, created in Matlab/Simulink based on the equations (A.1) - (A.6).

In Figure D.1, there are four subsystems of the mathematical air motor model including (1) air flow to speed block, (2) speed to torque or power output block, (3) the adjustment of boundary block for maximum air consumption, stall torque and free speed and (4) air consumption block.

Figure D.1 Subsystem of air motor model

Appendix D

Firstly, air flow to speed block is created from the revised equation (A.6) as given below:

$$\omega_r = c_2 \sqrt{\ln \left(\frac{\dot{V}_a}{\dot{V}_{\max}(p_i)} \right)} - c_2. \quad (D.1)$$

The equation (D.1) is then used to create air flow to speed block. It is given by

Figure D.2 Subsystem of air flow to speed block

The Fcn block in the MATLAB/Simulink library is applied with the specified mathematical expression [82]. In Figure D.2, the inputs of an air flow and the maximum air consumption are presented, using $u[1]$ and $u[2]$ respectively, as shown in (D.1).

Speed to torque and power output block are secondly created using the equations (A.4) and (A.5) as shown below:

Figure D.3 Subsystem of speed to torque/power output block

After that, equations (A.1)-(A.3) are used to adjust a boundary block for maximum air consumption, stall torque and free speed as presented in Figure D.4.

Figure D.4 Subsystem of boundary block adjustment

The air consumption is finally created based on the equation (A.3) as given below:

Figure D.5 Subsystem of air consumption

To build the mathematical model with the MATLAB/Simulink programme [82], the Fcn block is used by determining the inputs of the bus creator block as the maximum air consumption and air motor speed which are represented by $u(1)$ and $u(2)$ respectively as shown in Figure D.5.

In order to estimate the mathematical model of the selected air motor under both constant and varying pressure, real constant values are necessarily filled in a dialogue of the air motor model (see Figure D.6). The real constant values $C1$, $C2$, $Ct1$, $Ct2$, $Cn1$, $Cn2$, $Cn3$, $Ca1$ and $Ca2$ (see Table E.1) are derived from curve fit in MATLAB tool.

Figure D.6 Dialogue of air motor block

D.2 SS-CAES system model

A DC generator cascaded with a buck converter is used to convert mechanical to electrical energy. This model has been already provided in the MATLAB-SimPowerSystem module and its equations for the DC generator model are (2.1), (2.2) and (2.3). The buck converter is created by selecting items of the MATLAB-SimPowerSystem such as MOSFET switch, diode, capacitor, inductor and resistor and wiring these items together (see the buck converter circuit in Figure B.1). Therefore, the discharging process is established using air motor, permanent magnet DC generator and buck converter under constant and varying pressure as shown below:

Figure D.7 SS-CAES system model

D.3 Controllers

This section presents the different controllers used to estimate the speed reference. It is also shown how the speed reference input to the cascade PI controllers of speed regulator is created using the Matlab/Simulink, as follows:

D.3.1 Speed regulator controller

Figure D.8 Cascade PI controllers with speed command level of speed regulator

D.3.2 Cascade PI controllers in the Matlab script design

```
clear all;
close all;
clc;
%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%
% DC Generator maxon parameters 24V,3090 rpm,250W
%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%
Rag=0.4077;           %(Ohms)
Lag=585.897e-6;       %(H)
Ke=0.0691;           %(Nm/A)
Km=0.086;            % V-sec/rad
J=2.20407e-4;         %(kg-m2)
B=0.000298;          %(N-m-s/rad)
%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%
% Buck Converter parameters
%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%
Ts=1/10e3;           % Define Frequency Switching
Vin=20;              % Input Voltage
Vout=5;              % Output Voltage
Delta_iL=1;          % @ 10% of Full load
Delta_v=0.5;         % @ 10% of Full load
Duty_buck=Vout/Vin;  % voltage ratio
L_b=157e-6;          % Inductance
C_b=11e-6;           % Capacitance
RL=((Vout^2)/100);    % Maximum Load 100w
Cf=33e-6;            % Filter
%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%
% The small signal Model of PM DC generator with Buck converter %%%
%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%
%Tam %%% Teg
%Sum %%%
% %%%
% %%%
% %%%
```

Appendix D

```

% Gd
% (Omega)
%
% Km
% Ke*M
%
% E
%
% G1
%
% D
% I
% V
% G3
% Gst
%
%
%
% G2
%
%PI controller are determined using MASON Rule deal with SISOTOOL MATLAB
%Ts=1/20e3; % sampling interval of modelling
% Transfer Function of Speed Regulation with Buck Converter in
% injected-Absorbed Current Method
% Definition parameters as Lt, Ta, M and Im
Lt=Lag+L_b; % Total inductors
Tau=(Lt/Rag);
M=Duty_buck; % Duty cycle ratio at the efficiency of 100%
Im=1; % Minimum inductor current
% The estimation of transfer function G1, G2 and G3 are estimated using
% the small signal above:
Gcom=tf([0 (2*Tau)-(Ts*M*(2-M))],[1 (M/Tau)*(1-(M*Ts/2))]);
G11=(1/(2*Tau))*(2-(M*Ts))*Gcom;
G12=(2-M)*Ts;
G1=(M/(2*Lt))*(G11+G12); %The air motor torque input
G21=(M/Lt)*(1-(M*Ts/2));
G22=(1-M)/L_b;
G23=(G21+G22)*Gcom;
G24=(M/Lt)*(2-M);
G25=((1-M)^2)/L_b;
G26=(Tau*Ts)*(G24+G25);
G2=(1/(2*Tau))*(G26+G23); %feedback output voltage
G31=((Vin-Vout)/Lt)*(1-(M*Ts))+ (Vout/L_b);
G32=(1-(M*Ts))*Im/Tau;
G33=(1/(2*Tau))*((G31-G32)*Gcom);
G34=((Vin-Vout)/Lt)+(Vout/L_b)-(Im/Tau);
G35=(1-M)*Ts*G34;
G3=G35+G33; %buck conversion small signal
% The transfer function of the storage equipment and the dynamic DC
% machine
Gst=tf([0 RL],[RL*C_b 1]); % the storage RLC
Gd=tf(1,[J B]); %The dynamic DC machine
% Filter Design is estimated using Matlab tool in Filter Design & Analysis
% Tool for eliminating aliasing wave form which are generated by a high
% switching and auxiliary power supply.
Hf=tf(10*pi,[1 10*pi]); %cut off 5rad/s
Hfz=c2d(Hf,Tsz,'zoh');
```

```

%%%%%%%%%%%%%%
%Open loop transfer function of inner loop is
Gip_o=(G3)/(1+(G2*Gst)+(M*Km*Ke*G1*Gd));%Inner loop estimations
Gip=minreal(Gip_o,1e-4);                    % To normalise the order of transfer function
Gipz=c2d(Gip,Tsz,'zoh');
Gipz=minreal(Gipz,1e-4);
% The PI of current loop is designed using command sisotool (Gipz*Hfz)
OPT_i = pidtuneOptions('CrossoverFrequenc',2.27e4,'PhaseMargin',40);
Gciz=pidtune(Gipz*Hfz,'pi',OPT_i);
Kpiag=Gciz.Kp;
Kiiag=Gciz.Ki;
Gci=d2c(Gciz,'zoh');
%%%%%%%%%%%%%%
%Open loop transfer function of outer loop with the PI controller of
% inner loop feedback is
Gwp=(Gci*G3*Ke*Gd*M)/(1+(G2*Gst)+(Gci*G3*Hf)+(M*Km*Ke*G1*Gd));
Gwp=minreal(Gwp,1e-4);
Gwpz=c2d(Gwp,Tsz,'zoh');
OPT_w = pidtuneOptions('CrossoverFrequenc',15,'PhaseMargin',60);
Gcwz=pidtune(Gwpz,'pi',OPT_w);
Kpw=Gcwz.Kp;
Kiw=Gcwz.Ki;
%%%%%%%%%%%%%%

```

D.3.3 MEPT and MPPT controller

Figure D.9 MEPT/MPPT controllers with speed regulator

Figure D.10 Subsystem of the estimation of K1

Figure D.11 Subsystem of the estimation of K2

D.3.4 MPPT algorithm

Figure D.12 MPPT-algorithm with speed regulator

Figure D.13 Data acquisition of MPPT-algorithm and limitation of the duty cycle

According to the flow chart in Figure 4.9, the embedded block of the proposed MPPT-algorithm can be written by the MATLAB script as follows:

```
%Maximum Power Point Tracking (MPPT) by Vorrath Kokaew PhD student at
%University of Southampton
function Speed_ref = MPPT(Wr_new,Tam_new,Du_new)
%
%define variables Wr_new Te_new and Du_new which are used to store the current and rotor
%speed sensors respectively from the previous sampling period
persistent Wr_old;
persistent Tam_old;
persistent Du_old;
persistent Pam_old;
%set the increment constant of rotor speed in coarse-fine tuning
Delta_Wf =3;
Delta_Wc =20;
%initialization commands that are executed only during the first cycle.
if isempty(Wr_old)
    Wr_old=0;
    Tam_old=0;
    Du_old=0;
    Pam_old=0;
    Speed_ref = 0;
else
    %estimate the electric torque duty cycle and rotor speed differential
    Pam=Tam_new*Wr_new;
    dPam=Pam-Pam_old;
    dTam = Tam_new-Tam_old ;
    dWr = (Wr_new-Wr_old);
    dDu = (Du_new-Du_old);
    SlopeP_OverD=((Tam_new*(dWr/dDu))+(Wr_new*(dTam/dDu)));
    % To define boundary Coarse-fine tuning which base on step change of coarse tuning
    Sigma=1;
    %%%%%%%%%%%%%%%
    %Check loop of Perturbation-Observation (P-O)
    %%%%%%%%%%%%%%%
    if abs(dPam)<Sigma;
        if SlopeP_OverD==0;
            Wr_ref=Wr_new;
        elseif SlopeP_OverD>0&&dDu<0
            Wr_ref=Wr_new-Delta_Wf;
        else
            Wr_ref=Wr_new+Delta_Wf;
        end
    else
        if SlopeP_OverD>0&&dDu<0;% Power decision
            Wr_ref = Wr_new - Delta_Wc; %Starting system
        else
            Wr_ref = Wr_new + Delta_Wc;% Scale Delta with different actual speed in power go down
        end
    end
    %store the measures of the electric torque duty cycle and rotor speed for using the next sampling cycle
    Wr_old=Wr_new;
    Tam_old=Tam_new;
    Du_old=Du_new;
    Pam_old=Pam;
    %provide the optimal speed of maximum Power of air motor
    Speed_ref = Wr_ref;
end
```

D.3.5 MPPT fuzzy logic control

Figure D.14 MPPT-fuzzy logic controller with speed regulator

Figure D.15 Data acquisition of MPPT-FLC and limitation of the duty cycle

Figure D.16 Subsystem of the conventional MPPT-FLC when using the inputs of ΔP_{am} and $\Delta \omega_r$

Figure D.17 Subsystem of the conventional MPPT-FLC when using the inputs of $\Delta P_{am}/\Delta \omega_r$ and $\Delta \omega_r$

Figure D.18 Subsystem of the proposed MPPT-FLC

Figure D.19 Subsystem of the dP/dD

Figure D.20 Subsystem of the proposed vector-fuzzy logic

Appendix E System parameter values

Table E.1 Air motor model parameters

Symbol	Description	Value
c_{t1}	Stall torque coefficient	0.189
c_{t2}	Stall torque coefficient	0.021
c_{n1}	Free speed coefficient	-45.3
c_{n2}	Free speed coefficient	681.3
c_{n3}	Free speed coefficient	673.7
c_1	Maximum air flow coefficient	0.7402
c_2	Maximum air flow coefficient	-0.4555

Table E.2 Permanent magnet DC generator

Symbol	Description	Value
r_{ag}	Generator armature resistance	0.484 Ω
L_{ag}	Inductance of the generator	585 μH
K_e	Torque constant	0.0691 N·m/A
K_m	Back EMF constant	0.086 V·sec/rad
J_t	Total moments of inertia	2.20407×10^{-4} kg·m ²
B_t	Viscous friction coefficients	2.98×10^{-4} N·m·s/rad

Appendix E

Table E.3 Buck converter

Symbol	Description	Value
L	Inductance of the buck converter	157 μ H
C_o	Capacitance of the buck converter	11 μ F
R_L	Resistive load of the buck converter	0.25 Ω
I_m	Minimum inductor current	1 A
f	MOSFET switching frequency	10 kHz
f_{sc}	Sampling frequency	20 kHz
$\Delta\omega_{r,max}$	Maximum step speed size coefficient	25 rad/s

Table E.4 Buck-boost converter

Symbol	Description	Value
L	Inductance of the buck-boost converter	33.6 μ H
C_o	Capacitance of the buck –boost converter	1 mF
R_L	Resistive load of the buck-boost converter	1.44 Ω
I_m	Minimum inductor current	0.01 A
f	MOSFET switching frequency	10 kHz
f_{sc}	Sampling frequency	1 kHz
$\Delta\omega_c$	Step size in a P&O method	30 rad/s
$\Delta\omega_f$	Step size in a INC method	5 rad/s

Figure F.3 Subsystem of MEPT/MPPT strategies block

Figure F.4 Subsystem of MPPT-algorithm block

Figure F.5 Subsystem of MPPT-FLC block

Figure F.6 MPPT-FLC

Figure F.7 The derivative air motor power over duty cycle change estimation

F.2 Data acquisitions

Figure F.8 The analog to digital converter of all sensors

Figure F.9 The subsystem of flow sensor estimation

Bibliography

1. Luo, X., Wang, J., Dooner, M. and Clarke, J. (2015) Overview of current development in electrical energy storage technologies and the application potential in power system operation, *Applied Energy*, 137, 511-536.
2. Bullough, C., Gatzen, C., Jakiel, C., Koller, M., Nowi, A. and Zunft, S. (2004) Advanced Adiabatic Compressed Air Energy Storage for the Integration of Wind Energy IN: *Proceedings of the European Wind Energy Conference, EWEC 2004*, London, 22-25 November 2004, 22-25.
3. Lemofouet-Gatsi, S. (2006) *Investigation and optimisation of hybrid electricity storage systems based on compressed air and supercapacitors*, PhD thesis, ÉCOLE POLYTECHNIQUE FÉDÉRALE DE LAUSANNE (EPFL).
4. Barrade, P., Delalay, S. and Rufer, A. (2012) Direct Connection of Supercapacitors to Photovoltaic Panels With On-Off Maximum Power Point Tracking, *IEEE Transactions on Sustainable Energy*, 3 (2), 283-294.
5. Martínez, M., Molina, M.G., Frack, P.F. and Mercado, P.E. (2013) Dynamic Modeling, Simulation and Control of Hybrid Energy Storage System Based on Compressed Air and Supercapacitors, *IEEE (Revista IEEE America Latina) Latin America Transactions*, 11 (1), 466-472.
6. Kokaew, V., Moshrefi-Torbati, M. and Sharkh, S.M. (2011) Simulation of a Solar Powered Air Compressor IN: *2011 10th IEEE Conference on Environment and Electrical Engineering*, Rome, 8-11 May 2011. IEEE, 1-4.
7. Vongmanee, V. and Monyakul, V. (2008) A new concept of small-compressed air energy storage system integrated with induction generator IN: *ICSET 2008. IEEE International Conference on Sustainable Energy Technologies*, Singapore, 24-27 November 2008. IEEE, 866 - 871.
8. Dahraie, V.M., Najafi, H.R., Azizkandi, R. and Nezamdoust, N.M.R. (2012) Study on compressed air energy storage coupled with a wind farm IN: *2012 Second Iranian Conference on Renewable Energy and Distributed Generation*, Tehran, 6-8 March 2012. IEEE, 147 - 152.
9. Perkins, D.E. (2007) Compressed Air Energy Storage (CAES) IN:(ed.) *Encyclopedia of Energy Engineering and Technology - 3 Volume Set (Print Version)*, London: CRC Press,

Bibliography

214-218.

10. Kim, Y.M. (2012) *Novel concepts of compressed air energy storage and thermo-electric energy storage*, PhD thesis, ÉCOLE POLYTECHNIQUE FÉDÉRALE DE LAUSANNE (EPFL).
11. Kim, Y.M. and Daniel, F. (2010) Energy and exergy analysis of a micro-compressed air energy storage and air cycle heating and cooling system, *Energy*, 35 (1), 213-220, Available: <http://linkinghub.elsevier.com/retrieve/pii/S0360544209003971>.
12. Lemofouet, S. and Rufer, A. (2006) A Hybrid Energy Storage System Based on Compressed Air and Supercapacitors With Maximum Efficiency Point Tracking (MEPT), *IEEE Transactions on industrial electronics*, 53 (4), 1105-1115.
13. Kokaew, V., Moshrefi-Torbati, M. and Sharkh, S.M. (2013) Maximum Efficiency or Power Tracking of Stand-Alone Small Scale Compressed Air Energy Storage System, *Energy Procedia*, 42, 387-396.
14. Pan, C.-T. and Juan, Y.-L. (2009) A Novel Sensorless MPPT Controller for a High-Efficiency Microscale Wind Power Generation System, *IEEE Transactions on Energy Conversion*, 25 (1), 207 - 216.
15. Elgendy, M.A., Zahawi, B. and Atkinson, D.J. (2012) Assessment of perturb and observe MPPT algorithm implementation techniques for PV pumping applications, *IEEE Transactions on Sustainable Energy*, 3 (1), 21-33.
16. Kokaew, V., Sharkh, S.M. and Moshrefi-Torbati, M. (2015) Maximum Power Point Tracking of a Small Scale Compressed Air Energy Storage System, *IEEE Transactions on Industrial Electronics*, 63 (2), 985-994.
17. Crampsie, S. (2009) Full charge, *Engineering & Technology*, 4 (6), 52-55.
18. Le, H.T. and Santoso, S. (2013) Operating compressed-air energy storage as dynamic reactive compensator for stabilising wind farms under grid fault conditions, *IET Renewable Power Generation*, 7 (6), 717-726.
19. Farret, F.A. and Simões, M.G. (2006) *Integration of alternative sources of energy*, Hoboken: IEEE Press ; Wiley-Interscience.
20. Cleary, B., Duffy, A., O'Connor, A., Conlon, M. and Fthenakis, V. (2015) Assessing the Economic Benefits of Compressed Air Energy Storage for Mitigating Wind Curtailment,

IEEE Transactions on Sustainable Energy, 6 (3), 1021 - 1028.

21. PacifiCorp (2014) *Update to Energy Storage Screening Study For Integrating Variable Energy Resources within the PacifiCorp System*. Utah: HDR. Available from: <http://www.pacificorp.com/index.html> [19 November 2015].
22. Jaber, J.O., Odeh, S.D. and Probert, S.D. (2003) Integrated PV and gas-turbine system for satisfying peak-demands, *Applied Energy*, 76 (4), 305-319.
23. Bradshaw, D.T. (2000) Pumped hydroelectric storage (PHS) and compressed air energy storage (CAES) IN: *2000 Power Engineering Society Summer Meeting*, Seattle, Washington, 16-20 July 2000. IEEE, 1551-1573.
24. Iov, F. and Blaabjerg, F. (2007) *Advanced Power Converters for Universal and Flexible Power Management in Future*. UNIFLEX-PM, 019794 (SES6).
25. Nejad, H.S., Iqbal, T. and Quaicoe, J. (2014) Compressed Air Energy Storage System Control and Performance Assessment Using Energy Harvested Index, *Electronics*, 3 (1), 1-21.
26. Grazzini, and Milazzo, A. (2012) A Thermodynamic Analysis of Multistage Adiabatic CAES, *Proceedings of the IEEE*, 100 (2), 461-472.
27. Kantharaj, B., Garvey, S. and Pimm, A. (2015) Compressed air energy storage with liquid air capacity extension, *Applied Energy*, 157, 152-164.
28. He, X., Lecomte, R., Nekrassov, A., Delarue, E. and Mercier, E. (2011) Compressed air energy storage multi-stream value assessment on the french energy market IN: *2011 IEEE Trondheim PowerTech*, Trondheim, 19-23 June 2011. IEEE, 1-6.
29. Hartmann, N., Vöhringer, O., Kruck, C. and Eltrop, L. (2012) Simulation and analysis of different adiabatic Compressed Air Energy Storage plant configurations, *Applied Energy*, 93, 541-548.
30. Desrues, T., Ruer, J., Marty, P. and Fourmigué, J.F. (2010) A thermal energy storage process for large scale electric applications, *Applied Thermal Engineering*, 30 (5), 425-432.
31. Jaroslav, H., Mehmet, M., Lilian, K. and Christian, O. (2011) Thermoelectric energy storage based on transcritical CO₂ cycle IN: *Supercritical CO₂ Power Cycle Symposium*, Boulder, Colorado, May 24-25. Supercritical CO₂ Power Cycle Resource Center.
32. SustainX (2012) *SustainX smarter energy storage*. Available from: <http://www.sustainx.com/technology-isothermal-caes.htm> [Accessed 24 November 2015].

Bibliography

33. *LightSail energy*. Available from: <http://www.lightsail.com/> [Accessed 24 November 2015].
34. Proczka, J.J., Muralidharan, K., Villela, D., Simmons, J.H. and Frantziskonis, G. (2013) Guidelines for the pressure and efficient sizing of pressure vessels for compressed air energy storage, *Energy Conversion and Management*, 65 (0), 597-605.
35. Jannelli, E., Minutillo, M., Lavadera, A.L. and Falcucci, G. (2014) A small-scale CAES (compressed air energy storage) system for stand-alone renewable energy power plant for a radio base station: A sizing-design methodology, *Energy*, 78, 313–322.
36. Zhang , C., Yan , B., Wieberdink , J., Li, P.Y., Van de Ven , J.D., Loth, E. and Simon, T.W. (2014) Thermal analysis of a compressor for application to Compressed Air Energy Storage, *Applied Thermal Engineering*, 73 (2), 1402–1411.
37. Garvey, D. (2012) The dynamics of integrated compressed air renewable energy systems, *Renewable Energy*, 39 (1), 271-292.
38. Lund, H. and Salgi, G. (2009) The role of compressed air energy storage (CAES) in future sustainable energy systems, *Energy Conversion and Management*, 50 (5), 1172–1179.
39. Ibrahim, H., Ilinca, A. and Perron, J. (2008) Energy storage systems—Characteristics and comparisons, *Renewable and Sustainable Energy Reviews*, 12 (5), 1221-1250.
40. Boicea, V.A. (2014) Energy Storage Technologies: The Past and the Present, *Proceedings of the IEEE*, 102 (11), 1777 - 1794.
41. Vazquez, S., Lukic, S.M., Galvan, E., Franquelo, L.G. and Carrasco, J.M. (2010) Energy Storage Systems for Transport and Grid Applications, *IEEE Transactions on Industrial Electronics*, 57 (12), 3881-3895.
42. Lawder, M.T., Suthar, B., Northrop, P.W.C., De, S., Hoff, C.M., Leitermann, O., Crow, M.L., Santhanagopalan, S. and Subramanian, V.R. (2014) Battery Energy Storage System (BESS) and Battery Management System (BMS) for Grid-Scale Applications, *Proceedings of the IEEE*, 102 (6), 1014 - 1030.
43. Luki, S.M. and Emadi, A. (2008) Charging ahead, *IEEE Industrial Electronics Magazine*, 2 (4), 22-31.
44. Yu, J. (2015) State-of-Health Monitoring and Prediction of Lithium-Ion Battery Using Probabilistic Indication and State-Space Model, *IEEE Transactions on Instrumentation and Measurement*, 64 (11), 2937-2949.

45. Çengel, Y.A. and Boles, M.A. (2011) *Thermodynamics : an engineering approach*, London: McGraw-Hill.
46. Villela, D., Kasinathan, V.V., Valle, S.D., Alvarez, M., Frantziskonis, G., Deymier, P. and Muralidharan, K. (2010) Compressed-air energy storage systems for stand-alone off-grid photovoltaic modules IN: *2010 35th IEEE Photovoltaic Specialists Conference (PVSC)*, Honolulu, HI, 20-25 June 2010. IEEE, 962 -967.
47. Lasseter, R. (2001) Dynamic models for micro-turbines and fuel cells IN: *Power Engineering Society Summer Meeting, 2001*, Vancouver, 15-19 Jul 2001. IEEE, 761-766 vol.2.
48. Etezadi-Amoli, M. and Choma, K. (2001) Electrical performance characteristics of a new micro-turbine generator IN: *Power Engineering Society Winter Meeting, 2001. IEEE*, Columbus, 28 Jan 2001-01 Feb 2001. IEEE, 736-740 vol.2.
49. Balaghi Enalou, H. and Abbasi Soreshjani, E. (2015) A Detailed Governor-Turbine Model for Heavy-Duty Gas Turbines With a Careful Scrutiny of Governor Features, *IEEE Transactions on Power Systems*, 30 (3), 1435-1441.
50. Nanda, J., Mangla, A. and Suri, S. (2006) Some new findings on automatic generation control of an interconnected hydrothermal system with conventional controllers, *IEEE Transactions on Energy Conversion*, 21 (1), 187-194.
51. Jagatheesan, K. and Anand, B. (2014) Automatic generation control of three area hydro-thermal power systems with electric and mechanical governor IN: *2014 IEEE International Conference on Computational Intelligence and Computing Research (ICCIC)*, Coimbatore, 18-20 Dec. 2014. IEEE, 1-6.
52. Paz, F. and Ordonez, M. (2014) Zero Oscillation and Irradiance Slope Tracking for Photovoltaic MPPT, *IEEE Transactions on Industrial Electronics*, 61 (11), 6138 - 6147.
53. Dalala, Z.M., Zahid, Z.U., Yu, W., Cho, Y. and Lai, J.-S. (2013) Design and Analysis of an MPPT Technique for Small-Scale Wind Energy Conversion Systems, *IEEE Transactions on Energy Conversion*, 28 (3), 756 - 767.
54. Singaravel, M.M.R. and Daniel, S.A. (2015) MPPT With Single DC–DC Converter and Inverter for Grid-Connected Hybrid Wind-Driven PMSG–PV System, *IEEE Transactions on Industrial Electronics*, 62 (8), 4849 - 4857.
55. Elgendy, M.A., Zahawi, B. and Atkinson, D.J. (2013) Assessment of the Incremental

Bibliography

- Conductance Maximum Power Point Tracking Algorithm, *IEEE Transactions on Sustainable Energy*, 4 (1), 108-117.
56. Merabet, A., Islam, A.M. and Beguenane, R. (2014) Predictive speed controller for laboratory size wind turbine experiment system IN: *2014 IEEE 27th Canadian Conference on Electrical and Computer Engineering (CCECE)*, Toronto, ON, 4-7 May 2014. IEEE, 1-6.
57. Xia, C., Geng, Q., Gu, X., Shi, T. and Song, Z. (2012) Input–Output Feedback Linearization and Speed Control of a Surface Permanent-Magnet Synchronous Wind Generator With the Boost-Chopper Converter, *IEEE Transactions on Industrial Electronics*, 59 (9), 3489 - 3500.
58. Koutroulis, E. and Kalaitzakis, K. (2006) Design of a maximum power tracking system for wind-energy-conversion applications, *IEEE Transactions on Industrial Electronics*, 53 (2), 486-494.
59. Raza Kazmi, S.M., Goto, H., Guo, H.-J. and Ichinokura, O. (2011) A Novel Algorithm for Fast and Efficient Speed-Sensorless Maximum Power Point Tracking in Wind Energy Conversion Systems, *IEEE Transactions on Industrial Electronics*, 58 (1), 29 - 36.
60. Mohd Zainuri, M.A.A., Mohd Radzi, M.A., Soh, A.C. and Rahim, N.A. (2014) Development of adaptive perturb and observe-fuzzy control maximum power point tracking for photovoltaic boost dc-dc converter, *IET Renewable Power Generation*, 8 (2), 183-194.
61. Hong, Y., Pham, S.N., Yoo, T., Chae, K., Baek, K.-H. and Kim, Y.S. (2015) Efficient Maximum Power Point Tracking for a Distributed PV System under Rapidly Changing Environmental Conditions, *IEEE Transactions on Power Electronics*, 30 (8), 4209 - 4218.
62. Max, L. (2009) *Design and Control of a DC Collection Grid for a Wind Farm*, PhD thesis, Department of Energy and Environment, Chalmers University of Technology.
63. Kazimierczuk, M.K. (2008) *Pulse-width modulated DC-DC power converters*, Chichester, U.K.: John Wiley & Sons.
64. Vorpérian, V. (1990) Simplified analysis of PWM converters using the PWM switch. Continuous conduction mode, *IEEE Transactions on Aerospace and Electronic Systems*, 26 (3), 490 - 496.
65. Hissem, M., Chériti, A., Sicard, P. and Ba-Razzouk, A. (1997) Application of the Current-Injected Modeling Approach to Quasi-Resonant Converters, *IEEE Transactions on Power Electronics*, 12 (4), 695 - 703.

66. Capel, A. and Ferrante, J.G. (1977) A General Model for Switching Converters, *IEEE Transactions on Aerospace and Electronic Systems*, AES-13 (4), 397-400.
67. Fossard, A.J., Clique, M., Ferrante, J.G. and Capel, A. (1977) A general linear continuous model for design of power conditioning units at fixed and free running frequency IN: *1977 IEEE Power Electronics Specialists Conference*, Palo Alto, CA, USA, 14-16 June 1977. IEEE, 113-124.
68. Kislovski, A.S., Redl, R. and Sokal, N.O. (1991) *Dynamic analysis of switching-mode DC/DC converters*, New York: Van Nostrand Reinhold.
69. Ang, S. and Oliva, A. (2005) *Power-Switching Converters*, London: CRC Press.
70. Kokaew, V., Sharkh, S.M. and Torbati-Moshrefi, M. (2014) A Hybrid Method for Maximum Power Tracking of a Small Scale CAES System IN: *9th IEEE/IET International Symposium on Communication Systems, Networks & Digital Signal Processing, CSNDSP14*, Manchester, 23-25 July 2014. IEEE, 61-66.
71. Kazimierczuk, M.K. (2016) *Pulse-Width Modulated DC-DC Power Converters*, 2nd edition, Chichester, U.K.: John Wiley & Sons.
72. El Khateb, A.H., Rahim, N.A., Selvaraj, J. and Williams, B.W. (2015) DC-to-DC Converter With Low Input Current Ripple for Maximum Photovoltaic Power Extraction, *IEEE Transactions on Industrial Electronics*, 62 (4), 2246-2256.
73. Ogata, K. (1995) *Discrete-Time Control Systems*, New Jersey: Prentice-Hall.
74. Monmasson, E., Idkhajine, L. and Naouar, M.W. (2011) FPGA-based Controllers, *IEEE Industrial Electronics Magazine*, 5 (1), 14-26.
75. Corradini, L., Maksimovic, D., Mattavelli, P. and Zane, R. (2015) *Digital Control of High-Frequency Switched-Mode Power Converters*, New Jersey: John Wiley & Sons.
76. Mason, S.J. (1956) Feedback Theory-Further Properties of Signal Flow Graphs, *Proceedings of the IRE*, 44 (7), 920-926.
77. Nise, N.S. (2015) *Control Systems Engineering*, 7th edition, California State Polytechnic University, Pomona: Wiley.
78. Åström, K.J. and Hägglund, T. (2006) *Advanced PID Control*, ISA-The Instrumentation, Systems, and Automation Society.

Bibliography

79. Parr, J. (1997) Bode Diagram Method IN: Irwin, J.D.(ed.) *The Industrial Electronics Handbook*, CRC Press, 474-489.
80. Ahmed, A., Ran, L. and Bumby, J.R. (2010) New constant electrical power soft-stalling control for small-scale VAWTs, *IEEE Transactions on Energy Conversion*, 25 (4), 1152-1161.
81. Dorf, R.C. and Bishop, R.H. (2011) *Modern Control Systems*, 12th edition, Boston ; London: Pearson.
82. The MathWorks (2003) *SimPowerSystems User's Guide*. Available from: http://www.mathworks.com/help/releases/R13sp2/pdf_doc/phymod/powersys/powersys.pdf [14 December 2015].
83. Computing, M. (n.d) Noise Reduction and Isolation, *Measurement*, 508, 1-10.
84. Li, S.G., Sharhk, S.M., Walsh, F.C. and Zhang, C.N. (2011) Energy and Battery Management of a Plug-In Series Hybrid Electric Vehicle Using Fuzzy Logic, *IEEE Transactions on Vehicular Technology*, 60 (8), 3571 - 3585.
85. Yoo, H., Sul, S.-K., Park, Y. and Jeong, J. (2008) System Integration and Power-Flow Management for a Series Hybrid Electric Vehicle Using Supercapacitors and Batteries, *IEEE Transactions on Industry Applications*, 44 (1), 108-114.
86. Kim, Y., Salvi, A., Stefanopoulou, A.G. and Ersal, T. (2015) Reducing Soot Emissions in a Diesel Series Hybrid Electric Vehicle Using a Power Rate Constraint Map, *IEEE Transactions on Vehicular Technology*, 64 (1), 2-12.
87. Chiu, Y.-J., Yu, T.L. and Chung, Y.-C. (2011) A semi-empirical model for efficiency evaluation of a direct methanol fuel cell, *Journal of Power Sources*, 196 (11), 5053–5063.
88. Zhu, G.-R., Loo, K.H., Lai, Y.M. and Tse, C.K. (2012) Quasi-Maximum Efficiency Point Tracking for Direct Methanol Fuel Cell in DMFC/Supercapacitor Hybrid Energy System, *IEEE Transactions on Energy Conversion*, 27 (3), 561 - 571.
89. Atlas Copco (2014) *Air Motors*. Available from: <http://www.atlascopco.com/airmotors/productrange/selectiontool/> [Accessed 1 October 2011].
90. Hussein, K.H., Muta, I., Hoshino, T. and Osakada, (1995) Maximum photovoltaic power tracking: an algorithm for rapidly changing atmospheric conditions, *IEE Proceedings Generation, Transmission & Distribution*, 142 (1), 59-64.

91. Nabulsi, A.A. and Dhaouadi, R. (2012) Efficiency Optimization of a DSP-Based Standalone PV System Using Fuzzy Logic and Dual-MPPT Control, *IEEE Transactions on Industrial Informatics*, 8 (3), 573-584.
92. Liu, F., Kang, Y., Zhang, Y. and Duan, S. (2008) Comparison of P&O and hill climbing MPPT methods for grid-connected PV converter IN: *2008 3rd IEEE Conference on Industrial Electronics and Applications, ICIEA 2008*, Singapore, 804-807.
93. Salas, V., Olías, E., Barrado, A. and Lázaro, A. (2006) Review of the maximum power point tracking algorithms for stand-alone photovoltaic systems, *Solar energy materials and solar cells*, 90 (11), 1555-1578.
94. Shiau, J.-K., Wei, Y.-C. and Chen, B.-C. (2015) A Study on the Fuzzy-Logic-Based Solar Power MPPT Algorithms Using Different Fuzzy Input Variables, *Algorithms*, 8 (2), 100-127.
95. Sera, D., Mathe, L., Kerekes, T., Spataru, S.V. and Teodorescu, R. (2013) On the perturb-and-observe and incremental conductance mppt methods for PV systems, *IEEE Journal of Photovoltaics*, 3 (3), 1070-1078.
96. Sullivan, C.R., Awerbuch, J.J. and Latham, A.M. (2012) Decrease in Photovoltaic Power Output from Ripple: Simple General Calculation and the Effect of Partial Shading, *IEEE Transactions on Power Electronics*, 28 (2), 740-747.
97. Pinkerton, J.F. (2006) *Thermal and compressed air storage system*. United States Patent , 7086231, August, Available: <http://www.freepatentsonline.com/7086231.html>.
98. Liu, F., Duan, S., Liu, F., Liu, B. and Kang, Y. (2008) A variable step size INC MPPT method for PV systems, *IEEE Transactions on Industrial Electronics*, 55 (7), 2622-2628.
99. Mesemanolis, A., Mademlis, C. and Kioskeridis, I. (2012) High-Efficiency Control for a Wind Energy Conversion System With Induction Generator, *IEEE Transactions on Energy Conversion*, 27 (4), 958-967.
100. Wu, T.-F., Chang, C.-H. and Chen, Y.-K. (2000) A Fuzzy-Logic-Controlled Single-Stage Converter for PV-Powered Lighting System Applications, *IEEE Transactions on Industrial Electronics*, 47 (2), 287-296.
101. Alajmi, B.N., Ahmed, K.H., Finney, S.J. and Williams, B.W. (2013) A maximum power point tracking technique for partially shaded photovoltaic systems in microgrids, *IEEE Transactions on Industrial Electronics*, 60 (4), 1596-1606.

Bibliography

102. Radjai, T., Rahmani, L., Mekhilef, S. and Gaubert, J.P. (2014) Implementation of a modified incremental conductance MPPT algorithm with direct control based on a fuzzy duty cycle change estimator using dSPACE, *Solar Energy*, 110, 325-337.
103. Esham, T. and Chapman, P.L. (2007) Comparison of Photovoltaic Array Maximum Power Point Tracking Techniques, *IEEE Transactions on Energy Conversion*, 22 (2), 439-449.
104. Khateb, A.E., Rahim, N.A. and Uddin, M.N. (2014) Fuzzy Logic Controller Based SEPIC Converter for Maximum Power Point Tracking, *IEEE Transactions on Industry Applications*, 50 (4), 2349-2358.
105. Kadri, R., Gaubert, J.-P. and Champenois, G. (2011) An Improved Maximum Power Point Tracking for Photovoltaic Grid-Connected Inverter Based on Voltage-Oriented Control, *IEEE Transactions on Industrial Electronics*, 58 (1), 66-75.
106. Noman, A.M., Addoweesh, K.E. and Mashaly, H.M. (2013) DSPACE Real-Time Implementation of MPPT-Based FLC Method, *International Journal of Photoenergy*, 2013, p. 11, Available: <http://dx.doi.org/10.1155/2013/549273>.
107. Cheng, P.-C., Peng, B.-R., Liu, Y.-H., Cheng, Y.-S. and Huang, J.-W. (2015) Optimization of a Fuzzy-Logic-Control-Based MPPT Algorithm Using the Particle Swarm Optimization Technique, *Energies*, 8 (6), 5338-5360.
108. Sivanandam, S.N., Sumathi, S. and Deepa, S.N. (2007) *Introduction to fuzzy logic using MATLAB*, Berlin ; New York: Springer.
109. The MathWorks (2015) *Fuzzy Logic Toolbox User's Guide*. Available from: http://cn.mathworks.com/help/pdf_doc/fuzzy/fuzzy.pdf [17 December 2015].