

BIREFRINGENT OPTICAL FIBRES FOR SENSORS

W.A. Gambling,  
Department of Electronics & Information  
Engineering, The University of Southampton,  
Southampton, SO9 5NH, Hampshire,  
United Kingdom

Optical fibres have been developed to a high degree of sophistication for applications in long-distance transmission. Silica-based fibres have attenuations close to the theoretical minimum at wavelengths of 0.85µm, 1.3µm and 1.55µm, while the bandwidth of single-mode fibres can, for all practical purposes, be made almost infinite at wavelengths greater than 1.3µm. Attention is now being given to the design of new types of fibre for application as active and passive fibre components, as sensors and in other new types of optical circuit element.

At Southampton we have been studying four types of structure, involving new materials and new fibre designs. Firstly we have fabricated fibres with zero birefringence<sup>1</sup>, strong linear birefringence<sup>2</sup> and strong circular birefringence<sup>3,4</sup>. Secondly we have made fibres with longitudinal metal components close to the core so that the effect of transverse electric fields can be investigated with a view of producing electrically-activated modulation and switching. Thirdly, a technique has been developed for doping the core of single-mode fibres with rare-earth and transition-metal materials through an extension of the MCVD technique<sup>5</sup>. Fourthly we are looking at the fabrication of fibres with non-silica glasses chosen so as to enhance the Kerr, Faraday and acousto-optical effects.

This paper addresses the first of these topics.

LINEARLY-BIREFRINGENT FIBRES

In many applications it is necessary that the state of polarisation of the modes in a fibre should be strictly controlled. For example it is necessary to control linear polarisation in fibres used in interferometric sensors, in

coherent transmission and for coupling to integrated optical circuits. The state of polarisation in ordinary single-mode fibres is indeterminate. In theory, if a fibre is perfectly constructed so that it is circularly symmetric and laid in a straight line then linearly-polarised light launched at the input will maintain this state along the whole length of the fibre to the output. In practice, however, this does not happen. Firstly, fibres cannot be made as perfect cylindrical structures so that both intrinsic imperfections and external factors such as bends, stress and changes of temperature, will produce some optical azimuthal inhomogeneity. Thus linearly-polarised input light may be decomposed into linearly-polarised, orthogonal, components along the two principal transverse planes and these components will have different phase velocities. Coupling between the two orthogonal components will cause the state of polarisation to vary along the length of the fibre in an unpredictable way.

In order to stabilise the linear polarisation state it is necessary to reduce the amount of coupling between the two mode components and this can be done by introducing strong linear birefringence into the fibre.

One method of doing so<sup>6</sup> is to make the core non-circular in shape so that the refractive-index distributions in the two principal directions are different. Some linearly-birefringent fibres have been made in this way but the refractive-index difference between core and cladding must be large, which means in turn that in order to maintain single-mode propagation the core diameter must be very small. This gives rise to problems of fabrication and jointing of the fibre.

On the other hand coupling to the non-circular active emission spot of a semiconductor laser is eased and a simple butt connection to a laser diode can have a loss<sup>7</sup> of only 1.9dB. The transmission loss of this type of fibre has been reduced to 9dB/km at  $0.85\mu\text{m}$  and 2.5dB/km at  $1.3\mu\text{m}$ .

A more common method of producing linear birefringence is by introducing asymmetric stress over the core of the fibre. The core and cladding remain circular but non-circularly symmetric sectors of very different expansion coefficient are introduced into the substrate region of the fibre. Several methods have been suggested<sup>8</sup> but the

one producing the largest birefringence is the "Bow-Tie" structure<sup>9</sup> in which the shape of the stress-producing sectors has been optimised to produce the maximum degree of birefringence.

The fibres are fabricated by a modification of the MCVD process. After the normal buffer layer has been deposited on the inside of the deposition tube to prevent the diffusion of water into the core and cladding regions, a layer of stress-producing material (for example borosilicate glass) is deposited. The tube rotation is then stopped and some of the stress-producing glass is etched away on opposite sides of the preform tube. The tube is again rotated and layers of cladding, followed by core, glass are deposited in the usual way. The deposited tube is then collapsed into a solid rod preform. During the collapse process the cusp-like regions of stress-producing glass in the tube assume the Bow-Tie shape in the fibre. It is possible to produce a high degree of stress in the preform, even up to the breakdown level of glass thus causing the preform to shatter. Assuming that shattering has not occurred the preform rod is then drawn into a fibre. During the cooling from the drawing temperature of approximately 2000°C to room temperature a high degree of asymmetric stress is once again introduced, due to the different thermal expansion coefficients of the borosilicate sectors and the silica substrate. The fibre, as distinct from the preform, is mechanically strong and is no more likely to break than a conventional fibre.

The degree of birefringence can be assessed easily by looking at the light scattered sideways from the fibre. The two propagating modes run into, and out of, phase at a rate depending on the birefringence so that the scattered light varies periodically in intensity. Beat lengths of less than 1mm (modal birefringence  $B = 6 \times 10^{-4}$ ) can be obtained. The cross-section of a Bow-Tie fibre is shown in Figure 1. The transmission loss is comparable with that of a normal telecommunications fibre.

#### POLARISATION-MAINTAINING FIBRES AND POLARISING FIBRES

As indicated above, the polarisation state in a normal telecommunications fibre is indeterminate. On the other hand a fibre exhibiting a high degree of linear birefringence can operate in two quite distinct ways. In the first of these the two orthogonal modes have a low transmission loss and propagate with roughly equal

attenuation. If an equal amount of light is launched into each of the modes then, because of the different phase constants, the state of polarisation changes periodically along the length of the fibre from linear, to circular, to linear, and so on. On the other hand, if only one of the modes is launched then providing no mode conversion occurs the light will continue to be linearly polarised along the entire length of the fibre. In the presence of strong external distortion then some of the original polarisation will couple into the orthogonal mode and will continue to propagate in that mode to the output.

Another method of operating a Bow-Tie fibre is to introduce attenuation preferentially into one of the modes. Light launched into the low-loss mode will continue in that mode to the end of the fibre. Any light coupled into the orthogonal, i.e. high-loss, mode is attenuated and the output remains linearly polarised despite the mode coupling. Such a fibre is termed a "polarising" fibre because, for any state of input polarisation, only linearly-polarised light emerges.

One method of introducing a preferential loss into one mode is to wind the fibre into a coil. Because of the different refractive-index distributions in the two principal transverse planes, the bending loss edges of the two modes will be at different wavelengths. This effect is illustrated in Figure 2, showing that there is a wavelength region where the attenuation of the two modes is very different. The steepness of the bending edges, their positions and their separation, can be changed by the fabrication conditions, the radius of bend and by microbends<sup>10</sup>. The wavelength region in which polarising action occurs can also be controlled. Extinction ratios of 40dB have been obtained.

#### FIBRES WITH NEGLIGIBLE BIREFRINGENCE AND POLARISATION MODE DISPERSION

Fibres with almost zero internal birefringence can be made by rotating the preform of a conventional fibre about its longitudinal axis<sup>1</sup> during fibre drawing. Spinning rates of several thousand revolutions per minute are possible with the result that any azimuthal inhomogeneities rotate along the length of the fibre with a very short pitch length. Linearly-polarised light is unable to follow this rapid rotation of the birefringence axes with the result that the core appears to be circularly symmetric as far as the propagating mode is concerned. The inherent linear

birefringence, and polarisation mode dispersion, can be reduced to a very low level in this way. External effects, such as bends, pressure, etc., can re-introduce birefringence which is not affected by the spun core, so that spun fibres can be used as sensors. They are particularly useful for measurement of magnetic fields and electric currents by exploiting the Faraday effect. Thus the angle of polarisation is rotated by an amount proportional to the integral of the magnetic field strength along the length of the fibre.

#### CIRCULARLY-BIREFRINGENT FIBRES

It is also possible to produce fibres exhibiting a high degree of circular birefringence. Such fibres can find application in the monitoring of electric current and magnetic fields and also in the control of polarisation in telecommunications.

Probably the simplest method of producing circular birefringence is by twisting a conventional optical fibre about its longitudinal axis. It is then found that the propagation constants of modes polarised in the left-hand, and right-hand, circular directions are different. However, this method is quite limited since the fibre will break at beat lengths shorter than about 10cm. Also, of course, a fibre twisted in this way is difficult to handle experimentally.

A much more effective method is to produce a fibre in which the core does not lie along the longitudinal fibre axis but follows a helical path about it. Such fibres have been developed and fabricated at Southampton<sup>11,12</sup> by inserting a normal MCVD preform, containing core and cladding, into a hole drilled off-axis in a silica rod. Whilst the silica rod containing the offset core/cladding preform is drawn into fibre it is rotated about its longitudinal axis. The core of the resulting fibre is in the form of a tight helix with a quite short pitch length. The degree of circular birefringence is more than an order of magnitude greater than is possible by twisting the fibre and beat lengths down to 5mm (corresponding to a modal birefringence of  $B = 1.3 \times 10^{-4}$ ) and less have been produced.

An interesting consequence of this method of fabrication is that the bend loss of the second, and higher-order, modes is greatly increased compared with that of the fundamental mode so that the fibre can be operated at high

normalised frequencies, e.g.  $V = 25$ , whilst maintaining single-mode operation. The core diameter can thus be much larger than normal. The use of such fibres for measuring magnetic fields and electric currents is now being investigated.

#### CONCLUSION

A wide variety of new optical fibre materials and structures are possible giving rise to many different types of application. Whilst optical-fibre components cannot compete with integrated optical circuits in terms of size, they are flexible, comparatively simple to fabricate, and are compatible with optical fibre transmission lines so avoiding the large coupling loss between fibres and planar optical circuits. In addition to passive devices such as couplers and filters a wide variety of active components can be devised, ranging from optical amplifiers and tunable sources to devices based on non-linear interactions involving soliton propagation, Raman interaction and the like.

#### REFERENCES

1. A.J. Barlow, D.N. Payne, M.R. Hadley and R.J. Mansfield: *Electron. Lett.*, 17, (1981), 725-726.
2. R.D. Birch, D.N. Payne and M.P. Varnham: *Electron. Lett.*, 18, (1982), 1036-1038.
3. M.P. Varnham, R.D. Birch and D.N. Payne: *Proc. European Conference on Optical Communication, Venice, (1985), pp. 135-138.*
4. C.D. Hussey, R.D. Birch and Y. Fujii: *Electron. Lett.*, 22, (1986), 129-130.
5. S.B. Poole, D.N. Payne and M.E. Fermann: *Electron. Lett.*, 21, (1985), 737.
6. R.B. Dyott, J.R. Cozens and D.G. Morris: *Electron. Lett.*, 15, (1979), 380-382.
7. R.B. Dyott: *Private Communication.*
8. D.N. Payne, *Optical Fibre Communication '84, Technical Digest, Paper ME2, Optical Society of America.*
9. M.P. Varnham, D.N. Payne, A.J. Barlow and R.D. Birch: *Journal of Lightwave Technology, LT-1, (1983), 332-339.*
10. M.P. Varnham, D.N. Payne, R.D. Birch and E.J. Tarbox, *Electron. Lett.*, 19, (1983), 246-247.
11. M.P. Varnham, R.D. Birch, D.N. Payne and J.D. Love:

Optical Fibre Communication '86, Technical Digest,  
Paper TUL20, Optical Society of America.